CR-IR346/348CL Service Manual

MT: Machine Troubleshooting

WARNING

This manual is written for International distribution (including distribution in the U.S.) and therefore may contain references to mammography related options.
Mammography functionality for this product is not commercially available in the US, pending FDA Approval.
This functionality must not be activated on US models, the only breast related functionality available in the U.S. is the Specimen Imaging Application.

Control Sheet

Issue date	Revision number	Reason	Pages affected
10/20/2000	00	New release (FM2862)	All pages
12/10/2000	00	Revision (FM2950)	Pages I, II, 1, 6, 8, 10, 13, 15, 16
04/10/2001	01	Previous Chapter C “Error Information/Service Parts” divided and modified (FM2951)	All pages
05/30/2001	02	Revision for software version A02 and GX150 (FM3027)	I, II, 5, 6, 12, 17, 21
08/30/2001	03	Revision for software version A04 (FM3125)	I, II, 5, 18
03/20/2002	04	Revision for software version A07 (FM3297)	I, II, 4, Appx MT A-1, A-34, A-50, A-75, A-98, A-99, A-111, A-112
03/20/2002	04	Changes in pagination (FM3297)	Appx MT A-35–49, A-51–74, A-76-97, A-100-110
07/20/2002	05	Revision for software version A08 (FM3428)	I, II, 4, 11, 19, 23-36, Appx MT A-34, A-39, A-40, A-42, A-43, A-46, A-51, A-52, A-58, A-66, A-94, A-95, A-104, A-105, A-111
07/20/2002	05	Changes in pagination (FM3428)	Appx MT A-35–38, A-41, A-44, A-45, A-47–50, A-53–57, A-59–65, A-67–93, A-96–103, A-106–110, A-112–116
11/30/2002	06	Revision for software version A09 (FM3499)	I-IV, Appx MT A-1, 18, 31–33, 36, 43–45 ,48, 49, 53, 78 , 105, 109
11/30/2002	06	Changes in pagination (FM3499)	Appx MTA-19–30, 34, 35, 37–42, 46, 47, 50–52, 54–77, 79–104, 106–108, 110–116
03/01/2003	07	Revision for software version A10 (FM3634)	I, II, 5, 6, 23, 24, Appx MT A-1, 36, 103, 104
03/01/2003	07	Changes in pagination (FM3634)	Appx MT A-37–49, 105, 106
08/20/2003	08	Revision for software version A11 (FM4009)	I, II, 17, Appx MT A-1, 38, 45, 50, 52–54, 60, 78, 79, 90, 101, 105, 107–114, 118–120
08/20/2003	08	Changes in pagination (FM4009)	Appx MT A-39–44, 46–49, 51, 55–59, 61–77, 80–89, 91–100, 102–104, 106, 115–117
12/10/2003	09	Revision for software version B00 (FM4158)	I, II, 15, 16, Appx MT A-1–3, 5–7, 20, 38, 48, 68–70, 81, 86, 88, 90–98, 124
12/10/2003	09	Changes in pagination (FM4158)	Appx MT A-4, 8–19, 21–37, 39–47, 49–67, 71–80, 82–85, 87, 89, 99–123, 125, 126
02/20/2004	10	A new production tool adopted and layout design changed (FM4220)	All pages

Appendix CL Error Message Table (A00 to A11, V1.0(B) to V3.1(B))

Event	Event Source	Description	Causes	Remedies	Remarks
10900	IIPInputEz	%1 : Registry Value Get/Set Error%n [Key] %2%n [Exp] %3%n %4%n %5	The acquisition/setup key or registration information is abnormal.	Check the registry key.	
10901	IIPInputEz	%1 : Database Connection Error%n [DB] %2%n [Exp] %3%n %4%n %5	This error is attributable to an abnormal character string in Directory.ini, an incorrect database file name, or a damaged database.	Check Directory.ini or database file name.	
10902	IIPInputEz	%1 : Database Data Get/Set Error%n [DB] %2%n [Table] %3%n [Field] %4%n [Exp] %5	This error is attributable to an abnormal database acquisition/setup key or database.	Check the database table/field name.	
10903	IIPInputEz	%1 : Dicom Data Object Get/Set Error%n [Tag] %2%n [Exp] %3%n %4%n %5	The DDO acquisition/setup tag is abnormal.	Check the DDO tag.	
10904	IIPInputEz	%1 : Other Error%n [Procedure] %2%n [ErrorCode] %3%n [Exp] %4%n %5	Unknown error.		
11900	IIPInputEz	%1 : Registry Value Get/Set Error%n [Key] %2%n [Exp] %3%n %4%n %5	The acquisition/setup key or registration information is abnormal.	Check the registry key.	
11900	IIPPortable	%1 : Registry Value Get/Set Error [Key] %2 [Exp] %3 %4 %5	The registry was damaged.	Restart. If the same symptom recurs, reinstall the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
11901	IIPInputEz	%1 : Database Connection Error%n [DB] %2%n [Exp] %3%n %4%n %5	This error is attributable to an abnormal character string in Directory.ini, an incorrect database file name, or a damaged database.	Check Directory.ini or database file name.	
11901	IIPPortable	%1 : Database Connection Error [DB] %2 [Exp] %3 %4 %5	Failed in accessing the image database.	Restart. If the same symptom recurs, reinstall the system and perform “Initialization of image database”. (Image data will be fully deleted.)	
11902	IIPInputEz	%1 : Database Data Get/Set Error%n [DB] %2%n [Table] %3%n [Field] %4%n [Exp] %5	This error is attributable to an abnormal acquisition/setup key or database.	Check the database table/field name.	
11902	IIPPortable	%1 : Database Data Get/Set Error [DB] %2 [Table]%3 [Field]%4 [Exp]%5	Failed in accessing the image database.	Restart. If the same symptom recurs, reinstall the system and perform “Initialization of image database”. (Image data will be fully deleted.)	
11903	IIPInputEz	%1 : Dicom Data Object Get/Set Error%n [Tag] %2%n [Exp] %3%n %4%n %5	The DDO acquisition/setup tag is abnormal.	Check the DDO tag.	
11903	IIPPortable	%1 : DDO Data Get/Set Error [Tag] %2 %3 %4 %5	The DDO file was damaged.	Restart. If the same symptom recurs, reinstall the system and perform “Initialization of image database”. (Image data will be fully deleted.)	
11904	IIPInputEz	%1 : Other Error%n [Procedure] %2%n [ErrorCode] %3%n [Exp] %4%n %5	Unknown error.		
11904	IIPPortable	%1 : Other Error [Procedure] %2 [Error Code]%3 [Exp]%4 %5	Program error or unstable system status.	Check POCKET id Console connection status and restart. If the same symptom recurs, reinstall the system and perform “Initialization of image database”. (Image data will be fully deleted.)	

Event	Event Source	Description	Causes	Remedies	Remarks
12001	FF32	[%1] It failed in CreateFile(%2). %3	Failed in reading a bitmap file. It is conceivable that there was no such file, free disk space was not sufficient or the system was unstable.	Check to see if the filename is correct or available hard disk space is sufficient. Proceed with processing.	"%1": Instance name "%2": Error code "%3": Bitmap file name/Icon file name
12002	FF32	[%1] It failed in CreateFileMapping(%2). %3	Failed in creating a file map object. It is conceivable that available resources were insufficient or the system was unstable.	Proceed with processing.	"%1": Instance name "%2": Error code "%3": Bitmap file name/Icon file name
12003	FF32	[%1] It failed in MapViewOfFile(%2). %3	Failed in mapping a file. It is conceivable that available resources were insufficient or the system was unstable.	Proceed with processing.	"%1": Instance name "%2": Error code "%3": Bitmap file name/Icon file name
12004	FF32	[%1] It failed in CreateCompatibleDC. [%2]	Failed in creating a device context. It is conceivable that available resources were insufficient or the system was unstable.	Proceed with processing.	"%1": Instance name "%2": Error code
12005	FF32	[%1] It failed in CreateDIBSection(%2). %3	Failed in creating a DIB section. It is conceivable that available resources were insufficient or the system was unstable.	Proceed with processing.	"%1": Instance name "%2": Error code "%3": Bitmap file name/Icon file name
12006	FF32	[%1] It failed in OleCreatePictureIndirect(%2). %3	Failed in creating a bitmap picture object. It is conceivable that available resources were insufficient or the system was unstable.	Proceed with processing.	"%1": Instance name "%2": Error code "%3": Bitmap file name/Icon file name
12008	FF32	[%1] It failed in ExtractIon. %2	Failed in reading an icon file. It is conceivable that there was no such file, free disk space was not sufficient or the system was unstable.	Check to see if the filename is correct or available hard disk space is sufficient. Proceed with processing.	"%1": Instance name "%2": Error code
12009	FF32	[%1] It failed in OleCreatePictureIndirect(%2). %3	Failed in creating an picture object for an icon. It is conceivable that available resources were insufficient or the system was unstable.	Proceed with processing.	"%1": Instance name "%2": Error code "%3": Bitmap file name/Icon file name
12011	FF32	[%1] It is a filepath error. %2	The file path was illegal.	Check to see if the filename is correct. Proceed with processing.	"%1": Instance name "%2": Error code
12012	FF32	[%1] Memory allocation failed(%2). %3	Failed in acquiring memory. It is conceivable that available resources were insufficient or the system was unstable.	Check to see if the filename is correct. Proceed with processing.	"%1": Instance name "%2": Error code "%3": Bitmap file name/Icon file name

Event	Event Source	Description	Causes	Remedies	Remarks
12900	IIPInputEz	%1 : Registry Value Get/Set Error%n [Key] %2%n [Exp] %3%n %4%n %5	The acquisition/setup key or registration information is abnormal.	Check the registry key.	
12900	IIPPortable	%1 : Registry Value Get/ Set Error [Key] %2 [Exp] %3 %4 %5	A registry was damaged.	Restart. If the same symptom recurs, reinstall the system.	
12901	IIPInputEz	%1 : Database Connection Error%n [DB] %2%n [Exp] %3%n %4%n %5	This error is attributable to an abnormal character string in Directory.ini, an incorrect database file name, or a damaged database.	Check Directory.ini or database file name.	
12901	IIPPortable	%1 : Database Connection Error [DB] %2 [Exp] %3 %4 %5	Failed in accessing the image database.	Restart. If the same symptom recurs, reinstall the system and perform “Initialization of image database”. (Image data will be fully deleted.)	
12902	IIPInputEz	%1 : Database Data Get/Set Error%n [DB] %2%n [Table] %3%n [Field] %4%n [Exp] %5	This error is attributable to an abnormal acquisition/setup key or database.	Check the database table/field name.	
12902	IIPPortable	%1 : Database Data Get/ Set Error [DB] %2 [Table]%3 [Field]%4 [Exp]%5	Failed in accessing the image database.	Restart. If the same symptom recurs, reinstall the system and perform “Initialization of image database”. (Image data will be fully deleted.)	
12903	IIPInputEz	%1 : Dicom Data Object Get/Set Error%n [Tag] %2%n [Exp] %3%n %4%n %5	The DDO acquisition/setup tag is abnormal.	Check the DDO tag.	
12903	IIPPortable	%1 : DDO Data Get/Set Error [Tag] %2 %3 %4 %5	The DDO file was damaged.	Restart. If the same symptom recurs, reinstall the system and perform “Initialization of image database”. (Image data will be fully deleted.)	

Event	Event Source	Description	Causes	Remedies	Remarks
12904	IIPInputEz	%1 : Unknown Error%n [Procedure] %2%n [ErrorCode] %3%n [Exp] %4%n %5	Unknown error.	Check the POCKET id Console connection status.	
12904	IIPPortable	%1 : Other Error [Procedure] %2 [Error Code]%3 [Exp]%4 %5	A general-purpose information event log.	Check the POCKET id Console connection status.	
13000	FFIdDepartSelect	It failed that [%1] connects departDB	The requesting department database was not found in the path indicated by the connection character string. The requesting department table did not exist.	Reinstall.	
13000	FFIdFilmMark	It failed that [%1] gets the FontName	The “Font” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13000	FFIdMenuChange	It failed that [%1] gets the FontName	The “Font” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13000	FFIdMenuItem	It failed that [%1] gets the FontName	The “Font” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13000	FFIdParamedicSelect	It failed that [%1] connects paramedicDB	The technician’s database was not found in the pass indicated by the connection character string or the technician's table did not exist.	Reinstall.	
13000	FFIdPatInfoInput	It failed that [%1] gets the ID# caption	The “LangStrDB” key was not found in Directory.ini or the ID “30700” was not registered in the character string database.	Reinstall.	
13001	FF32LIB	Image Database Access Failure. ErrNo:%1 NativeErrNo:%2 SQLState:%3 Source:%4 Description:%5	The image database was not successfully accessed (ADO error).	Restart.	
13001	FFCustomMsgBox	MessageBox DataBase Connection Error.	The message database was not successfully connected. It is conceivable that the database did not exist or that the specified data source name was invalid.	Reinstall or check whether the message database exists and the contents of Directory.ini are correct.	
13001	FFCustomMsgBox	MessageBox DataBase Connection Error. [%1]	The connection to the message database was not successfully established. The database did not exist or the specified data source name was invalid.	Perform a reinstallation or check whether the message database exists and the contents of Directory.ini are correct.	
13001	FFIdDepartSelect	It failed that [%1] gets the DepartLabel caption	The “LangStrDB” key was not found in Directory.ini or the ID “30800” was not registered in the character string database.	Reinstall.	
13001	FFIdFilmMark	It failed that [%1] gets the FontSize	The “FontSizeSS”/“FontSizeS”/ “FontSizeM”/“FontSizeL”/“FontSizeLL” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	

Event	Event Source	Description	Causes	Remedies	Remarks
13001	FFIdMenuChange	It failed that [%1] gets the FontSize	The “FontSizeSS”/“FontSizeS”/ “FontSizeM”/“FontSizeL”/“FontSizeLL” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13001	FFIdMenuItem	It failed that [%1] gets the FontSize	The “FontSizeSS”/“FontSizeS”/ “FontSizeM”/“FontSizeL”/“FontSizeLL” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13001	FFIdParamedicSelect	It failed that [%1] gets the ParamedicLabel caption	The “LangStrDB” key was not found in Directory.ini or the ID “30800” was not registered in the character string database.	Reinstall.	
13001	FFIdPatInfoInput	It failed that [%1] gets the EXAM# caption	The “LangStrDB” key was not found in Directory.ini or the ID “30701” was not registered in the character string database.	Reinstall.	
13001	FFIipInput	It failed that [%1] gets the FontName	The “Font” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13001	FFImageDBCTL	Image Database Access Error. ErroNo:%1 Source:%2 Description:%3	The image database was not successfully accessed (ADO error).	Restart.	
13001	FFImageDBCTL	Image Database Access Failure. ErrNo:%1 NativeErrNo:%2 SQLState:%3 Source:%4 Description:%5	The image database was not successfully accessed (ADO error).	Restart.	
13001	FFIpcInf	[%1] It failed in CoInitialize(%2).	Initialization was unsuccessful. It is conceivable that the system was unstable.	Restart.	“%1”: Instance name “%2”: Error code
13001	FFLogFile	[%1] It failed in CreateFile(%2).	Log file creation was unsuccessful. The problem might have been caused, for instance, by an invalid filename selection, inadequate disk space, or system instability.	Check for a free disk space or restart.	“%1”: Instance name “%2”: Error code “%3”: File name/mutex name
13001	FF32LIB	FF32lib Database Access Failure.%nFunction:%1 Command:%2%nErrNo:%3 NativeErrNo:%4 SQLState:%5%n Source:%6%n Description:%7	Failed in accessing the database.	Restart.	
13002	FFCustomMsgBox	MessageBox Data Get Error.	The specified message was not databased. It is conceivable that the message was not registered in the message database or that the specified ID was incorrect (program defect).	Perform a reinstallation or replace the message database with the latest one.	
13002	FFIdDepartSelect	It failed that [%1] gets the FontName	The “Font” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	

Event	Event Source	Description	Causes	Remedies	Remarks
13002	FFIdFilmMark	It failed that [%1] gets the Clear Caption	The “LangStrDB” key was not found in Directory.ini or the ID “34800” was not registered in the character string database.	Reinstall.	
13002	FFIdMcrControl	Driver initialize error[%1]	The magnetic card was not connected.	Connect the magnetic card reader.	
13002	FFIdMenuChange	It failed that [%1] gets the multibyte flag	The “Multibyte” key was not found in the registry.	Reinstall.	
13002	FFIdMenuItem	It failed that [%1] gets the multibyte flag	The “Multibyte” key was not found in the registry.	Reinstall.	
13002	FFIdParamedicSelect	It failed that [%1] gets the FontName	The “Font” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13002	FFIdPatInfoInput	It failed that [%1] gets the PatNameSbcs caption	The “LangStrDB” key was not found in Directory.ini or the ID “30702” was not registered in the character string database.	Reinstall.	
13002	FFIdRuMainControl	Driver initialize error[%1]	The magnetic card reader was not connected.	There are no operational problems.	
13002	FFIipInput	It failed that [%1] gets the FontSize	The “FontSizeSS”/“FontSizeS”/ “FontSizeM”/“FontSizeL”/“FontSizeLL” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13002	FFImageDBCTL	[%1] %2	The image database was not successfully accessed.	Restart.	
13002	FFImageDBCTL	Image Database Access Failure. InstanceName[%1]%2	The image database was not successfully accessed.	Restart.	
13002	FFIpcInf	[%1] It failed in CoCreateInstance(%2). LogFileCom create failure.	A log save control was not successfully created. The problem is attributable to system instability or unregistered control.	Restart. If the same symptom recurs, perform a reinstallation.	“%1”: Instance name “%2”: Error code
13002	FFLogFile	[%1] It failed in CreateFileMapping(%2).	File map object creation was unsuccessful. The problem is attributable to resource inadequacy or system instability.	Restart.	“%1”: Instance name “%2”: Error code
13002	FF32LIB	FF32lib Database Access Failure. InstanceName[%1] %n%2%nFunction:%3 Command:%4	Failed in accessing the database.	Restart.	
13003	FF32LIB	Image Database Access Failure. InstanceName[%1]%2 %3	The image database was not successfully accessed.	Restart.	
13003	FFCustomMsgBox	Same MessageBox Existed. [%1]	The specified message box is already open.	Close the message box.	
13003	FFIdDepartSelect	It failed that [%1] gets the FontSize	The “FontSizeSS”/“FontSizeS”/ “FontSizeM”/“FontSizeL”/“FontSizeLL” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	

Event	Event Source	Description	Causes	Remedies	Remarks
13003	FFIdFilmMark	It failed that [%1] gets the connection string of strDB	The “LangStrDB” key was not found in Directory.ini.	Reinstall.	
13003	FFIdMenuChange	[%1] failed in the initialization for the display group data acquisition	The “DisplayDataDB” key was not found in Directory.ini or the connection character string was not properly registered in the display group table.	Reinstall.	
13003	FFIdMenuItem	Image Folder Path Get Error	The “Bitmap” key was not found in Directory.ini.	Reinstall.	
13003	FFIdParamedicSelect	It failed that [%1] gets the FontSize	The “FontSizeSS”/“FontSizeS”/ “FontSizeM”/“FontSizeL”/“FontSizeLL” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13003	FFIdPatInfoInput	It failed that [%1] gets the PatNameDbcs caption	The “LangStrDB” key was not found in Directory.ini or the ID “30703” was not registered in the character string database.	Reinstall.	
13003	FFIipInput	It failed that [%1] gets the multibyte flag	The “Multibyte” key was not found in the registry.	Reinstall.	
13003	FFImageDBCTL	[%1] %2 %3	The image database was not successfully accessed.	Restart.	
13003	FFImageDBCTL	Image Database Access Failure. InstanceName[%1]%2%3	The image database was not successfully accessed.	Restart.	
13003	FFIpcInf	[%1] Memory allocation failed.	Memory allocation was not successfully achieved for main thread creation. The problem is attributable to resource inadequacy or system instability.	Restart.	“%1”: Instance name
13003	FFLogFile	[%1] It failed in MapViewOfFile(%2).	File mapping was unsuccessful. The problem is attributable to resource inadequacy or system instability.	Restart.	“%1”: Instance name “%2”: Error code
13003	FF32LIB	FF32lib Database Access Failure. InstanceName[%1]%n%2 %n%3	Failed in accessing the database.	Restart.	“%1”: Instance name “%2”: Error code
13004	FFCustomMsgBox	MessageBox Dialog Create Error. [%1]	The message box could not be created. This error occurred due to insufficient resources or system instability.	Restart.	
13004	FFIdDepartSelect	It failed that [%1] gets the depart field list	The “FieldDepartList” key was not found in the system setup database.	Reinstall.	
13004	FFIdFilmMark	It failed that [%1] connects to strDB	The connection character string was not properly registered for the “LangStrDB” key in Directory.ini.	Reinstall.	
13004	FFIdMcrControl	Magnetic card data acquisition error[%1]	The magnetic card was found damaged.	Have a normal magnetic card be read.	

Event	Event Source	Description	Causes	Remedies	Remarks
13004	FFIdMenuChange	[%1] failed in the display group data acquisition	The “DisplayDataDB” key was not found in Directory.ini or the connection character string was not properly registered in the display group table.	Reinstall.	
13004	FFIdMenuItem	[Miss]Image Get Error	Id_MissExposure_I.bmp was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13004	FFIdParamedicSelect	It failed that [%1] gets the paramedic field list	The “FieldParamedicList” key was not found in the system setup database.	Reinstall.	
13004	FFIdPatInfoInput	It failed that [%1] gets the Sex caption	The “LangStrDB” key was not found in Directory.ini or the ID “30704” was not registered in the character string database.	Reinstall.	
13004	FFIdRuMainControl	Magnetic card data acquisition error[%1]	The magnetic card is damaged.	Have a normal magnetic card be read.	
13004	FFIipInput	It failed that [%1] gets the connection string of STR DB	The “LangStrDB” key was not found in Directory.ini.	Reinstall.	
13004	FFIpcInf	[%1] A pipe has already been made(%2).	An attempt was made to duplicate a pipe.	There are no operational problems.	“%1”: Instance name “%2”: Error code
13004	FFLogFile	[%1] It failed in CreateMutex(%2). %3	Mutex creation was unsuccessful. The problem is attributable to resource inadequacy or system instability.	Restart.	“%1”: Instance name “%2”: Error code “%3”: file name/mutex name
13005	FFCustomMsgBox	MessageBox Dialog Show Error. [%1]	The message box could not be opened. This error occurred due to insufficient resources or system instability.	Restart.	
13005	FFIdConnectionWatchEX	Recv Error Message [%1] Error Code [%2]	The connection to the RU was closed or a connection error occurred.	Restore the RU connection to normal.	
13005	FFIdFilmMark	It failed that [%1] gets the connection string of FilmMarkDB	The “FilmMarkDB” key was not found in Directory.ini.	Reinstall.	
13005	FFIdMcrControl	Magnetic card variation error[%1]	The magnetic card was not of the specified type.	Have the specified type of magnetic card be read.	
13005	FFIdMenuChange	[%1] failed in the liberating processing of the display group data acquisition	The connection to the display group table was not successfully closed.	Restart. If the same symptom recurs, reinstall.	
13005	FFIdPatInfoInput	It failed that [%1] gets the SexMale caption	The “LangStrDB” key was not found in Directory.ini or the ID “30705” was not registered in the character string database.	Reinstall.	
13005	FFIdRuMainControl	Magnetic card variation error[%1]	The employed magnetic card type was different than specified.	Have the specified type of magnetic card be read.	
13005	FFIdRuMainControl	Recv error[%1]	The connection to the RU was closed or an error occurred in the connection.	Check the connection to the RU.	

Event	Event Source	Description	Causes	Remedies	Remarks
13005	FFIdRUMainControlEx	Recv Error Message [%1] Error Code [%2]	The connection to the RU was closed or a connection error occurred.	Restore the RU connection to normal.	
13005	FFIipInput	It failed that [%1] connects to STR DB	The connection character string was not properly registered for the “LangStrDB” key in Directory.ini.	Reinstall.	
13005	FFIpcInf	[%1] It failed in _beginthread(%2).	Main thread creation was not successful. The problem is attributable to resource inadequacy or system instability.	Restart.	“%1”: Instance name “%2”: Error code
13006	FFCustomMsgBox	List For Modeless MessageBox Management New Error.	The modeless message box management table was not successfully created. The problem is attributable to resource inadequacy or system instability.	Restart.	
13006	FFCustomMsgBox	List For Modeless MessageBox Management New Error. [%1]	The modeless message box management table was not successfully created. This error occurred due to insufficient resources or system instability.	Restart.	
13006	FFIdFilmMark	It failed that [%1] connects to FilmMarkDB	The connection character string was not properly registered for the “FilmMarkDB” key in Directory.ini.	Reinstall.	
13006	FFIdMcrControl	Magnetic card variation check error[%1]	The card format was incorrect or an attempt was made to read an unspecified hospital card.	Have the specified hospital card be read.	
13006	FFIdMenuChange	[%1] Failed in the initialization for the display menu data acquisition	The “DisplayDataDB” key was not found in Directory.ini.	Reinstall.	
13006	FFIdPatInfoInput	It failed that [%1] gets the SexFemale caption	The “LangStrDB” key was not found in Directory.ini or the ID “30706” was not registered in the character string database.	Reinstall.	
13006	FFIdRuMainControl	Magnetic card variation check error[%1]	The card format was wrong or an attempt was made to cause an unspecified hospital card to be read.	Have the specified hospital card be read.	
13006	FFIipInput	It failed that [%1] gets the connection string of SYS DB	The “SysConfigDB“ key was not found in Directory.ini.	Reinstall.	
13006	FFIpcInf	[%1] It failed in WaitNamedPipe(%2).	The specified pipe was not successfully connected. It is conceivable that the pipe was not created or was unconnectable or that the system was unstable.	Make a change so as to let the program initiate a retransmission, or restart.	“%1”: Instance name “%2”: Error code
13007	FFIdDepartSelect	It failed that [%1] gets the connection string of strDB	The “LangStrDB” key was not found in Directory.ini.	Reinstall.	
13007	FFIdMcrControl	DataFormatDB access error[%1]	“McrDataFormatDB” key was not found in Directory.ini or McrDataFormat.mdb did not exist in the specified path.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13007	FFIdMenuChange	[%1] failed in the acquisition of number of records of display menu data	The connection character string was not properly registered in the display group table.	Reinstall.	
13007	FFIdParamedicSelect	It failed that [%1] gets the connection string of strDB	The “LangStrDB” key was not found in Directory.ini.	Reinstall.	
13007	FFIdPatInfoInput	It failed that [%1] gets the SexOther caption	The “LangStrDB” key was not found in Directory.ini or the ID “30707” was not registered in the character string database.	Reinstall.	
13007	FFIdRuMainControl	DataFormatDB access error[%1]	The “McrDataFormatDB” key was not found in Directory.ini or McrDataFormat. mdb did not exist in the path.	Reinstall.	
13007	FFIipInput	It failed that [%1] connects to SYS DB	The connection character string was not properly registered for the “SysConfigDB“ key in Directory.ini.	Reinstall.	
13007	FFIpcInf	[%1] It failed in CreateFile(%2).	The specified pipe was not successfully connected. It is conceivable that the pipe was closed or that the system was unstable.	The problem is attributable to the program. Check the program or restart.	“%1”: Instance name “%2”: Error code
13007	FFIpcInf	[%1] It failed in CreateFile(%2). [Send Msg:%3]	The connection to the specified pipe was not established. This error occurred because the pipe was closed or the system was unstable.	The problem is attributable to the program. Check the program or restart.	
13008	FFCustomMsgBox	An exception error occurred. [%1] %2	An exception occurred (the system was unstable).	Restart.	
13008	FFIdConnectionWatch Ex	Message Send Error [%1] Error Code [%2]	A connection error occurred.	Restore the RU connection to normal.	
13008	FFIdDepartSelect	It failed that [%1] connects to strDB	The connection character string was not properly registered for the “LangStrDB” key in Directory.ini.	Reinstall.	
13008	FFIdFilmMark	It failed that [%1] get the folder path to Bitmap	The “Bitmap” key was not found in Directory.ini.	Reinstall.	
13008	FFIdMenuChange	[%1] failed in the display menu data acquisition	Not properly registered to the display group table.	Reinstall.	
13008	FFIdParamedicSelect	It failed that [%1] connects to strDB	The connection character string was not properly registered for the “LangStrDB” key in Directory.ini.	Reinstall.	
13008	FFIdPatInfoInput	It failed that [%1] gets the DateOfBirth caption	The “LangStrDB” key was not found in Directory.ini or the ID “30708” was not registered in the character string database.	Reinstall.	
13008	FFIdRuMainControl	DataFormatDB close error[%1]	The database was faulty.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13008	FFIdRUMainControlEx	Message Send Error [%1] WSAGetLastError = [%2]	A connection error occurred.	Restore the RU connection to normal.	
13008	FFIipInput	It failed that [%1] calls the CUSTOM MESSAGE BOX (%2)	The message database did not exist or the program was faulty.	Reinstall.	
13008	FFIpcInf	[%1] It failed in WriteFile(%2).	A message was not successfully transmitted. It is conceivable that the pipe was closed or that the system was unstable.	The problem is attributable to the program. Check the program or restart.	"%1": Instance name "%2": Error code
13008	FFIpcInf	[%1] It failed in WriteFile(%2). [Send Msg:%3]	The message transmission was not successfully completed. This error occurred due to a closed pipe or system instability.	It is conceivable that the program may be faulty. Check the program or restart.	
13009	FFCustomMsgBox	Common function error occurred. [%1] %2	The common function returned an error.	Restart.	
13009	FFIdConnectionWatch	LogFile Name Make error(%1).%n[%2]	The "Log" key was not found in Directory. ini.	Reinstall.	
13009	FFIdConnectionWatchEx	Log File Name Make Error[%1] Error Code [%2]	The "Log" key was not found in Directory. ini.	Register the "Log" key in Directory.ini.	
13009	FFIdDepartSelect	It failed that [%1] gets the connection string of sysDB	The "SysConfigDB" key was not found in Directory.ini.	Reinstall.	
13009	FFIdFilmMark	It failed that [%1] get the bitmap to Previous Page	Id_UpScroll_U.bmp/"Id_UpScroll_D.bmp"/ "Id_UpScroll_X.bmp" was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13009	FFIdMcrControl	DataFormatDB close error[%1]	The database was faulty.	Reinstall.	
13009	FFIdMenuChange	[%1] Failed in the liberating processing of the display menu data acquisition	The connection to the display menu table was not successfully closed.	Restart. If the problem frequently occurs, initialize the image database.	
13009	FFIdParamedicSelect	Is failed that [%1] gets the connection string of sysDB	The "SysConfigDB" key was not found in Directory.ini.	Reinstall.	
13009	FFIdPatInfoInput	It failed that [%1] gets the FontName	The "Font" key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13009	FFIdRuMainControl	LogFile Name Make error[%1]	The "Log" key was not found in Directory. ini.	Reinstall.	
13009	FFIdRUMainControlEx	Log File Name Make Error[%1] Error Code [%2]	The "Log" key was not found in Directory. ini.	Register the "Log" key in Directory.ini.	

Event	Event Source	Description	Causes	Remedies	Remarks
13009	FFIpcInf	[%1] Memory allocation failed.	Memory allocation was not successfully achieved for reception thread creation. The problem is attributable to resource inadequacy or system instability.	Restart.	"%1": Instance name "%2": Error code
13010	FFIdConnectionWatch	DB Connect error(%1).%n[%2]	The "SysConfigDB" key was not found in Directory.ini or SysConfig.mdb did not exist in the path.	Reinstall.	
13010	FFIdConnectionWatchEx	DB Connect Error [%1] Error Code [%2]	"SysConfigDB" key was not found in Directory.ini or SysConfig.mdb did not exist in the specified path.	Properly register the "SysConfigDB" key in Directory.ini.	
13010	FFIdDepartSelect	It failed that [%1] connects to sysDB	The connection character string was not properly registered for the "SysConfigDB" key in Directory.ini.	Reinstall.	
13010	FFIdFilmMark	It failed that [%1] get the bitmap to Next Page	Id_DownScroll_U.bmp/"Id_DownScroll_D.bmp"/"Id_DownScroll_X.bmp" was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13010	FFIdMcrControl	Patient info data error[%1] %n(%2)	The patient information contained in the magnetic card was incorrect.	Check the data contained in the magnetic card.	
13010	FFIdMenuChange	[%1] Failed in the termination of the display menu data acquisition	The connection to the display menu table was not successfully closed.	Restart. If the problem frequently occurs, initialize the image database.	
13010	FFIdParamedicSelect	It failed that [%1] connects to sysDB	The connection character string was not properly registered for the "SysConfigDB" key in Directory.ini.	Reinstall.	
13010	FFIdPatInfoInput	It failed that [%1] gets the FontSize	The "FontSizeSS"/"FontSizeS"/"FontSizeM"/"FontSizeL"/"FontSizeLL" key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13010	FFIdRuMainControl	DB Connect error[%1]	The "SysConfigDB" key was not found in Directory.ini or SysConfig.mdb did not exist in the path.	Reinstall.	
13010	FFIdRuMainControl	Patient info data error[%1]	The patient information carried by the magnetic card was incorrect.	Check the data stored in the magnetic card.	
13010	FFIdRUMainControlEx	DB Connect Error [%1] Error Code [%2]	"SysConfigDB" key was not found in Directory.ini or SysConfig.mdb did not exist in the specified path.	Properly register the "SysConfigDB" key in Directory.ini.	
13010	FFIpcInf	[%1] It failed in CreateNamedPipe(%2).	Pipe creation was not successful. It is conceivable that the system was unstable.	Restart.	"%1": Instance name "%2": Error code
13010	FFIpcInf	[%1] It failed in CreateNamedPipe(%2). [Pipe:%3]	The pipe was not successfully created. The system was unstable.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
13011	FFIdConnectionWatch	DB Read error(%1).%n[%2]	The “EchoInterval”, “ComBreakTimeout1” “PartFrupStatus”, or “EnableLog FrupConnect” key was not found in SysConfig.mdb.	Reinstall.	
13011	FFIdConnectionWatchEx	DB Read error[%1] Error Code [%2]	The “EchoInterval”, “ComBreakTimeout1” “PortFrupStatus”, or “EnableLogFrupConnect” key was not found in SysConfig.mdb.	Ensure that the “EchoInterval”, “ComBreakTimeout1”, “PortFrupStatus”, and “EnableLogFrupConnect” keys are all registered in SysConfig.mdb.	
13011	FFIdDepartSelect	It's failed that [%1] gets the connection string of departDB	DepartDB did not exist in Directory.ini.	Reinstall.	
13011	FFIdFilmMark	It failed that [%1] get the bitmap to Clear	Id_Clear_U.bmp/“Id_Clear_D.bmp”/ “Id_Clear_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13011	FFIdParamedicSelect	It failed that [%1] gets the connection string of paramedicDB	ParamedicDB did not exist in Directory.ini.	Reinstall.	
13011	FFIdPatInfoInput	It failed that [%1] gets the max length of ID#	The “IdLength” key was not found in the system setup database.	Reinstall.	
13011	FFIdRuMainControl	DB Read error[%1]	The “PortFrupMain”, “AckTimeout”, or “EnableLogFrupMain” key was not found in SysConfig.mdb.	Reinstall.	
13011	FFIdRUMainControlEx	DB Read error[%1] Error Code [%2]	The “PortFrupMain”, “AckTimeout”, or “EnableLogFrupMain” key was not found in SysConfig.mdb.	Ensure that the “PortFrupMain”, “AckTimeout”, and “EnableLogFrupMain” keys are all registered in SysConfig.mdb.	
13011	FFIipInput	It failed that [%1] gets the window size	The “ScallHight”/“ScallWidth” key was not registered in the registry.	Reinstall.	
13011	FFIpcInf	[%1] It failed in ConnectNamedPipe(%2).	Pipe connection was not successfully awaited. It is conceivable that the system was unstable.	Restart.	“%1”: Instance name “%2”: Error code
13011	FFIpcInf	[%1] It failed in ConnectNamedPipe(%2). [Pipe:%3]	The pipe connection request was not successfully enqueued. The system was unstable.	Restart.	
13011	FFCustomMsgBox	ActiveX Data Objects(ADO) Error. ErrorNo:%1 Source:%2 Description:%3	An ADO error was detected.	Restart.	
13012	FFIdPatInfoInput	It failed that [%1] gets the max length of EXAM#	The “ExaminationNoLength” key was not found in the system setup database.	Reinstall.	
13012	FFIpcInf	[%1] It failed in _beginthread(%2).	Reception thread creation was not successful. The problem is attributable to resource inadequacy or system instability.	Restart.	“%1”: Instance name “%2”: Error code

Event	Event Source	Description	Causes	Remedies	Remarks
13012	FFIpcInf	[%1] It failed in _beginthread(%2). [Pipe:%3]	The reception thread was not successfully created. This error occurred due to insufficient resources or system instability.	Restart.	
13013	FFIdMenuChange	It failed that [%1] get the folder path to Bitmap	The “Bitmap” key was not found in Directory.ini.	Reinstall.	
13013	FFIdPatInfoInput	It failed that [%1] gets the padding type of ID#	The “IdPadding” key was not found in the system setup database.	Reinstall.	
13013	FFIdRUMainControlEx	Configration error[%1] WSAGetLastError = [%2]	SysConfig.mdb was abnormal.		
13013	FFIpcInf	[%1] It failed in ReadFile(%2).	Message reception was not successful. It is conceivable that the system was unstable.	Restart.	“%1”: Instance name “%2”: Error code
13013	FFIpcInf	[%1] It failed in ReadFile(%2). [Pipe:%3]	The message reception was not successfully completed. The system was unstable.	Restart.	
13014	FFIdConnectionWatch	Ack Messeage Time Out(%1).%n[%2]	The connection to the RU was closed or an error occurred in the connection.	Check the connection to the RU.	
13014	FFIdConnectionWatchEx	Ack Message Time Out[%1] Error Code [%2]	The connection to the RU was closed or a connection error occurred.	Restore the RU connection to normal.	
13014	FFIdMenuChange	It failed that [%1] get the bitmap to Previous Page	Id_PrevPage_U.bmp/“Id_PrevPage_D.bmp”/“Id _PrevPage_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13014	FFIdPatInfoInput	It failed that [%1] gets the padding type of EXAM#	The “ExaminationNoPadding” key was not found in the system setup database.	Reinstall.	
13014	FFIdRuMainControl	Ack Messeage Time Out[%1]	The connection to the RU was closed or an error occurred in the connection.	Check the connection to the RU.	
13014	FFIdRUMainControlEx	Ack Message Time Out[%1] WSAGetLastError = [%2]	The connection to the RU was closed or a connection error occurred.	Restore the RU connection to normal.	
13014	FFIipInput	[%1] No RU Used	Although the FRUP option was selected, NetConfig did not have any RU connection setting. There was a conflict between the option setup and Config setup.	Check the settings.	
13014	FFIpcInf	[%1] It is a parameter error.	An illegal parameter was encountered (program defect).		“%1”: Instance name
13015	FFIdMenuChange	It failed that [%1] get the bitmap to Next Page	Id_NextPage_U.bmp/“Id_NextPage_D.bmp”/“Id _NextPage_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13015	FFIdPatInfoInput	It failed that [%1] gets the multibyte flag	The “Multibyte” key was not found in the registry.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13015	FFIpcInf	[%1] Exception Information. %2	An exception occurred (the system was unstable).	Restart.	
13016	FFIdPatInfoInput	It failed that [%1] gets the date format type	The “DateFormat” key was not found in the system setup database.	Reinstall.	
13017	FFIdConnectionWatchEx	RU Host Unknown Error[%1] Error Code [%2]	The RU was not properly set for the IIP.	Check the setup.	
13017	FFIdPatInfoInput	It failed that [%1] gets the connection string of strDB	The “LangStrDB” key was not found in Directory.ini.	Reinstall.	
13017	FFIdRUMainControlEx	RU Host Unknown Error[%1] Error Code [%2]	The RU was not properly set for the IIP.	Check the setup.	
13018	FFIdPatInfoInput	It failed that [%1] connects to strDB	The connection character string was not properly registered for the “LangStrDB” key in Directory.ini.	Reinstall.	
13019	FFIdPatInfoInput	It failed that [%1] gets the connection string of sysDB	The “SysConfigDB” key was not found in Directory.ini.	Reinstall.	
13020	FFIdPatInfoInput	It failed that [%1] connects to sysDB	The connection character string was not properly registered for the “SysConfigDB” key in Directory.ini.	Reinstall.	
13020	FFIipInput	RU Error DB Connect Error in [%1]	The connection character string was not properly registered for the “RuErrorDataDB” key in Directory.ini or the RU error information database did not exist.	Reinstall.	
13021	FFIipInput	RU Error Data Get Error in [%1]	The window number sent from the RU was not found in the RU error information database.	Ensure that the RU version agrees with the RU error information database version.	
13022	FFIdPatInfoInput	It failed that [%1] gets System ID	The system setup database was damaged.	Reinstall.	
13022	FFIipInput	RU Status DB Connection String Get Error in [%1]	The connection character string was not properly registered for the “RuStatusDataDB” key in Directory.ini.	Reinstall.	
13023	FFIdPatInfoInput	%1 (%2) : Patient Information Check Error%n Item [%3]%n Error [%4]	The patient information contained illegal information.	Correct the patient information setup.	
13023	FFIipInput	RU Status DB Connect Error in [%1]	The connection character string was not properly registered for the “RuErrorDataDB” key in Directory.ini or the RU error information database did not exist.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13024	FFIdPatInfoInput	%1 (%2) : Bitmap Image Get Error%n BMP File [%3]	“Id_LocalSearch_U.bmp”, “Id_LocalSearch_D.bmp”, or “Id_LocalSearch_X.bmp” was not found in the path to the folder in which images were positioned.	Place “Id_LocalSearch_U.bmp”, “Id_LocalSearch_D.bmp”, and “Id_LocalSearch_X.bmp” in the path to the folder in which images are positioned.	
13024	FFIipInput	RU Status Data Get Error in [%1]	The window number sent from the RU was not found in the RU error information database.	Ensure that the RU version agrees with the RU error information database version.	
13025	FFIdPatInfoInput	%1 (%2) : Patient Info Get Error%n Error [%3]%n RetCode [%4]	The patient information database was damaged.	Repair the patient information database.	
13026	FFIdPatInfoInput	%1 (%2) : Patient Info Set Error%n Error [%3]%n RetCode [%4]	The patient information to be registered contained illegal information or the patient information database was damaged.	Enter correct patient information or repair the patient information database.	
13027	FFIdPatInfoInput	%1 (%2) : Patient Info Not Correspond%n RetCode [%3]%n	No matching patient information was found.		
13027	FFIipInput	%1%n%2%n%3%n%4%n %5%n%6%n%7%0	Control information	No particular remedy needs be taken.	
13030	FFIipInput	%1%n%2%n%3%n%4%n %5%n%6%n%7%0	The connection character string was not properly registered for the “RuStatusDataDB” key in Directory.ini.	Reinstall.	
13031	FFIipInput	[%s] %s (%s): Log Output Directory Get Error	The system setup database was damaged.	Reinstall.	
13032	FFIipInput	[%s] %s (%s): MCR Control Initialize Error	The card reader unit was not connected.	There are no particular problems except that the magnetic card reader is not available.	
13033	FFIipInput	[%s] %s (%s): LR button cannot be concave set	The range was changed by the Service Utility.	No particular remedy needs be taken.	
13034	FFIipInput	[%s] %s (%s): TB button cannot be concave set	The range was changed by the Service Utility.	No particular remedy needs be taken.	
13035	FFIipInput	[%s] %s (%s): TBLR button cannot be concave set	The range was changed by the Service Utility.	No particular remedy needs be taken.	
13036	FFIipInput	[%s] %s (%s): Rotation button cannot be concave set	The range was changed by the Service Utility.	No particular remedy needs be taken.	
13037	FFIipInput	[%s] %s (%s): Message Table Name Get Error	The “MsgTableName” key was not found in the system setup database.	Reinstall.	
13038	FFIipInput	[%s] %s (%s): StrDB Connection String Get Error	The “LangStrDB” key was not found in Directory.ini.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13039	FFlipInput	[%s] %s (%s): StrDB Connect Error	The connection character string was not properly registered for the “LangStrDB” key in Directory.ini.	Reinstall.	
13040	FFlipInput	[%s] %s (%s): SysDB Connection String Get Error	The “SysConfigDB” key was not found in Directory.ini.	Reinstall.	
13041	FFlipInput	[%s] %s (%s): SysDB Connect Error	The connection character string was not properly registered for the “SysConfigDB” key in Directory.ini.	Reinstall.	
13042	FFlipInput	[%s] %s (%s): ImageDB Connection Character String Get Error	The “ImageDB“ key was not found in Directory.ini.	Reinstall.	
13043	FFlipInput	[%s] %s (%s): Failed ImageDB Connection	The connection character string was not properly registered for the “ImageDB” key in Directory.ini.	Reinstall.	
13044	FFlipInput	[%s] %s (%s): Failed ImageDB Open Recordset	The image database was not successfully accessed.	Reinstall.	
13045	FFlipInput	[%s] %s (%s): Failed ImageDB Close Recordset	The image database was not successfully accessed.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
13046	FFlipInput	[%s] %s (%s): ImageDB Data Get Error	The image database was not successfully accessed.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
13047	FFlipInput	[%s] %s (%s): ImageDB Data Set Error	The image database was not successfully accessed.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
13048	FFlipInput	[%s] %s (%s): ImageDB Data Delete Error	The image database was not successfully accessed.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	

Event	Event Source	Description	Causes	Remedies	Remarks
13049	FFlipInput	[%s] %s (%s): Failed ImageDBFlag Connection	The image database was not successfully accessed.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
13050	FFlipInput	[%s] %s (%s): Failed ImageDBFlag Close	The image database was not successfully accessed.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
13051	FFlipInput	[%s] %s (%s): ImageDBFlag Data Set Error	The image database was not successfully accessed.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
13052	FFlipInput	[%s] %s (%s): Failed MenuDB Initialize	The initialization process for menu database access was not successfully performed.	Reinstall.	
13053	FFlipInput	[%s] %s (%s): Menu Data in ImageDB Get Error	Menu information was not successfully acquired from the menu database.	Reinstall.	
13054	FFlipInput	[%s] %s (%s): Menu Parameter Data in ImageDB Get Error	Menu parameter information was not successfully acquired from the menu database.	Reinstall.	
13055	FFlipInput	[%s] %s (%s): Failed MenuDB Termination	The termination process for menu database access was not successfully performed.	Reinstall.	
13056	FFlipInput	[%s] %s (%s): NetDB Connection Character String Get Error	The “NetConfigDB” key was not found in Directory.ini.	Reinstall.	
13057	FFlipInput	[%s] %s (%s): Failed NetDB Connection	The connection character string was not properly registered for the “NetConfigDB” key in Directory.ini.	Reinstall.	
13058	FFlipInput	[%s] %s (%s): NetDB Data Get Error	The network setup database was damaged.	Reinstall.	
13059	FFlipInput	[%s] %s (%s): Failed Create New DICOM Data	New DICOM data was not successfully created.	Restart. If the problem frequently occurs, initialize the image database.	
13060	FFlipInput	[%s] %s (%s): DICOM Data Get Error	DICOM data was not successfully acquired.	Restart. If the problem frequently occurs, initialize the image database.	
13061	FFlipInput	[%s] %s (%s): DICOM Data Set Error	DICOM data was not successfully set up.	Restart. If the problem frequently occurs, initialize the image database.	
13062	FFlipInput	[%s] %s (%s): DICOM Data Delete Error	DICOM data was not successfully deleted.	Restart. If the problem frequently occurs, initialize the image database.	

Event	Event Source	Description	Causes	Remedies	Remarks
13063	FFlipInput	[%s] %s (%s): DICOM Data Load Error	DICOM data was not successfully loaded.	Restart. If the problem frequently occurs, initialize the image database.	
13064	FFlipInput	[%s] %s (%s): DICOM Data Save Error	DICOM data was not successfully saved.	Restart. If the problem frequently occurs, initialize the image database.	
13065	FFlipInput	[%s] %s (%s): DICOM Data Free Error	DICOM data was not successfully freed.	Restart. If the problem frequently occurs, initialize the image database.	
13066	FFlipInput	[%s] %s (%s): Failed in Padding Acquisition[Id#]	The “IdPadding” key was not found in the system setup database.	Reinstall.	
13067	FFlipInput	[%s] %s (%s): Failed in Padding Acquisition[Exam#]	The “ExaminationNoPadding” key was not found in the system setup database.	Reinstall.	
13068	FFlipInput	[%s] %s (%s): Failed in Format Acquisition[Date Of Birth]	The “DateFormat” key was not found in the system setup database.	Reinstall.	
13069	FFlipInput	[%s] %s (%s): Cannot Access Data Base[Departmdb]	The requesting department database was not found in the path indicated by the connection character string. The requesting department table did not exist.	Reinstall.	
13070	FFlipInput	[%s] %s (%s): Displayed Item Is Not Understood[Depart List]	The “FieldDepartList” key was not found in the system setup database.	Reinstall.	
13072	FFlipInput	[%s] %s (%s): Failed in Connected String Acquisition[Depart]	The “DepartDB” key was not found in Directory.ini.	Reinstall.	
13073	FFlipInput	[%s] %s (%s): Cannot Access Data Base[Paramedicmdb]	The technician’s database was not found in the path indicated by the connection character string. The technician’s table did not exist.	Reinstall.	
13074	FFlipInput	[%s] %s (%s): Displayed Item Is Not Understood[Paramedic List]	The “FieldParamedicList” key was not found in the system setup database.	Reinstall.	
13076	FFlipInput	[%s] %s (%s): Failed in Connected String Acquisition[Paramedic]	The “ParamedicDB” key was not found in Directory.ini.	Reinstall.	
13077	FFlipInput	[%s] %s (%s): Failed in Window Size Acquisition	The registry was damaged.	Reinstall.	
13078	FFlipInput	[%s] %s (%s): Failed in ExposureList Erase	The “ExposureListErase” key was not found in the system setup database.	Reinstall.	
13079	FFlipInput	[%s] %s (%s): Config Directory Character String Get Error	The “Config” key was not found in Directory.ini.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13080	FFIipInput	[%s] %s (%s): ImageDBFlag Data Get Error	The image database was damaged.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
13081	FFIipInput	[%s] %s (%s): StrDB Message String Get Error	The character string database was damaged.	Reinstall.	
13082	FFIipInput	[%s] %s (%s): IP-Address(RU) Get Error	The network setup database was damaged.	Restart.	
13083	FFIipInput	[%s] %s (%s): Initialize Timeout <InImg>	The system was unstable.	Restart.	
13084	FFIipInput	[%s] %s (%s): Terminate Error <InImg>	The system was unstable.	Restart.	
13085	FFIipInput	[%s] %s (%s): Terminate Timeout <InImg>	The system was unstable.	Restart.	
13086	FFIipInput	[%s] %s (%s): Input Method Error <InImg>	The system was unstable.	Restart.	
13087	FFIipInput	[%s] %s (%s): Original Image Input Failure <InImg>	The system was unstable.	Restart.	
13088	FFIipInput	[%s] %s (%s): Image Processing Trouble <InImg>	The system was unstable.	Restart.	
13089	FFIipInput	[%s] %s (%s): Menu Read Error <IdExposureList>	The image database/information file was damaged.	Reinstall.	
13090	FFIdDepartSelect	%1 (%2) : Invalid Depart Code%n Code [%3]	Directory.ini was damaged.	Reinstall.	
13090	FFIdParamedicSelect	%1 (%2) : Invalid Paramedic Code%n Code [%3]	Directory.ini was damaged.	Reinstall.	
13090	FFIdIndividualSelect	%1 (%2) : Invalid Depart/Paramedic Code%n Code [%3]	Directory.ini was damaged.	Repair Directory.ini.	
13091	FFIdDepartSelect	%1 (%2) : Invalid Depart Name (SBCS)%n Name (SBCS) [%3]	The database was damaged.	Reinstall.	
13091	FFIdParamedicSelect	%1 (%2) : Invalid Paramedic Name (SBCS)%n Name (SBCS) [%3]	The database was damaged.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13091	FFIdIndividualSelect	%1 (%2) : Invalid Depart/Paramedic Name (SBCS)%n Name (SBCS) [%3]	The database was damaged.	Repair the database.	
13094	FFIipInput	[%s] %s (%s): Message Send Error <IpcInfCom>	The system was unstable.	Restart.	
13096	FFIipInput	[%s] %s (%s): Request Command Not Executed <RU>	It is conceivable that there was a problem on the RU side. (Although a command was requested, it was not executed.)	Check the RU status.	
13098	FF32LIB	FF32lib A WIN32 system library error occurred. [%1]%n%2	An error occurred when calling up the WIN32 API.	Restart.	
13098	FFIipInput	[%s] %s (%s): Reconnect Error <RU>	The line was abnormal.	Check the line.	
13098	FFIdPatInfoInput	%1 (%2) : %n [%3]%n %4%n %5	A general-use message for the input of patient information (serves as an error message and also as information).	If it is referring to an error, follow the custom message box that opens.	
13099	FFIipInput	[%s] %s (%s): Disconnect Error <RU>	The line was abnormal.	Check the line.	
13099	FF32LIB	FF32lib An unknown error occurred. [%1]%n%2	An exception error occurred.	Restart.	
13100	FFIipInput	[%s] %s (%s): Failed in Display Group Acquisition[Initialize]	The “DisplayDataDB” key was not found in Directory.ini or the connection character string was not properly registered in the display group table.	Reinstall.	
13101	FFIipInput	[%s] %s (%s): Failed in Display Group Acquisition	The “DisplayDataDB” key was not found in Directory.ini or the connection character string was not properly registered in the display group table.	Reinstall.	
13103	FFIipInput	[%s] %s (%s): Failed in Display Menu Acquisition[Initialize]	The “DisplayDataDB” key was not found in Directory.ini.	Reinstall.	
13104	FFIipInput	[%s] %s (%s): Failed in Display Menu Acquisition[Record]	The menu database was damaged.	Reinstall.	
13108	FFIipInput	[%s] %s (%s): Failed in Exposure Menu Acquisition	The menu database was damaged.	Reinstall.	
13109	FFIipInput	[%s] %s (%s): Next Set Number Data Get Error	The registry was damaged.	Reinstall.	
13110	FFIipInput	[%s] %s (%s): Next Set Number Data Set Error	The registry was damaged.	Reinstall.	
13111	FFIipInput	[%s] %s (%s): System ID Data Get Error	The system setup database was damaged.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13112	FFlipInput	[%s] %s (%s): Auto Distribution Data Get Error	The system setup database was damaged.	Reinstall.	
13113	FFlipInput	[%s] %s (%s): Enable Selector Data Get Error	The system setup database was damaged.	Reinstall.	
13114	FFlipInput	[%s] %s (%s): Auto Menu Select Data Get Error	The system setup database was damaged.	Reinstall.	
13115	FFlipInput	[%s] %s (%s): Next Set Number Min Data Get Error	The system setup database was damaged.	Reinstall.	
13116	FFlipInput	[%s] %s (%s): Next Set Number Max Data Get Error	The system setup database was damaged.	Reinstall.	
13120	FFlipInput	[%s] %s (%s): Failed in Getting ID-Online Port#	The database was not found or the associated key did not exist.	Reinstall.	
13121	FFlipInput	[%s] %s (%s): Failed in ID-Online Device Name	The database was not found or the associated key did not exist.	Reinstall.	
13122	FFlipInput	[%s] %s (%s): RU Status DB Connection String Get Error	Directory.ini was damaged.	Reinstall.	
13123	FFlipInput	[%s] %s (%s): Failed in selectable direction	The “SelectableDirection” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13124	FFlipInput	[%s] %s (%s): Failed in Selectable Image Format Acquisition	The “SelectableFormat” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13125	FFlipInput	[%s] %s (%s): FilmMarkDB Connection String Get Error	The “FilmMarkDB“ key was not found in Directory.ini.	Reinstall.	
13126	FFlipInput	[%s] %s (%s): FilmMarkDB Connect Error	The connection character string was not properly registered for the “FilmMarkDB“ key in Directory.ini.	Reinstall.	
13128	FFlipInput	[%s] %s (%s): Failed in Limit Film Copy Acquisition	The “LimitFilmCopy” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13131	FFlipInput	[%s] %s (%s): Failed in Selectable EDR Mode Acquisition	The “SelectableEdrMode” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13132	FFlipInput	[%s] %s (%s): Failed in Selectable Function Acquisition	The “SelectableFunction” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13134	FFlipInput	[%s] %s (%s): Failed in Selectable EDR Mode Acquisition	The “SelectableFilingMode” key was not found in the system setup database or its value was incorrect.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13135	FFlipInput	[%s] %s (%s): NetDB Data Get Error	The connection character string for the network setup database was not successfully acquired or the network setup database did not exist.	Reinstall.	
13136	FFlipInput	[%s] %s (%s): Failed in Enable DistributionCode Acquisition	The “EnableDistributionCode” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13137	FFlipInput	[%s] %s (%s): Failed in Enable FileString Acquisition	The “EnableFileString” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13138	FFlipInput	[%s] %s (%s): Failed in Enable Function Acquisition	The “EnableFunction” key was not found in the system setup database or its value was incorrect.	Reinstall.	
13157	FFlipInput	[%s] %s (%s): Finish Mode Get Error	The system setup database was damaged.	Reinstall.	
13158	FFlipInput	[%s] %s (%s): RU Error DB Connection String Get Error	The “RuErrorDataDB” key was not found in Directory.ini.	Reinstall.	
13159	FFlipInput	[%s] %s (%s): RU Error DB Table Name Get Error	The “MsgTableName” key was not found in the system setup database.	Reinstall.	
13160	FFlipInput	[%s] %s (%s): Call Error [RU Error CUSTOM MESSAGE BOX]	The specified ID was not registered in “RuErrorDataDB“ or the custom message box was not successfully called.	Reinstall.	
13161	FFlipInput	[%s] %s (%s): Failed Display Thumbnail Image	The program was faulty or the image file was damaged.	Restart. If the problem frequently occurs, initialize the image database.	
13162	FFlipInput	[%s] %s (%s): Ip Size Unit (Inch/Metric) Get Error	The system setup database was damaged.	Reinstall.	
13165	FFlipInput	[%s] %s (%s): Image Size Code Specify Error	RU-dependent symptom.	Check the RU status.	
13166	FFlipInput	[%s] %s (%s): Pantomo Setting Get Error	The system setup database was damaged.	Repair the system setup database.	
13167	FFlipInput	[%s] %s (%s): RU Error Info Get Error	The RU error database was damaged.	Reinstall the RU software.	
13168	FFlipInput	[%s] %s (%s): RU Status Info Get Error	The RU status information database was damaged.	Reinstall the RU software.	
13177	FFlipInput	[%s] %s (%s): Default Menu Code Get Error	The system setup database was damaged.	Reinstall.	
13178	FFlipInput	[%s] %s (%s): Next Multi Frame Pair Code Data Get Error	The registry was damaged.	Reinstall.	
13179	FFlipInput	[%s] %s (%s): Next Multi Frame Pair Code Data Set Error	The registry was damaged.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13180	FFlipInput	[%s] %s (%s): Series Generation Type Data Get Error	The system setup database was damaged.	Reinstall.	
13181	FFlipInput	[%s] %s (%s): Multi Frame UID Information Get Error	The system setup database was damaged.	Reinstall.	
13182	FFlipInput	[%s] %s (%s): Failed in Getting XCON Port#	The database did not exist or the associated key was not found.	Reinstall.	
13183	FFlipInput	[%s] %s (%s): Failed in XCON Device Name	The database did not exist or the associated key was not found.	Reinstall.	
13184	FFlipInput	[%s] %s (%s): MCR Type Get Error	The system setup database was damaged.	Reinstall.	
13185	FFlipInput	[%s] %s (%s): MCR Variation Get Error	The system setup database was damaged.	Reinstall.	
13186	FFlipInput	[%s] %s (%s): Custom Card Use Get Error	The system setup database was damaged.	Reinstall.	
13187	FFlipInput	[%s] %s (%s): Font Name Get Error	The “Font” key was not found in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
13188	FFlipInput	[%s] %s (%s): Font Size Get Error	The “FontSizeSS”/“FontSizeS”/ “FontSizeM”/“FontSizeL”/“FontSizeLL” key was not found in the registry.	Displayed characters can be corrupted. Reinstall the IIP as necessary.	
13189	FFlipInput	[%s] %s (%s): Multibyte Flag Get Error	The “Multibyte” key was not found in the registry.	Reinstall.	
13190	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Id#]	The “LangStrDB” key was not found in Directory.ini or the ID “30700” was not registered in the character string database.	Reinstall.	
13191	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Exam#]	The “LangStrDB” key was not found in Directory.ini or the ID “30701” was not registered in the character string database.	Reinstall.	
13192	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[SBCS Patient Name]	The “LangStrDB” key was not found in Directory.ini or the ID “30702” was not registered in the character string database.	Reinstall.	
13193	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[DBCS Patient Name]	The “LangStrDB” key was not found in Directory.ini or the ID “30703” was not registered in the character string database.	Reinstall.	
13194	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Sex]	The “LangStrDB” key was not found in Directory.ini or the ID “30704” was not registered in the character string database.	Reinstall.	
13195	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Sex M]	The “LangStrDB” key was not found in Directory.ini or the ID “30705” was not registered in the character string database.	Reinstall.	
13196	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Sex F]	The “LangStrDB” key was not found in Directory.ini or the ID “30706” was not registered in the character string database.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13197	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Sex O]	The “LangStrDB” key was not found in Directory.ini or the ID “30707” was not registered in the character string database.	Reinstall.	
13198	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Date Of Birth]	The “LangStrDB” key was not found in Directory.ini or the ID “30708” was not registered in the character string database.	Reinstall.	
13199	FFlipInput	[%s] %s (%s): Failed in Limitation No Acquisition[Id#]	The “IdLength” key was not found in the system setup database.	Reinstall.	
13200	FFlipInput	[%s] %s (%s): Failed in Limitation No Acquisition[Exam#]	The “ExaminationNoLength” key was not found in the system setup database.	Reinstall.	
13201	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Depart]	The “LangStrDB” key was not found in Directory.ini or the ID “30800” was not registered in the character string database.	Reinstall.	
13202	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Paramedic]	The “LangStrDB” key was not found in Directory.ini or the ID “30800” was not registered in the character string database.	Reinstall.	
13203	FFlipInput	[%s] %s (%s): Image Folder Path Get Error	The “Bitmap” key was not found in Directory.ini.	Reinstall.	
13204	FFlipInput	[%s] %s (%s): [Clear]Button Image Get Error	Id_Clear_U.bmp/“Id_Clear_D.bmp”/ “Id_Clear_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13205	FFlipInput	[%s] %s (%s): [Ok]Button Image Get Error	Id_Ok_U.bmp/“Id_Ok_D.bmp”/“Id_Ok_X. bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13206	FFlipInput	[%s] %s (%s): [Cancel]Button Image Get Error	Id_Cancel_U.bmp/“Id_Cancel_D.bmp”/ “Id_Cancel_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13207	FFlipInput	[%s] %s (%s): [Plus]Button Image Get Error	Id_Plus_U.bmp/“Id_Plus_D.bmp”/“Id_Plus_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13208	FFlipInput	[%s] %s (%s): [Minus]Button Image Get Error	Id_Minus_U.bmp/“Id_Minus_D.bmp”/ “Id_Minus_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13209	FFlipInput	[%s] %s (%s): [Next Page]Button Image Get Error	Id_NextPage_U.bmp/“Id_NextPage_ D.bmp”/“Id _NextPage_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	

Event	Event Source	Description	Causes	Remedies	Remarks
13210	FFlipInput	[%s] %s (%s): [Previous Page]Button Image Get Error	Id_PrevPage_U.bmp/“Id_PrevPage_ D.bmp”/“Id _PrevPage_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13211	FFlipInput	[%s] %s (%s): RU Watch Connection Disconnected	The line was abnormal.	The program was faulty.	
13212	FFlipInput	[%s] %s (%s): No ACK Returned in RU Watch Connection	The line was abnormal.	The program was faulty.	
13213	FFlipInput	[%s] %s (%s): RU Control Connection Disconnected	The line was abnormal.	The program was faulty.	
13214	FFlipInput	[%s] %s (%s): No ACK Returned in RU Control Connection	The line was abnormal.	The program was faulty.	
13217	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Complete]	The “LangStrDB” key was not found in Directory.ini or the ID “30202” was not registered in the character string database.	Reinstall.	
13218	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[QA Unfinished]	The “LangStrDB” key was not found in Directory.ini or the ID “30201” was not registered in the character string database.	Reinstall.	
13219	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Interrupt]	The “LangStrDB” key was not found in Directory.ini or the ID “30200” was not registered in the character string database.	Reinstall.	
13220	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Cancel]	The “LangStrDB” key was not found in Directory.ini or the ID “30203” was not registered in the character string database.	Reinstall.	
13221	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[New Study]	The “LangStrDB” key was not found in Directory.ini or the ID “30500” was not registered in the character string database.	Reinstall.	
13222	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Registered]	The “LangStrDB” key was not found in Directory.ini or the ID “30501” was not registered in the character string database.	Reinstall.	
13223	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[QA Waiting]	The “LangStrDB” key was not found in Directory.ini or the ID “30502” was not registered in the character string database.	Reinstall.	
13224	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Output Waiting]	The “LangStrDB” key was not found in Directory.ini or the ID “30503” was not registered in the character string database.	Reinstall.	
13225	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Outputted]	The “LangStrDB” key was not found in Directory.ini or the ID “30504” was not registered in the character string database.	Reinstall.	
13226	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[All]	The “LangStrDB” key was not found in Directory.ini or the ID “30505” was not registered in the character string database.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13227	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Today]	The “LangStrDB” key was not found in Directory.ini or the ID “30506” was not registered in the character string database.	Reinstall.	
13228	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[System]	The “LangStrDB” key was not found in Directory.ini or the ID “30507” was not registered in the character string database.	Reinstall.	
13229	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[StudyReseve]	The “LangStrDB” key was not found in Directory.ini or the ID “30600” was not registered in the character string database.	Reinstall.	
13230	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[StudyStart]	The “LangStrDB” key was not found in Directory.ini or the ID “30601” was not registered in the character string database.	Reinstall.	
13231	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[Priority]	The bmp file path/bmp file was abnormal.	Reinstall.	
13232	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[End]	The bmp file path/bmp file was abnormal.	Reinstall.	
13233	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[Change]	The bmp file path/bmp file was abnormal.	Reinstall.	
13234	FFlipInput	[%s] %s (%s): [New]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13235	FFlipInput	[%s] %s (%s): [Repeat]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13236	FFlipInput	[%s] %s (%s): [Again]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13237	FFlipInput	[%s] %s (%s): [Add]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13238	FFlipInput	[%s] %s (%s): [Delete]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13239	FFlipInput	[%s] %s (%s): [Prev]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13240	FFlipInput	[%s] %s (%s): [Next]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13241	FFlipInput	[%s] %s (%s): [Monitor Mode]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13242	FFlipInput	[%s] %s (%s): [QA]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13243	FFlipInput	[%s] %s (%s): [Change]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13244	FFlipInput	[%s] %s (%s): [AP/PA]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13245	FFlipInput	[%s] %s (%s): [EDR Mode]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13246	FFlipInput	[%s] %s (%s): [Film Format]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13247	FFlipInput	[%s] %s (%s): [Detail]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13248	FFlipInput	[%s] %s (%s): [New]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13249	FFlipInput	[%s] %s (%s): [Repeat]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13250	FFlipInput	[%s] %s (%s): [Again]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13251	FFlipInput	[%s] %s (%s): [Add]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13252	FFlipInput	[%s] %s (%s): [Delete]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13253	FFlipInput	[%s] %s (%s): [Prev]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13254	FFlipInput	[%s] %s (%s): [Next]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13255	FFlipInput	[%s] %s (%s): [Monitor Mode]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13256	FFlipInput	[%s] %s (%s): [QA]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13257	FFlipInput	[%s] %s (%s): [Change]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13258	FFlipInput	[%s] %s (%s): [AP/PA]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13259	FFlipInput	[%s] %s (%s): [EDR Mode]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13260	FFlipInput	[%s] %s (%s): [Film Format]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13261	FFlipInput	[%s] %s (%s): [Detail]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13262	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[New]	The bmp file path/bmp file was abnormal.	Reinstall.	
13263	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[Normal]	Id_NormalImage_U.bmp/ “Id_NormalImage_ D.bmp”/ “Id_NormalImage_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13264	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[LR]	Id_LR_Reverse_U.bmp/“Id_LR_Reverse_ D.bmp”/“Id_LR_Reverse_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13265	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[TB]	Id_TB_Reverse_U.bmp/“Id_TB_Reverse_ D.bmp”/“Id_TB_Reverse_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13266	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[TB LR]	Id_Rotation180_U.bmp/ “Id_Rotation180_D.bmp”/ “Id_Rotation180_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13267	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[Rotation]	Id_Rotation90_U.bmp/“Id_Rotation90_D. bmp”/ “Id_Rotation90_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13268	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[Single]	Id_Single_U.bmp/“Id_Single_D.bmp”/“Id_ Single_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13269	FFlipInput	[%s] %s (%s): Failed in Image Acquisition[Twin]	Id_Twin_U.bmp/“Id_Twin_D.bmp”/ “Id_Twin_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	

Event	Event Source	Description	Causes	Remedies	Remarks
13270	FFlipInput	[%s] %s (%s): An Illegal Film Mark Character Was Detected	The film mark database was damaged.	Reinstall.	
13271	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[FIX]	The “LangStrDB” key was not found in Directory.ini or the ID “33502” was not registered in the character string database.	Reinstall.	
13272	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Skfix]	The “LangStrDB” key was not found in Directory.ini or the ID “33503” was not registered in the character string database.	Reinstall.	
13273	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[SEMI-X]	The “LangStrDB” key was not found in Directory.ini or the ID “33504” was not registered in the character string database.	Reinstall.	
13274	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition [DensityAverage]	The “LangStrDB” key was not found in Directory.ini or the ID “33505” was not registered in the character string database.	Reinstall.	
13275	FFlipInput	[%s] %s (%s): [Utility]Button Image Get Error	Id_Utility_U.bmp/“Id_Utility_D.bmp”/ “Id_Utility_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed nor mally.	
13276	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Alarm Stop]	The “LangStrDB” key was not found in Directory.ini or the ID “32700” was not registered in the character string database.	Reinstall.	
13277	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Exit]	The character string database was damaged.	Reinstall.	
13278	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[User Utility]	The character string database was damaged.	Reinstall.	
13279	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[List Setting]	The character string database was damaged.	Reinstall.	
13280	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Version]	The character string database was damaged.	Reinstall.	
13281	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[CANCEL]	The character string database was damaged.	Reinstall.	
13282	FFlipInput	[%s] %s (%s): [Clear]Button Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13283	FFlipInput	[%s] %s (%s): [Clear]Button ToolTipText Get Error	The character string database was damaged.	Reinstall.	
13284	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[CANCEL]	The “LangStrDB” key was not found in Directory.ini or the ID “35000” was not registered in the character string database.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13285	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[DUST]	The “LangStrDB” key was not found in Directory.ini or the ID “35001” was not registered in the character string database.	Reinstall.	
13286	FFlipInput	[%s] %s (%s): Tooltip Text Get Error	The character string database was damaged.	Reinstall.	
13287	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[TitleBar]	The character string database was damaged.	Reinstall.	
13288	FFlipInput	[%s] %s (%s): Failed in Caption Acquisition[Option]	The character string database was damaged.	Reinstall.	
13289	FFlipInput	[%s] %s (%s): Version Info Get Error	The registry was damaged.	Reinstall.	
13290	FFlipInput	[%s] %s (%s): Option List Get Error	The registry was damaged.	Reinstall.	
13291	FFlipInput	[%s] %s (%s): [Cassette Acceptable] Image Get Error	Id_RuProcess_I.bmp was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13292	FFlipInput	[%s] %s (%s): [Cassette Unacceptable] Image Get Error	Id_RuProcessN_I.bmp was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13293	FFlipInput	[%s] %s (%s): [Miss]Image Get Error	The bmp file path/bmp file was abnormal.	Reinstall.	
13294	FFlipInput	[%s] %s (%s): [Image Style]Button Image Get Error	Id_ApPa_U.bmp/“Id_ApPa_D.bmp”/ “Id_ ApPa_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13295	FFlipInput	[%s] %s (%s): [EDR]Button Image Get Error	Id_Edr_U.bmp/“Id_Edr_D.bmp”/ “Id_Edr_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13296	FFlipInput	[%s] %s (%s): [Function]Button Image Get Error	Id_Edr_U.bmp/“Id_Edr_D.bmp”/“Id_Edr_X. bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13297	FFlipInput	[%s] %s (%s): [Film Count]Button Image Get Error	Id_FilmCount_U.bmp/“Id_FilmCount_ D.bmp”/“Id_FilmCount_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13298	FFlipInput	[%s] %s (%s): [Ip Size]Button Image Get Error	Id_IpSize_U.bmp/“Id_IpSize_D.bmp”/ “Id_ IpSize_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	

Event	Event Source	Description	Causes	Remedies	Remarks
13299	FFlipInput	[%s] %s (%s): [Image Format]Button Image Get Error	Id_FilmFormat_U.bmp/“Id_FilmFormat_ D.bmp”/“Id_FilmFormat_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13300	FFlipInput	[%s] %s (%s): [Filing]Button Image Get Error	Id_FilingMode_U.bmp/“Id_FilingMode_ D.bmp”/“Id_FilingMode_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13301	FFlipInput	[%s] %s (%s): [Film Mark]Button Image Get Error	Id_FilmMark_U.bmp/“Id_FilmMark_D.bmp” /“Id_ FilmMark_X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13302	FFlipInput	[%s] %s (%s): [Distribution Code]Button Image Get Error	Id_DistributionCode_U.bmp/ “Id_DistributionCode_D.bmp”/ “Id_DistributionCode_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13303	FFlipInput	[%s] %s (%s): [CSSS]Button Image Get Error	Id_CsCs_U.bmp/“Id_CsCs_D.bmp”/ “Id_CsCs_ X.bmp” was not found in the path to an image folder or the image format was illegal.	Reinstall the IIP because the button cannot be displayed normally.	
13304	FFlipInput	[%s] %s (%s): Image Data Connection Disconnected	The line was abnormal.	Check the line.	
13309	FFlipInput	[%s] %s (%s): Failed in Patient Information	The patient information contained an illegal character string.	Ensure that the patient information does not contain any illegal character string.	
13345	FFIdDepartSelect	%1 (%2) : Database Data Get Error%n Database [%3]%n Table [%4]%n Key [%5]	The database was damaged.	Reinstall.	
13345	FFIdFilmMark	%1 (%2) : Database Data Get Error%n Database [%3]%n Table [%4]%n Key [%5]	The database was damaged.	Reinstall.	
13345	FFIdMcrControl	IdMcrControl (threadMcrRead) : Database Data Get Error	The database was faulty.	Reinstall.	
13345	FFIdParamedicSelect	%1 (%2) : Database Data Get Error%n Database [%3]%n Table [%4]%n Key [%5]	The database was damaged.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13345	FFIdPatInfoInput	%1 (%2) : Database Data Get Error%n Database [%3]%n Table [%4]%n Key [%5]	The database was damaged.	Reinstall.	
13345	FFIipInput	%1 (%2) : Database Data Get Error%n Database [%3]%n Table [%4]%n Key [%5]	The database was damaged.	Reinstall.	
13345	FFIdIndividualSelect	%1 (%2) : Database Data Get Error%n Database [%3]%n Table [%4]%n Key [%5]	The database was damaged.	Repair the database.	
13346	FFIipInput	%1 (%2) : Patient Information Check Error%n Item [%3]%n Error [%4]	The patient information contained illegal information.	Correct the patient information setup.	
13347	FFIipInput	%1 (%2) : Caption Get Error%n CaptionId [%3]	The character string database was damaged.	Reinstall.	
13348	FFIdDepartSelect	%1 (%2) : Registry Data Get Error%n Value [%3]	The registry was damaged.	Reinstall.	
13348	FFIdFilmMark	%1 (%2) : Registry Data Get Error%n Value [%3]	The registry was damaged.	Reinstall.	
13348	FFIdMenuChange	%1 (%2) : Registry Data Get Error%n Value [%3]	The registry was damaged.	Reinstall.	
13348	FFIdParamedicSelect	%1 (%2) : Registry Data Get Error%n Value [%3]	The registry was damaged.	Reinstall.	
13348	FFIdPatInfoInput	%1 (%2) : Registry Data Get Error%n Value [%3]	The registry was damaged.	Reinstall.	
13348	FFIipInput	%1 (%2) : Registry Data Get Error%n Value [%3]	The registry was damaged.	Reinstall.	
13348	FFIdIndividualSelect	%1 (%2) : Registry Data Get Error%n	The registry was damaged.	Repair the registry.	
13349	FFIdDepartSelect	%1 (%2) : INI File Data Get Error%n Key [%3]	Directory.ini was damaged.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
13349	FFIdFilmMark	%1 (%2) : INI File Data Get Error%n Key [%3]	Directory.ini was damaged.	Reinstall.	
13349	FFIdMenuChange	%1 (%2) : INI File Data Get Error%n Key [%3]	Directory.ini was damaged.	Reinstall.	
13349	FFIdParamedicSelect	%1 (%2) : INI File Data Get Error%n Key [%3]	Directory.ini was damaged.	Reinstall.	
13349	FFIdPatInfoInput	%1 (%2) : INI File Data Get Error%n Key [%3]	Directory.ini was damaged.	Reinstall.	
13349	FFIipInput	%1 (%2) : INI File Data Get Error%n Key [%3]	Directory.ini was damaged.	Reinstall.	
13349	FFIdIndividualSelect	%1 (%2) : INI File Data Get Error%n Key [%3]	Registry.ini was damaged.	Repair Registry.ini.	
13350	FFIdFilmMark	%1 (%2) : Bitmap Image Get Error%n BMP File [%3]	The bmp file path or bmp file was abnormal.	Reinstall.	
13350	FFIdMenuChange	%1 (%2) : Bitmap Image Get Error%n BMP File [%3]	The bmp file path or bmp file was abnormal.	Reinstall.	
13350	FFIipInput	%1 (%2) : Bitmap Image Get Error%n BMP File [%3]	The bmp file path or bmp file was abnormal.	Reinstall.	
13352	FFIipInput	%1 (%2) : Dicom MWM & PPS Option Not Install	The DICOM MWM & PPS option was not installed.	Install the DICOM MWM & PPS option.	
13353	FFIipInput	%1 (%2) : Dicom MWM Option Not Install	The DICOM MWM option was not installed.	Install the DICOM MWM option.	
13362	FFIipInput	%1 (%2) : Not Entry Host Name	The host name for the local enclosure was not successfully acquired.	With the service utility, register the host information about the PPS local enclosure.	
13370	FFIipInput	%1 (%2) : PPS Request Failure [IN PROGRESS]	The equipment connection was faulty or the remote equipment power was OFF.	Retry.	
13371	FFIipInput	%1 (%2) : PPS Request Failure [COMPLETED]	The equipment connection was faulty or the remote equipment power was OFF.	Retry.	
13372	FFIipInput	%1 (%2) : PPS Request Failure [DISCONTINUED]	The equipment connection was faulty or the remote equipment power was OFF.	Retry.	
13382	FFIipInput	%1 (%2) : Study List Refresh Exception%nError [%3]		Retry.	

Event	Event Source	Description	Causes	Remedies	Remarks
13386	FFIipInput	%1 (%2) : Failed in data reception%n[Online Time Out]	The serial cable was broken or the connected equipment did not respond.	Reinstall.	
13389	FFIdDepartSelect	%1 (%2) : Database Connection Error%n Database [%3]%n	The database was damaged.	Reinstall.	
13389	FFIdFilmMark	%1 (%2) : Database Connection Error%n Database [%3]%n	The database was damaged.	Reinstall.	
13389	FFIdParamedicSelect	%1 (%2) : Database Connection Error%n Database [%3]%n	The database was damaged.	Reinstall.	
13389	FFIdPatInfoInput	%1 (%2) : Database Connection Error%n Database [%3]%n	The database was damaged.	Reinstall.	
13389	FFIipInput	%1 (%2) : Database Connection Error%n Database [%3]%	The database was damaged.	Reinstall.	
13389	FFIdIndividualSelect	%1 (%2) : Database Connection Error%n Database [%3]%n	The database was damaged.	Repair the database.	
13392	FFIipInput	%1 (%2) : BCR Control Initialize Error	The barcode reader was not connected.	Connect the barcode reader.	
13420	FFIipInput	%1 (%2) : Failed in Menu Clear.%nInternal Error in Builtin [%3]	A problem occurred in the 550X unit when a cleared menu was reported.	Check the 550X unit.	
13421	FFIipInput	%1 (%2) : Menu Clear Command Time out [%3]	A timeout occurred because the 550X unit did not respond to a report about a cleared menu.	Check the 550X unit (power supply, cable, etc.).	
13423	FFIipInput	%1 (%2) : Failed in Ip Shelter.%nFatal Error [%3]	A problem occurred in the 550X unit during the IP evacuation sequence.	Check the 550X unit.	
13424	FFIipInput	%1 (%2) : Failed in Ip Shelter.%nIntervention Error in Builtin [%3]	A problem occurred in the 550X unit during the IP evacuation sequence.	Check the 550X unit. Solve the problem with a UTL or the like.	
13425	FFIipInput	%1 (%2) : Failed in Ip Shelter.%nInternal Error in Builtin [%3]	A problem occurred in the 550X unit during the IP evacuation sequence.	Check the 550X unit.	
13426	FFIipInput	%1 (%2) : Ip Shelter Command Time out [%3]	A timeout occurred because the 550X unit did not respond to an IP evacuation request.	Check the 550X unit (power supply, cable, etc.).	
13428	FFIipInput	%1 (%2) : Failed in Menu Fixed.%nConnection Error to Builtin [%3]	A line abnormality was encountered.	Check the line.	

Event	Event Source	Description	Causes	Remedies	Remarks
13429	FFlipInput	%1 (%2) : Failed in Menu Fixed.%nInternal Error in Builtin [%3]	A problem occurred in the 550X unit when a finalized menu was reported.	Check the 550X unit.	
13430	FFlipInput	%1 (%2) : Menu Fixed Command Time out [%3]	A timeout occurred because the 550X unit did not respond to a report about a finalized menu.	Check the 550X unit (power supply, cable, etc.).	
13432	FFlipInput	%1 (%2) : Failed in Ip Size%nConnection Error to Builtin [%3]	A line abnormality was encountered.	Check the line.	
13435	FFlipInput	%1 (%2) : Failed in Ip Size.%nInternal Error in Builtin [%3]	A problem occurred in the 550X unit when a size notification request was issued.	Check the 550X unit.	
13436	FFlipInput	%1 (%2) : Ip Size Command Time out [%3]	A timeout occurred because the 550X unit did not respond to a size notification request.	Check the 550X unit (power supply, cable, etc.).	
13438	FFlipInput	%1 (%2) : Failed in Ip Set.%nFatal Error [%3]	A problem occurred in the 550X unit during the IP setup sequence.	Check the 550X unit.	
13439	FFlipInput	%1 (%2) : Failed in Ip Set.%nIntervention Error in Builtin [%3]	A problem occurred in the 550X unit during the IP setup sequence.	Check the 550X unit. Solve the problem with a UTL or the like.	
13440	FFlipInput	%1 (%2) : Failed in Ip Set.%nInternal Error in Builtin [%3]	A problem occurred in the 550X unit during the IP setup sequence.	Check the 550X unit.	
13441	FFlipInput	%1 (%2) : Ip Set Command Time out [%3]	A timeout occurred because the 550X unit did not respond to an IP setup request.	Check the 550X unit (power supply, cable, etc.).	
13442	FFlipInput	%1 (%2) : Ip Delete Command Time out [%3]	A timeout occurred because the 550X unit did not issue an IP deletion request.	Check the 550X unit (power supply, cable, etc.).	
13443	FFlipInput	%1 (%2) : Cannot Change Patient Info EditMode [%3]	An attempt was made to change the patient information during an image input sequence (patient information change button: inactive).	Change the information after completion of image input.	
13444	FFlipInput	%1 (%2) : Cannot End Examination ExamEndMode [%3]	An attempt was made to terminate a study during an image input sequence (study end button: inactive).	Terminate the study after completion of image input.	
13447	FFlipInput	%1 : IipInput.exe [Starts]	IipInput.exe is started (information).		
13448	FFlipInput	%1 : IipInput.exe [Normal Termination]	IipInput.exe is terminated (information).		
13449	FFlipInput	%1 : IipInput.exe [Forced Termination]	IipInput.exe is terminated (information).		
13451	FFlipInput	%1 (%2) : Failed in Get Ip Information Response.%nConnection Error to Builtin [%3]	Line error.	Check the 550X unit (power supply, cable, etc.).	

Event	Event Source	Description	Causes	Remedies	Remarks
13452	FFlipInput	%1 (%2) : Get Ip Information Response Time out [%3]	A timeout occurred when an attempt was made to respond to an ID information request from the 550X unit.	Check the 550X unit (power supply, cable, etc.).	
13457	FFlipInput	%1 (%2) : Image Processing Information <InImg>	This error occurs if the image processing parameter file does not exist.		
13458	FFlipInput	%1 (%2) : Failed in Connection Between Reader and Console.%nIIP[%3]%nRU [-%4]	Setup error.	Change IIP's SysConfig setup or RU's connection style.	
13459	FFlipInput	%1 (%2) : Wait Timeout for X-Cont Shot Result	The XCON shot result reception timeout value for built-in type exposures was found improper.	Review the XCON shot result reception timeout value for built-in type exposures.	
13462	FFlipInput	%1 (%2) : Ordering Exposure Menu Not Entry [%3]	The exposure menu received as the ordering information was not registered.	Register the exposure menu with the user utility.	
13470	FFlipInput	%1 (%2) : Exposure Menu Register Error.	The exposure menu received as the ordering information was not registered.	Register the exposure menu with the user utility.	
13471	FFlipInput	%1 (%2) : All Exposure Menu Register Error.	The exposure menu received as the ordering information was not registered.	Register the exposure menu with the user utility.	
13472	FFlipInput	%1 (%2) : Selected Menu is Done. XCON Result Information is annulled. [%3]	The exposure process for the selected exposure menu was already performed. The result data received from the XCON will be discarded.	Select a menu for which an exposure process has not been performed.	
13473	FFlipInput	%1 (%2) : Menu is not Selected. XCON Result Information is annulled. [%3]	No exposure menu was selected. The result data received from the XCON will be discarded.	Select a menu for which an exposure process has not been performed.	
13474	FFlipInput	%1 (%2) : Exceeded the Limitation Value of XCON Exposure Data. [%3 = %4]	The XCON parameter was improperly set.	Reregister the XCON parameter with the user utility.	
13475	FFlipInput	%1 (%2) : Failed in Ordering Data.[RIS]	The patient exposure order information sent from the RIS was abnormal.		
13477	FFlipInput	%1 (%2) : Exposure Menu Register Error.	The exposure menu specified by the received ordering information was not registered.	Register the exposure menu with the user utility.	
13478	FFlipInput	%1 (%2) : All Exposure Menu Register Error.	The exposure menu specified by the received ordering information was not registered.	Register the exposure menu with the user utility.	
13479	FFlipInput	%1 (%2) : Failed in Examination End Command.[Ris]	The order exposure study termination signal was received from the RIS although an order exposure was not received.	Check the RIS settings.	

Event	Event Source	Description	Causes	Remedies	Remarks
13480	FFlipInput	%1 (%2) : Failed in Communication with RIS. [%3]%n[%4]	The problem is attributable to a disconnected line or invalid parameter.	Check the equipment and cables.	
13483	FFlipInput	%1 (%2) : Menu is not Selected. Failed in Getting ID Information	An ID acquisition request was received from built-in type equipment although no exposure menu was selected.	Make a menu selection and then press the OK button on the built-in type Console.	
13484	FFlipInput	%1 (%2) : Failed in the System Start. [Error: OpDcmStandardDx or MenuData.mdb]	Inappropriate installation.	Reinstall the system to secure matching between DX option and menu database.	
13489	FFlipInput	%1 (%2) : Patient Info Set Error%n Error [%3]%n RetCode [%4]	Patient information to be registered included illegal information items or patient information database was damaged.	Enter correct patient information or repair patient information database.	
13490	FFlipInput	%1 (%2) : UserName Check Error%n Item [%3]%n Error [%4]	Illegal information was input as the username.	Call upon the user to input a correct username.	
13491	FFlipInput	User Login [UserName:%1]	The user logged in the system.		
13492	FFlipInput	User Logout [UserName:%1	The user logged off the system.		
13493	FFlipInput	%1 (%2) : MCR-Data Send Error.[RIS]	Failed in transferring magnetic card information to the FRIS.	Repeat the same operation. If the symptom remains uncorrected, check the barcode information.	
13494	FFlipInput	%1 (%2) : BCR-Data Send Error.[RIS]	Failed in transferring barcode information to the FRIS.	Repeat the same operation. If the symptom remains uncorrected, check the barcode information.	
13495	FFlipInput	[%1] Failed in setting MCR data [%2]	Failed in setting magnetic card information.	Repeat the same operation. If the symptom remains uncorrected, check the magnetic card information.	
13496	FFlipInput	[%1] Failed in setting BCR data [%2]	Failed in setting barcode information.	Repeat the same operation. If the symptom remains uncorrected, check the barcode information.	
13497	FFlipInput	%1 (%2) : Failed in deleting multibyte data	Program error.		
13901	IIPInputEz	%1 : Registry Value Get/Set Error%n [Key] %2%n [Exp] %3%n %4%n %5	The acquisition/setup key or registration information was abnormal.	Check the registry key.	

Event	Event Source	Description	Causes	Remedies	Remarks
13902	IIPInputEz	%1 : Database Connection Error%n [DB] %2%n [Exp] %3%n %4%n %5	This error is attributable to an abnormal character string in Directory.ini, an incorrect database file name, or a damaged database.	Check Directory.ini or database file name.	
13903	IIPInputEz	%1 : Database Data Get/Set Error%n [DB] %2%n [Table] %3%n [Field] %4%n [Exp] %5	The acquisition/setup key or database was abnormal.	Check the database table/field name.	
13903	IIPInputEz	%1 : Dicom Data Object Get/Set Error%n [Tag] %2%n [Exp] %3%n %4%n %5	The DDO acquisition/setup tag was abnormal.	Check the DDO tag.	
13904	IIPInputEz	%1 : Other Error%n [Procedure] %2%n [ErrorCode] %3%n [Exp] %4%n %5	Unknown error.		
13998	FFIipInput	%1 (%2) : [%3]	General information event log.		
14900	IIPInputEz	%1 : Registry Value Get/Set Error%n [Key] %2%n [Exp] %3%n %4%n %5	An acquisition/setup key error. A registry information error.	Check the registry key.	
14900	IIPPortable	%1 : Registry Value Get/ Set Error [Key] %2 [Exp] %3 %4 %5	A registry was damaged.	There is no particular problem with operations.	
14901	IIPInputEz	%1 : Database Connection Error%n [DB] %2%n [Exp] %3%n %4%n %5	Incorrect Directory.ini file character strings. An incorrect database filename. Damaged database.	Check the Directory.ini file. Also check the database filename.	

Event	Event Source	Description	Causes	Remedies	Remarks
14901	IIPPortable	%1 : Database Connection Error [DB] %2 [Exp] %3 %4 %5	Failed in accessing the image database.	There is no particular problem with operations.	
14902	IIPInputEz	%1 : Database Data Get/Set Error%n [DB] %2%n [Table] %3%n [Field] %4%n [Exp] %5	An acquisition/setup key error. A database error.	Check the database table/filed name.	
14902	IIPPortable	%1 : Database Data Get/ Set Error [DB] %2 [Table]%3 [Field]%4 [Exp]%5	Failed in accessing the image database.	There is no particular problem with operations.	
14903	IIPInputEz	%1 : DDO Data Get/Set Error%n [Tag] %2%n %3%n %4%n %5	A DDO acquisition/setup tag error.	Check the DDO tag.	
14903	IIPPortable	%1 : DDO Data Get/Set Error [Tag] %2 %3 %4 %5	The DDO file was damaged.	There is no particular problem with operations.	
14904	IIPInputEz	%1 : Other Error%n [Procedure] %2%n [ErrorCode] %3%n [Exp] %4%n %5	Other error.		
14904	IIPPortable	%1: Other Error [Procedure] %2 [Error Code]%3 [Exp]%4 %5	A general-purpose information event log.	There is no particular problem with operations.	
19001	FFDICOMCommit SCU	Initialization failed. [DPM Invoke fail]	DPM thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMCommit SCU	Initialization failed. [DPC Invoke fail]	DPC thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMCommit SCU	Initialization failed. [Insufficient memory]	Instance generation was unsuccessful. The system was unstable.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
19001	FFDICOMEchoSCU	Initialization failed. [DPM Invoke fail]	DPM thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMEchoSCU	Initialization failed. [Insufficient memory]	Instance generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMMPPSSCU	Initialization failed. [DPM Invoke fail]	DPM thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMMPPSSCU	Initialization failed. [Insufficient memory]	Instance generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMMWLSCU	Initialization failed. [DPM Invoke fail]	DPM thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMMWLSCU	Initialization failed. [Insufficient memory]	Instance generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMPrintSCU	Initialization failed. [DPM Invoke fail]	DPM thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMPrintSCU	Initialization failed. [Insufficient memory]	Instance generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMStoreSCP	Initialization failed. [DPM Invoke fail]	DPM thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMStoreSCP	Initialization failed. [DPC Invoke fail]	DPC thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMStoreSCP	Initialization failed. [Insufficient memory]	Instance generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMStoreSCU	Initialization failed. [DPM Invoke fail]	DPM thread generation was unsuccessful. The system was unstable.	Restart.	
19001	FFDICOMStoreSCU	Initialization failed. [Insufficient memory]	Instance generation was unsuccessful. The system was unstable.	Restart.	
19002	FFDICOMCommit SCU	Method Invoke failed. [PushPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMCommit SCU	Method Invoke failed. [DiscontinueRequest]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMEchoSCU	Method Invoke failed. [EchoPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMMPPSSCU	Method Invoke failed. [CreatePrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMMPPSSCU	Method Invoke failed. [SetPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
19002	FFDICOMMWLSCU	Method Invoke failed. [FindPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMMWLSCU	Method Invoke failed. [CancelPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMPrintSCU	Method Invoke failed. [PrintPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMPrintSCU	Method Invoke failed. [GetPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMPrintSCU	Method Invoke failed. [DiscontinueRequest]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMQRSCU	Method Invoke failed. [FindPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMQRSCU	Method Invoke failed. [MovePrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMQRSCU	Method Invoke failed. [CancelPrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMQRSCU	Method Invoke failed. [FreePrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19002	FFDICOMStoreSCU	Method Invoke failed. [StorePrc]	A message was not successfully transmitted. The system was unstable.	Restart.	
19003	FFDICOMCommit SCU	File I/O failed. [Communication log file name]	A communication log file was not successfully opened.	Although the communication log cannot be obtained, execution is possible.	
19003	FFDICOMEchoSCU	File I/O failed. [Communication log file name]	A communication log file was not successfully opened.	Although the communication log cannot be obtained, execution is possible.	
19003	FFDICOMMPPSSCU	File I/O failed. [Communication log file name]	A communication log file was not successfully opened.	Although the communication log cannot be obtained, execution is possible.	
19003	FFDICOMMWLSCU	File I/O failed. [Communication log file name]	A communication log file was not successfully opened.	Although the communication log cannot be obtained, execution is possible.	
19003	FFDICOMPrintSCU	File I/O failed. [Communication log file name]	A communication log file was not successfully opened.	Although the communication log cannot be obtained, execution is possible.	

Event	Event Source	Description	Causes	Remedies	Remarks
19003	FFDICOMStoreSCP	File I/O failed. [Communication log file name]	An adequate disk space was not available.	Check the available disk space.	
19003	FFDICOMStoreSCP	File I/O failed. [Communication log file name]	An image-related file was not successfully accessed. The problem is attributable to a disk.	Restart. If the same symptom frequently occurs, replace the disk.	
19003	FFDICOMStoreSCP	File I/O failed. [Communication log file name]	A communication log file was not successfully opened.	Although the communication log cannot be obtained, execution is possible.	
19003	FFDICOMStoreSCU	File I/O failed. [Communication log file name]	A communication log file was not successfully opened.	Although the communication log cannot be obtained, execution is possible.	
19900	IIPInputEz	%1 : Registry Value Get/Set Error%n [Key] %2%n [Exp] %3%n %4%n %5	The acquisition/setup key or registration information was abnormal.	Check the registry key.	
19901	IIPInputEz	%1 : Database Connection Error%n [DB] %2%n [Exp] %3%n %4%n %5	This error is attributable to an abnormal character string in Directory.ini, an incorrect database file name, or a damaged database.	Check Directory.ini or database file name.	
19902	IIPInputEz	%1 : Database Data Get/Set Error%n [DB] %2%n [Table] %3%n [Field] %4%n [Exp] %5	The acquisition/setup key or database was abnormal.	Check the database table/field name.	
19903	IIPInputEz	%1 : Dicom Data Object Get/Set Error%n [Tag] %2%n [Exp] %3%n %4%n %5	The DDO acquisition/setup tag was abnormal.	Check the DDO tag.	
19904	IIPInputEz	%1 : Other Error%n [Procedure] %2%n [ErrorCode] %3%n [Exp] %4%n %5	Unknown error.		

Event	Event Source	Description	Causes	Remedies	Remarks
20001	FFCtrlProc	It failed in CreateProcess. It has the possibility that an executive file doesn't exist. The start treatment can't be continued. /CtrlProc: RunProc() %1	A subprocess was not successfully started up. The system was unstable or a necessary executable file was not found.	Restart. If the same symptom occurs after a restart, reinstall.	A subsystem name is placed in the "%1" position.
20002	FFCtrlProc	Process start information is unusual. The start treatment can't be continued. /CtrlProc: RunProc()	An illegal parameter was used for process startup. It is conceivable that the contents of the process information database were wrong.	Restart. If the same symptom occurs after a restart, reinstall.	
20003	FFCtrlProc	It failed in the completion message preparation treatment. The treatment can't be continued. / CtrlProc:EndProc()	A process end request message was not successfully created. It is conceivable that the available resource was not adequate or that the system was unstable.	Restart.	
20004	FFCtrlProc	It failed in the completion message transmitting treatment. The treatment can't be continued. / CtrlProc:EndProc()	A process end request message was not successfully transmitted. It is conceivable that the transmission destination process was down or that the transmission destination was wrong.	Restart.	
20005	FFCtrlProc	It failed in the switching message preparation treatment. The treatment can't be continued. / CtrlProc:ChangeProc()	A window show/hide message was not successfully created. It is conceivable that the available resource was not adequate or that the system was unstable.	Restart.	
20006	FFCtrlProc	It failed in the switching message transmitting treatment. The treatment can't be continued. / CtrlProc:ChangeProc()	A window show/hide message was not successfully transmitted. It is conceivable that the transmission destination process was down or that the transmission destination was wrong.	Restart. If the same symptom occurs after a restart, reinstall.	
20007	FFCtrlProc	It failed in CreateProcess. It has the possibility that an executive file doesn't exist. The start treatment can't be continued. /CtrlProc:SetInitProcEnd()	A window show/hide message was not successfully transmitted. It is conceivable that the transmission destination process was down or that the transmission destination was wrong.	Restart. If the same symptom occurs after a restart, reinstall.	
20102	FFCustomMsgBox	[20102] Setup not completed.	It is conceivable that the application key was not installed.	Install the application key.	Main
20104	FFCustomMsgBox	[20104] Failed in securing system settings.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom occurs after a restart, reinstall.	Main
20104	FFIIPMAIN	It failed in the acquisition of the configuration information. The initialization treatment can't be continued. / MainProcess:Main()	The configuration information was not successfully acquired. This error occurred due to an improper installation or system instability.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
20105	FFCustomMsgBox	[20105] Failed in accessing the process control database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom occurs after a restart, reinstall.	Main
20105	FFIIPMAIN	It failed in the acquisition of the process information data base. The initialization treatment can't be continued. /MainProcess: Main()	Data was not successfully acquired from the process information database. This error occurred due to an improper installation or system instability.	Restart. If the same symptom recurs, perform a reinstallation.	
20106	FFCustomMsgBox	[20106] Failed in accessing the message distribution control database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom occurs after a restart, reinstall.	Main
20106	FFIIPMAIN	It failed in opening of the message data base. The initialization treatment can't be continued. / MainProcess:Main()	The message database was not successfully opened. This error occurred due to an improper installation or system instability.	Restart. If the same symptom recurs, perform a reinstallation.	
20108	FFCustomMsgBox	[20108] Failed in process activation.	A subprocess was not successfully started up for some reason.	View the event logs around to examine the cause.	Main
20108	FFIIPMAIN	It failed in the start of the sub-process. The initialization treatment can't be continued. / MainProcess:Main()	The subprocess was not successfully started. This error occurred due to an improper installation or system instability.	Restart. If the same symptom recurs, perform a reinstallation.	
20110	FFCustomMsgBox	[20110] Failed in initialization processing.	The subprocess was not successfully started. It is conceivable that the system was unstable. This error may also occur as a consequence of the occurrence of another error.	Check for error messages and warnings issued before the occurrence of this error and then take a remedial action. Or, restart. If the same symptom recurs, perform a reinstallation.	Main
20110	FFIIPMAIN	It failed in the start of the sub-process. The initialization treatment can't be continued. /MainProcess: m_ProcessControl_ OnRunProcComplete()	The subprocess was not successfully started. This error occurred due to an improper installation or system instability.	Restart. If the same symptom recurs, perform a reinstallation.	
20111	—	—	The MAC address could not be acquired.	Reinstall the network driver (delete it and then reinstall). Or, manually acquire the MAC address with the Service Utility's MAC address acquisition function.	
20118	FFCustomMsgBox	[20118] Failed in process termination.	An error occurred for some reason during subprocess end processing.	No particular remedy needs be taken.	Main
20118	FFIIPMAIN	It failed in the completion of the sub-process. /MainProcess: ProcessEndRequirement()	The subprocess was not successfully terminated. The system was unstable.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
20124	FFCustomMsgBox	[20124] Failed in process switchover.	A subprocess was not successfully controlled for some reason.	View the event logs around to examine the cause.	Main
20124	FFIIPMAIN	It failed in switching of the process. /MainProcess: xxxxx	A subprocess changeover was not successfully effected. The target subprocess was not active or the system was unstable.	Restart.	
21001	FFCustomMsgBox	[21001] Failed in connecting to the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	List
21002	FFCustomMsgBox	[21002] Failed in accessing the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	List
21003	FFCustomMsgBox	[21003] Failed in obtaining information from the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	List
21004	FFCustomMsgBox	[21004] Failed in accessing the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	List
21005	FFCustomMsgBox	[21005] Failed in setting information to the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	List
21006	FFCustomMsgBox	[21006] Failed in deleting the study information.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	List
21007	FFCustomMsgBox	[21007] Failed in connecting to the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List

Event	Event Source	Description	Causes	Remedies	Remarks
21008	FFCustomMsgBox	[21008] Failed in accessing the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21009	FFCustomMsgBox	[21009] Failed in obtaining information from the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21010	FFCustomMsgBox	[21010] Failed in connecting to the character database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21011	FFCustomMsgBox	[21011] Failed in accessing the character database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21012	FFCustomMsgBox	[21012] Failed in obtaining information from the character database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21013	FFCustomMsgBox	[21013] Failed in accessing the definition file.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21014	FFCustomMsgBox	[21014] Failed in opening the registry information.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21015	FFCustomMsgBox	[21015] Failed in retrieving the registry information.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21016	FFCustomMsgBox	[21016] Failed in writing the registry information.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21017	FFCustomMsgBox	[21017] Failed in closing the registry information.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21018	FFCustomMsgBox	[21018] Failed in receiving message.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21019	FFCustomMsgBox	[21019] Failed in canceling the output processing.	The selected image was being output or already deleted.	No particular response is required.	List
21020	FFCustomMsgBox	[21020] Failed in output.	The selected image was being output or already deleted.	No particular response is required.	List
21021	FFCustomMsgBox	[21021] Failed in receiving the message.	The system was unstable.	No particular response is required.	List
21022	FFCustomMsgBox	[21022] Failed in initializing process for message communication.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21023	FFCustomMsgBox	[21023] Failed in terminating process for message communication.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21024	FFCustomMsgBox	[21024] Failed in obtaining information from the host setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21025	FFCustomMsgBox	[21025] Failed in editing the host setting database.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List

Event	Event Source	Description	Causes	Remedies	Remarks
21030	FFCustomMsgBox	[21030] Failed in study start.	Connection equipment was not operative or the network was unstable.	Check the connected equipment or network.	List
21031	FFCustomMsgBox	[21031] Failed in QA start.	Connection equipment was not operative or the network was unstable.	Check the connected equipment or network.	List
21032	FFCustomMsgBox	[21032] Failed in study re-start.	Connection equipment was not operative or the network was unstable.	Check the connected equipment or network.	List
21033	FFCustomMsgBox	[21033] Failed in obtaining study information from host %s.	Connection equipment was not operative or the network was unstable.	Check the connected equipment or network.	List
21034	FFCustomMsgBox	[21034] Failed in locking the study.	Connection equipment was not operative or the network was unstable.	Check the connected equipment or network.	List
21035	FFCustomMsgBox	[21035] Failed in study completion processing.	Connection equipment was not operative or the network was unstable.	Check the connected equipment or network.	List
21036	FFCustomMsgBox	[21036] The target study exists but is not displayed on the list.	Connection equipment was not operative or the network was unstable.	Check the connected equipment or network.	List
21037	FFCustomMsgBox	[21037] The target study could not be found.	The specified study may have been deleted.	No particular measures need to be taken.	List
21038	FFCustomMsgBox	[21038] The input format for date is wrong.	The input format was incorrect.	No particular measures need to be taken.	List
21039	FFCustomMsgBox	[21039] The input format for time is wrong.	The input format was incorrect.	No particular measures need to be taken.	List
21040	FFCustomMsgBox	[21040] Searched word is illegal.	The input word was incorrect.	No particular measures need to be taken.	List
21041	FFCustomMsgBox	[21041] Multiple target studies exist. The study cannot be started.	Two or more relevant studies existed.	No particular measures need to be taken.	List
21051	FFCustomMsgBox	[21051] An unknown study was received from the RIS.	- Software version A06 or earlier was used for MWM connection. - Illegal data was contained in the study information received from the RIS.	- Upgrade the software to version A07 or later. - Check the RIS side setup information and the like.	
21052	FFMWMHelper	[MWMHelper]%1	This is an information log.	There is no particular problem with operations.	
21053	FFMWMHelper	[MWMHelper]%1	A warning condition is encountered. For details, refer to the contents of the event log.	There is no particular problem with operations.	
21054	FFMWMHelper	[MWMHelper]%1	An error occurred.	Restart. A study received by means of MWM didn't include StudyInstanceUID (0020,000D). Request the MWM Server to send StudyInstanceUID.	
21101	FFCustomMsgBox	[21101] An error of unknown cause occurred.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List

Event	Event Source	Description	Causes	Remedies	Remarks
21102	FFCustomMsgBox	[21102] Failed in obtaining study information.	A specified study has already been deleted.	No particular response is required.	List
21103	FFCustomMsgBox	[21103] Unable to specify a target destination for move.	Destination for move was specified incorrectly.	No particular response is required.	List
21104	FFCustomMsgBox	[21104] Unable to specify a target destination for move.	Destination for move was specified incorrectly.	No particular response is required.	List
21105	FFCustomMsgBox	[21105] Unable to move an image.	Destination for move was specified incorrectly.	No particular response is required.	List
21106	FFCustomMsgBox	[21106] A study information display error occurred.	The study information included illegal data.	Check study data setting.	List
21129	FFCustomMsgBox	[21129] The hard disk was full.	- The free hard disk space was insufficient. - The shuttering process was used with software version A07 or earlier. Or, a forced termination procedure was performed during a startup or freeze (when version A07 or earlier was used).	- Delete unnecessary images. If any images are left without being output, output them. - Upgrade the software to version A08 or later and then initialize the image database.	Main
21201	FFCustomMsgBox	[21201] An error of unknown cause occurred.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21202	FFCustomMsgBox	[21202] Initialization has not been completed.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21203	FFCustomMsgBox	[21203] Radiographer information database is abnormal.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21204	FFCustomMsgBox	[21204] Failed in obtaining the registry information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21205	FFCustomMsgBox	[21205] Failed in setting registry values.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21206	FFCustomMsgBox	[21206] Failed in clearing a displayed image.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21207	FFCustomMsgBox	[21207] Failed in connecting to the database.	Connection equipment was not operative or the network was unstable.	Check other connected equipment or network.	List
21208	FFCustomMsgBox	[21208] Failed in connecting to the database.	Connection equipment was not operative or the network was unstable.	Check other connected equipment or network.	List
21209	FFCustomMsgBox	[21209] Failed in setting the study information sharing host.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21210	FFCustomMsgBox	[21210] Failed in obtaining the study information from the database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List
21211	FFCustomMsgBox	[21211] An error of unknown cause occurred in obtaining radiographer information.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	List

Event	Event Source	Description	Causes	Remedies	Remarks
21212	FFCustomMsgBox	[21212] An error of unknown cause occurred.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21213	FFCustomMsgBox	[21213] An error of unknown cause occurred. Study information cannot be obtained.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
21214	FFCustomMsgBox	[21214] Failed in starting remote search/acquisition processing.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
22100	FFIIPListMoveImage	Warning. %1	A warning was issued. For details, see the contents of the event log.	There is no particular problem with operations.	
22103	FFIIPMAIN	It failed in the acquisition of the configuration information. The initialization treatment can't be continued. / MainProcess:Main()	The version information was not successfully acquired. It is conceivable that the Version.env file did not exist in the specified directory or that the contents of the file were damaged.	Reinstall.	
22128	FFIIPMAIN	An error occurred in logfile backup treatment. / MainProcess:xxxxx	A log file backup was not successfully made. It is conceivable that the specified pathname was incorrect.	Reinstall. (Although there are no operational problems, various communication logs cannot be saved.)	
22200	FFIIPListMoveImage	Error. %1	An error occurred. For details, see the contents of the event log.	Since the process was aborted due to an error occurrence, it is conceivable that a data inconsistency may exist. Verify the data consistency.	
22201	FFIIPListMoveImage	Initialize Error. %1	The initialization process failed.	Restart.	
22202	FFIIPListMoveImage	FFGetString Error. %1	The FFGetString function returned an error.	Restart.	
22203	FFIIPListMoveImage	DB Connect Error. %1	The database connection was not successfully established.	Restart.	
22204	FFIIPListMoveImage	DB Get Error. %	Data could not be acquired from the database.	Restart.	
22205	FFIIPListMoveImage	SetDB Error. %1	Data could not be set up for the database.	Restart.	
22206	FFIIPListMoveImage	Dicom Data Object Get Error. %1	Data could not be acquired from the Dicom Data Object.	Restart.	
22207	FFIIPListMoveImage	Dicom Data Object Set Error. %1	Data could not be set up for the Dicom Data Object.	Restart.	
22208	FFIIPListMoveImage	Dicom Data Object Set Error. %1	An exception error occurred.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
23000	FFMWMStudyList	RegCreatekey() returned with Error at %1. [%2]	The RegCreateKey function returned an error.	Restart.	
23000	FFStudyList, FFOutputList	RegCreatekey() returned with Error at %1.%n[%2]	The user authority may not have been granted or installation may have been ended abnormally.	Use the normal startup procedure or perform reinstallation.	
23000	FFIIPListCustomize	RegCreatekey() returned with Error at %1.%n[%2]	The user authority may not have been granted or installation may have been ended abnormally.	Use the normal startup procedure or perform reinstallation.	
23000	FFIIPListSearch	RegCreatekey() returned with Error at %1.%n[%2]	The user authority may not have been granted or installation may have been ended abnormally.	Use the normal startup procedure or perform reinstallation.	
23000	FFIIPListMoveImage	Information. %1	Information log.	There are no operational problems.	
23000	FFMWMStudyList	Study couldn't be started automatically. %1. [%2]	Failed in starting a study automatically for any reason.	There are no operational problems.	
23001	FFMWMStudyList	RegOpenkey() returned with Error at %1. [%2]	The RegOpenKey function returned an error.	Restart.	
23001	FFStudyList, FFOutputList	RegOpenkey() returned with Error at %1.%n[%2]	The user authority may not have been granted or installation may have been ended abnormally.	Use the normal startup procedure or perform reinstallation.	
23001	FFIIPListCustomize	RegOpenkey() returned with Error at %1.%n[%2]	The user authority may not have been granted or installation may have been ended abnormally.	Use the normal startup procedure or perform reinstallation.	
23001	FFIIPListSearch	RegOpenkey() returned with Error at %1.%n[%2]	The user authority may not have been granted or installation may have been ended abnormally.	Use the normal startup procedure or perform reinstallation.	
23001	FFMWMStudyList	RegOpenkey() returned with Error at %1. [%2]	Failed in opening the registry (an error occurred with the program or the system was unstable).	Restart.	
23001	FFMediaList	RegOpenKey()returnedwith Error at %1. [%2]	The RegOpenKey function returned an error.	Restart.	
23002	FFMWMStudyList	RegClosekey() returned with Error at %1. [%2]	The RegOpenKey function returned an error.	Restart.	
23002	FFStudyList, FFOutputList	RegClosekey() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23002	FFIIPListCustomize	RegClosekey() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23002	FFIIPListSearch	RegClosekey() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	

Event	Event Source	Description	Causes	Remedies	Remarks
23002	FFMWMStudyList	RegClosekey() returned with Error at %1. [%2]	Failed in closing the registry (an error occurred with the program or the system was unstable).	Restart.	
23002	FFMediaList	RegCloseKey() returned withError at %1. [%2]	The RegCloseKey function returned an error.	Restart.	
23003	FFMWMStudyList	RegQueryNumericValue() returned with Error at %1. [%2]	The RegOpenKey function returned an error.	Restart.	
23003	FFStudyList, FFOutputList	RegQueryNumericValue() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23003	FFIIPListCustomize	RegQueryNumericValue() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23003	FFIIPListSearch	RegQueryNumericValue() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23003	FFMWMStudyList	RegQueryNumericValue() returned with Error at %1. [%2]	Failed in acquiring data from the registry or the program may not have been installed properly.	Restart.	
23003	FFMediaList	RegQueryNumericValue()returned with Error at %1. [%2]	The RegQueryNumericValue function returned an error.	Restart.	
23004	FFMWMStudyList	RegSetNumericValue() returned with Error at %1. [%2]	The RegOpenKey function returned an error.	Restart.	
23004	FFStudyList, FFOutputList	RegSetNumericValue() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23004	FFIIPListCustomize	RegSetNumericValue() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23004	FFIIPListSearch	RegSetNumericValue() returned with Error at %1.%n[%2]	The user authority may not have been granted.	Use the normal startup procedure.	
23004	FFMWMStudyList	RegSetNumericValue() returned with Error at %1. [%2]	Failed in writing data in the registry (an error occurred with the program or the system was unstable).	Restart.	
23004	FFMediaList	RegSetNumericValue()returned with Error at %1. [%2]	The RegSetNumericValue function returned an error.	Restart.	
23005	FFIIPListCustomize	FFGetString() returned with Error at %1.%n[%2]	The problem is attributable to a damaged Directory.ini file.	Ensure that the Directory.ini file is normal, and then restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
23005	FFIIPListSearch	FFGetString() returned with Error at %1.%n[%2]	The problem is attributable to a damaged Directory.ini file.	Ensure that the Directory.ini file is normal, and then restart.	
23005	FFMWMStudyList	FFGetString() returned with Error at %1. [%2]	The FFGetString function returned an error.	Restart.	
23005	FFMWMStudyList	FFGetString() returned with Error at %1. [%2]	The FFGetString function failed. This problem is attributable to an improper installation.	Perform a reinstallation or restart.	
23005	FFStudyList, FFOutputList	FFGetString() returned with Error at %1.%n[%2]	The problem is attributable to a damaged Directory.ini file.	Ensure that the Directory.ini file is normal, and then restart.	
23005	FFMediaList	FFGetString() returned with Error at %1. [%2]	The FFGetString function returned an error.	Restart.	
23006	FFIIPListCustomize	FFStrDBConnect() returned with Error at %1.%n[%2]	The problem is attributable to a damaged Directory.ini file or missing LangStr.mdb file.	Ensure that the Directory.ini file is normal, and then restart. Or, check the LangStr. mdb file.	
23006	FFIIPListSearch	FFStrDBConnect() returned with Error at %1.%n[%2]	The problem is attributable to a damaged Directory.ini file or missing LangStr.mdb file.	Ensure that the Directory.ini file is normal, and then restart. Or, check the LangStr. mdb file.	
23006	FFMWMStudyList	FFStrDBConnect() returned with Error at %1. [%2]	The FFStrDBConnect function failed. The problem is due to an improper installation or system instability.	Perform a reinstallation or restart.	
23006	FFMWMStudyList	FFStrDBConnect() returned with Error at %1. [%2]	The FFStrDBConnect function returned an error.	Restart.	
23006	FFStudyList, FFOutputList	FFStrDBConnect() returned with Error at %1.%n[%2]	The problem is attributable to a damaged Directory.ini file or missing LangStr.mdb file.	Ensure that the Directory.ini file is normal, and then restart. Or, check the LangStr. mdb file.	
23006	FFMediaList	FFStrDBConnect() returned with Error at %1. [%2]	The FFStrDBConnect function returned an error.	Restart.	
23007	FFIIPListCustomize	FFStrDBClose() returned with Error at %1.%n[%2]	The LangStr.mdb file was damaged.	Check the LangStr.mdb file.	
23007	FFIIPListSearch	FFStrDBClose() returned with Error at %1.%n[%2]	The LangStr.mdb file was damaged.	Check the LangStr.mdb file.	
23007	FFMWMStudyList	FFStrDBClose() returned with Error at %1. [%2]	The FFStrDBClose function failed.	Restart.	
23007	FFStudyList, FFOutputList	FFStrDBClose() returned with Error at %1.%n[%2]	The LangStr.mdb file was damaged.	Check the LangStr.mdb file.	
23007	FFMediaList	FFStrDBClose() returned with Error at %1. [%2]	The FFStrDBClose function returned an error.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
23008	FFIIPListCustomize	FFStrDBReadString() returned with Error at %1.%n[%2]	The LangStr.mdb file was damaged.	Check the LangStr.mdb file.	
23008	FFIIPListSearch	FFStrDBReadString() returned with Error at %1.%n[%2]	The LangStr.mdb file was damaged.	Check the LangStr.mdb file.	
23008	FFMWMStudyList	FFStrDBReadString() returned with Error at %1. [%2]	The FFStrDBReadString function returned an error.	Restart.	
23008	FFMWMStudyList	FFStrDBReadString() returned with Error at %1. [%2]	The FFStrDBReadString function failed. The problem is attributable to an improper installation.	Perform a reinstall or restart.	
23008	FFStudyList, FFOutputList	FFStrDBReadString() returned with Error at %1.%n[%2]	The LangStr.mdb file was damaged.	Check the LangStr.mdb file.	
23008	FFMediaList	FFStrDBReadString() returned with Error at %1. [%2]	The FFStrDBReadString function returned an error.	Restart.	
23009	FFIIPListCustomize	FFRegGetKeySZ() returned with Error at %1.%n[%2]	The problem is attributable to an unprivileged user.	Use the normal startup procedure.	
23009	FFIIPListSearch	FFRegGetKeySZ() returned with Error at %1.%n[%2]	The problem is attributable to an unprivileged user.	Use the normal startup procedure.	
23009	FFMWMStudyList	FFRegGetKeySZ() returned with Error at %1. [%2]	The FFRegGetKeySZ function returned an error.	Restart.	
23009	FFMWMStudyList	FFRegGetKeySZ() returned with Error at %1. [%2]	The FFRegGetKeySZ function failed. This error is attributable to an improper installation.	Perform a reinstall or restart.	
23009	FFStudyList, FFOutputList	FFRegGetKeySZ() returned with Error at %1.%n[%2]	The problem is attributable to an unprivileged user.	Use the normal startup procedure.	
23009	FFMediaList	FFRegGetKeySZ() returned with Error at %1. [%2]	The FFRegGetKeySZ function returned an error.	Restart.	
2300A	FFMWMStudyList	FFRegGetKeyDWORD() returned with Error at %1. [%2]	The FFRegGetKeyDWORD function failed. This error is attributable to an improper IIP installation.	Perform a reinstallation or restart.	
23010	FFIIPListCustomize	FFRegGetKeyDWORD() returned with Error at %1.%n[%2]	The problem is attributable to an unprivileged user.	Use the normal startup procedure.	
23010	FFIIPListSearch	FFRegGetKeyDWORD() returned with Error at %1.%n[%2]	The problem is attributable to an unprivileged user.	Use the normal startup procedure.	

Event	Event Source	Description	Causes	Remedies	Remarks
23010	FFMWMStudyList	FFRegGetKeyDWORD() returned with Error at %1. [%2]	The FFRegGetKeyDWORD function returned an error.	Restart.	
23010	FFStudyList, FFOutputList	FFRegGetKeyDWORD() returned with Error at %1.%n[%2]	The problem is attributable to an unprivileged user.	Use the normal startup procedure.	
23010	FFMediaList	FFRegGetKeyDWORD() returned with Error at %1. [%2]	The FFRegGetKeyDWORD function returned an error.	Restart.	
23011	FFStudyList, FFOutputList	FFSysDBConnect() returned with Error at %1.%n[%2]	It is conceivable that the Directory.ini file was damaged or the Hosts.mdb file did not exist.	Ensure that the Directory.ini file is normal, and then restart. Or, check the SysConfig. mdb file.	
23011	FFIIPListCustomize	FFHostDBInitialize() returned with Error at %1.%n[%2]	It is conceivable that the Directory.ini file was damaged or the Hosts.mdb file did not exist.	Ensure that the Directory.ini file is correct, and then restart the system or check the SysConfig.mdb file.	
23011	FFMWMStudyList	FFHostDBInitialize() returned with Error at %1. [%2]	FFHostDBInitialize() sent back an error.	Restart the system.	
23011	FFMediaList	FFHostDBInitialize() returned with Error at %1. [%2]	FFHostDBInitialize() returned an error.	Restart.	
23012	FFStudyList, FFOutputList	FFSysDBClose() returned with Error at %1.%n[%2]	This error is attributable to a damaged Directory.ini file.	Check the SysConfig.mdb file.	
23012	FFIIPListCustomize	FFHostDBGetQueryHost() returned with Error at %1.%n[%2]	It is conceivable that the Hosts.mdb file was damaged.	Check the Hosts.mdb file.	
23012	FFMWMStudyList	FFHostDBGetQueryHost() returned with Error at %1. [%2]	FFHostDBGetQueryHost() sent back an error.	Restart the system.	
23012	FFMediaList	FFHostDBGetQueryHost() returned with Error at %1. [%2]	FFHostDBGetQueryHost() returned an error.	Restart.	
23013	FFStudyList, FFOutputList	FFSysDBReadszValue() returned with Error at %1.%n[%2]	This error is attributable to a damaged Directory.ini file.	Check the SysConfig.mdb file.	
23013	FFIIPListCustomize	FFHostDBSetQueryHost() returned with Error at %1.%n[%2]	It is conceivable that the Hosts.mdb file was damaged.	Check the Hosts.mdb file.	
23013	FFMWMStudyList	FFHostDBSetQueryHost() returned with Error at %1. [%2]	FFHostDBSetQueryHost() sent back an error.	Restart the system.	
23013	FFMediaList	FFHostDBSetQueryHost() returned with Error at %1. [%2]	FFHostDBSetQueryHost() returned an error.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
23014	FFStudyList, FFOutputList	FFSysDBReadnValue() returned with Error at %1.%n[%2]	This error is attributable to a damaged Directory.ini file.	Check the SysConfig.mdb file.	
23014	FFMediaList	FFSysDBReadnValue() returned with Error at %1.%n [%2]	It is conceivable that the SysConfig.mdb file was damaged.	Restart.	
23015	FFStudyList, FFOutputList	Failed ImageDB Connection at %1.%n[%2]	The SQL Server Service Manager starts running or necessary files are not installed.	Ensure that the SQL Server is running.	
23015	FFMediaList	Failed ImageDB Connection at %1.%n [%2]	It is conceivable that the SQL Server Service Manager is not running or necessary files are not installed.	Ensure that the SQL Server is running.	
23016	FFStudyList, FFOutputList	Failed ImageDB Disconnection at %1.%n[%2]	The SQL Server Service Manager starts running or necessary files are not installed.	Ensure that the SQL Server is running.	
23017	FFStudyList, FFOutputList	Failed ImageDB Open Recordset at %1.%n[%2]	The SQL Server Service Manager starts running or necessary files are not installed.	Ensure that the SQL Server is running.	
23018	FFStudyList, FFOutputList	Failed ImageDB Update Recordset at %1.%n[%2]	The SQL Server Service Manager starts running or necessary files are not installed.	Ensure that the SQL Server is running.	
23019	FFStudyList, FFOutputList	Failed ImageDB Close Recordset at %1.%n[%2]	The SQL Server Service Manager starts running or necessary files are not installed.	Ensure that the SQL Server is running.	
23020	FFStudyList	Failed Get HostName as %1.%n[%2]	Failed in acquiring a host name. The network may have been set up incorrectly.	Check the network/network settings.	
23020	FFMediaList	Failed Get HostName as %1.%n[%2]	Failed in acquiring a host name. The network may have been set up incorrectly.	Check the network/network settings.	
23021	FFStudyList	Failed HostDB Data at %1.%n[%2]	Failed in acquiring data from the Hosts. mdb file. The database may have been damaged.	Check the Hosts.mdb file.	
23021	FFMediaList	Failed HostDB Data at %1.%n [%2]	Failed in acquiring data from the Hosts. mdb file. The database may have been damaged.	Check the Hosts.mdb file.	
23022	FFStudyList	Failed GetPossession at %1.%n[%2]	Failed in acquiring property. It is conceivable that any other equipment has already acquired property, network disconnected or power not turned ON.	Check the network/equipment.	
23022	FFStudyList	Failed GetPossession at %1.%n [%2]	Failed in acquiring property. It is conceivable that any other equipment has already acquired property, network disconnected or power not turned ON.	Check the network/equipment.	
23023	FFMediaList	Error Occurred.%n	An error occurred for any reason.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
23023	FFStudyList	Failed DDOChangeOrDelivery at %1.%n[%2]	A failure occurred in file change or delivery processing at film division/extension (12on1) output.	Restart the system.	
23024	FFStudyList	Failed DicomQ/R at %1.%n[%2]	A failure occurred when performing DICOM Q/R processing.	Check the network/network settings, and then restart the system as necessary.	
23025	FFStudyList	FFNetDBConnect() returned with Error at %1.%n [%2]	An attempt to establish connection to the network setup database resulted in a failure.	Check NetConfig.mdb and restart the system.	
23026	FFStudyList	Failed DicomQ/R Initialize at %1.%n[%2]	A failure occurred in initialization of DICOM Q/R processing.	Restart the system.	
23027	FFStudyList	Failed MultiPrintDDOUpdate at %1.%n[%2]	A failure occurred in file change processing at film division/extension (12on1) output.	Restart the system.	
23028	FFStudyList	Failed MultiPrintDelivery %1.%n[%2]	A failure occurred in delivery processing at film division/extension (12on1) output.	Restart the system.	
23029	FFStudyList	Failed FFNetDBGet %1.%n[%2]	An attempt to acquire data from the network setup database resulted in a failure.	Check NetConfig.mdb and restart the system.	
23099	FFIIPListCustomize	An unknown error occurred.%n[%1]	An unknown error occurred.	Restart.	
23099	FFIIPListSearch	An unknown error occurred.%n[%1]	An unknown error occurred.	Restart.	
23099	FFMWMStudyList	An unknown error occurred. [%1]	An exception error occurred.	Restart.	
23099	FFMWMStudyList	An unknown error occurred. [%1]	An unknown error occurred. This error is attributable to system instability.	Restart.	
23099	FFStudyList, FFOutputList	An unknown error occurred.%n[%1]	An unknown error occurred.	Restart.	
23099	FFMediaList	An unknown error occurred. [%1]	An exception error occurred.	Restart.	
23108	FFIIPMAIN	It failed in the start of the sub-process. The initialization treatment can't be continued. / MainProcess:Main()	A subprocess was not successfully started up. It is conceivable that installation was not properly completed or that the system was unstable.	Restart. If the same symptom occurs after a restart, reinstall.	
23118	FFIIPMAIN	It failed in the completion of the sub-process. /MainProcess: ProcessEndRequirement()	A subprocess was not successfully ended. It is conceivable that the system was unstable.	Restart.	
23124	FFIIPMAIN	It failed in switching of the process. /MainProcess: xxxxx	Subprocess switching was not successfully performed. It is conceivable that the target subprocess was not running or that the system was unstable.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
24001	FFCustomMsgBox	[24001] Selected study information will be fully deleted.	This dialog box opens for confirmation only.	No particular response is required.	List
24002	FFCustomMsgBox	[24002] No items displayed.	There were no items to be displayed in the list.	Select at least one display item.	List
24003	FFCustomMsgBox	[24003] The item width is too large.	The maximum display width was exceeded by the specified value.	Enter a smaller value.	List
24004	FFCustomMsgBox	[24004] Cancels the selected output request.	This dialog box opens for confirmation only.		List
24005	FFCustomMsgBox	[24005] The search target string “%S” was not found.	No data matched the entered search criteria.		List
24057	FFCustomMsgBox	[24057] Unable to receive information from the RIS trigger transmitter.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	List
24062	FFCustomMsgBox	[24062] Failed in changing the host setting.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	Worklist
29001	FFCustomMsgBox	[29001] Unexpected operational message received from the output process.	It is highly probable that the program was faulty.		List
29002	FFCustomMsgBox	[29002] Unexpected command message received from the output process.	It is highly probable that the program was faulty.		List
29010	FFIIPEvtMonitoringCtrl	[%1]%nThe error occurred in Win32 API.%n%2	The Win32 API function returned an error.	Restart.	Worklist
29011	FFIIPEvtMonitoringCtrl	[%1]%nThe exception error occurred.%n%2	An exception error occurred.	Restart.	
29107	FFIIPMAIN	It failed in the preparation of the pipe. The treatment can’t be continued. / MainProcess:Main()	The pipe for inter-process communication was not successfully created. It is conceivable that the system was unstable.	Restart.	
29112	FFIIPMAIN	It failed in the indication of the routine mode transition. /MainProcess: m_ProcessControl _OnRunProcComplete()	The routine transition instruction message was not successfully issued. It is conceivable that the subprocess was not running or that the pipe was not created.	Restart. If the same symptom occurs after a restart, reinstall.	
29114	FFIIPMAIN	An unusual message was received. This message is ignored. /MainProcess: m_ProcessComControl _OnRecvNotification()	The received message was unusual. It is conceivable that the message was not registered in the message information database or that the system was unstable.	Restart. If the same symptom occurs after a restart, reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
29115	FFIIPMAIN	An unusual send cause was received. This send cause is ignored. /MainProcess: m_ProcessComControl _OnRecvNotification()	A message was received from an unknown source. It is conceivable that the transmission source was not registered in the message information database or that a wrong transmission source was selected.	Restart. If the same symptom occurs after a restart, reinstall.	
29116	FFIIPMAIN	The form of the place of the transmission isn't right. /MainProcess: SendMessage()	An unknown transmission destination was specified for the received message. It is conceivable that the transmission destination was not registered in the message information database or that a wrong transmission destination was selected.	Restart. If the same symptom occurs after a restart, reinstall.	
29117	FFIIPMAIN	It failed in the message delivery. /MainProcess: SendMessage()	A message delivery was not successful. It is conceivable that the subprocess at the transmission destination was not running.	Restart. If the same symptom occurs after a restart, reinstall.	
29119	FFIIPMAIN	It failed in the process completion notice. /MainProcess:ProcessEnd-AnswerMessage()	An end notice was not successfully sent to the subprocess. It is conceivable that the subprocess was not running or that the system was unstable.	Restart.	
29122	FFIIPMAIN	It failed in the unusual occurrence notice. /MainProcess: ErrorNoticeMessage()	An error notice was not successfully sent to the subprocess. It is conceivable that the subprocess was not running or that the system was unstable.	Restart.	
29123	FFIIPMAIN	It failed in the pipe close. /MainProcess: EndMainProcess()	An inter-process communication pipe was not successfully closed. It is conceivable that the system was unstable.	Restart.	
29125	FFIIPMAIN	It failed in close of the message data base. / MainProcess:xxxxx	The message database was not successfully closed. It is conceivable that the system was unstable.	Restart.	
29126	FFIIPMAIN	It failed in reading of the registry information. / MainProcess:xxxxx	Data was not successfully acquired from the registry. It is conceivable that installation was not properly completed.	Reinstall.	
29127	FFIIPMAIN	It failed in writing of the registry information. / MainProcess:xxxxx	Data was not successfully written into the registry. It is conceivable that the system was unstable.	Restart.	
29130	FFCustomMsgBox	[29130] The system is now starting up.	This dialog box opens for confirmation only. It appears when the system returns from a user utility to an application.		
30001	FFCustomMsgBox	[30001] Failed in obtaining the connection characters to the character database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30002	FFCustomMsgBox	[30002] Failed in connecting to the character database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
30003	FFCustomMsgBox	[30003] Failed in obtaining the connection characters to the system setting database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30004	FFCustomMsgBox	[30004] Failed in connecting to the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30005	FFCustomMsgBox	[30005] Failed in obtaining the connection characters to the image database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30013	FFCustomMsgBox	[30013] Failed in saving listed (worklist) display settings.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30019	FFCustomMsgBox	[30019] Failed in obtaining the connection characters to the network setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30027	FFCustomMsgBox	[30027] Failed in initializing the list (worklist). obtained.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30045	FFCustomMsgBox	[30045] IP address on the Image Reader not obtained.	It is conceivable that the database file was damaged or improperly set.	Restart. If the same symptom recurs, perform a reinstallation.	
30057	FFCustomMsgBox	[30057] Failed in receiving the message.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30085	FFCustomMsgBox	[30085] Failed in obtaining the connection characters to the Image Reader status information database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30105	FFCustomMsgBox	[30105] Failed in list initialization (waiting for study).	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30106	FFCustomMsgBox	[30106] Failed in list initialization (waiting for QA).	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30107	FFCustomMsgBox	[30107] Failed in list initialization (waiting for output).	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30108	FFCustomMsgBox	[30108] Failed in list initialization (already output).	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30109	FFCustomMsgBox	[30109] Failed in list initialization (all).	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30110	FFCustomMsgBox	[30110] Failed in list initialization (today).	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
30117	FFCustomMsgBox	[30117] Failed in updating list (worklist) display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30121	FFCustomMsgBox	[30121] Failed in obtaining the connection characters to the Image Reader information database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30122	FFCustomMsgBox	[30122] Failed in accessing the Image Reader information database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30125	FFCustomMsgBox	[30125] Failed in obtaining the system setting information (IP size series).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30129	FFCustomMsgBox	[30129] Failed in obtaining the system setting information (Pantomography processing).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30147	FFCustomMsgBox	[30147] Failed in obtaining the system setting information (Magnetic card type).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30148	FFCustomMsgBox	[30148] Failed in obtaining the system setting information (Magnetic card type).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30149	FFCustomMsgBox	[30149] Failed in obtaining the system setting information (Hospital card used).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30150	FFCustomMsgBox	[30150] Failed in accessing the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30151	FFCustomMsgBox	[30151] Failed in initialization processing.	- The connection to the network was not established. - Node setup was not completed for “THIS HOST (IIP)” under “Network Config”. - The system was unstable.	- Connect to the network. - Set a dummy node for “THIS HOST (IIP)” (e.g., DICOM Print). - Restart. If the same symptom recurs, perform a reinstallation.	
30152	FFCustomMsgBox	[30152] Failed in obtaining the pass information (image data folder).	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
30153	FFCustomMsgBox	[30153] The shutdown process resulted in a failure.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30155	FFCustomMsgBox	[30155] Failed in list initialization (waiting for study).	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
30157	FFCustomMsgBox	[30157] Database access was unsuccessful.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
30200	FFCustomMsgBox	[30200] Failed in RIS activation.	There may be a problem with the RIS module or RIS setup.	Verify the settings and then restart. If the same symptom recurs, perform a reinstallation.	
30201	FFCustomMsgBox	[30201] A communication error with RIS occurred.	There may be a problem with the RIS module or RIS setup.	Verify the settings and then restart. If the same symptom recurs, perform a reinstallation.	
30202	FFCustomMsgBox	[30202] A communication error with RIS occurred.	There may be a problem with the RIS module or RIS setup.	Verify the settings and then restart. If the same symptom recurs, perform a reinstallation.	
30204	FFCustomMsgBox	[30204] Because of improperly performed installation processing, the system cannot be started.	Failed in installation.	Reinstall.	
30205	FFCustomMsgBox	[30205] Failed in search processing.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
30206	FFCustomMsgBox	[30206] Failed in initializing patient-incidental information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31001	FFCustomMsgBox	[31001] Failed in obtaining the registry information (font name).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31002	FFCustomMsgBox	[31002] Failed in obtaining the registry information (font size).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31003	FFCustomMsgBox	[31003] Failed in obtaining the registry information (multi-byte language information).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31004	FFCustomMsgBox	[31004] Failed in obtaining the used language in system setting.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31005	FFCustomMsgBox	[31005] Failed in obtaining the connection characters to the character database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31006	FFCustomMsgBox	[31006] Failed in connecting to the character database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31007	FFCustomMsgBox	[31007] Failed in obtaining the connection characters to the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31008	FFCustomMsgBox	[31008] Failed in connecting to the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31010	FFCustomMsgBox	[31010] Failed in connecting to the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31011	FFCustomMsgBox	[31011] Failed in acquiring information from the image database.	- The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database. - Software version A07 or earlier was used.	- Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted). - Upgrade the software to version A08 or later.	
31012	FFCustomMsgBox	[31012] Failed in accessing the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31013	FFCustomMsgBox	[31013] Failed in obtaining the information from the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31014	FFCustomMsgBox	[31014] Failed in setting information to the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31015	FFCustomMsgBox	[31015] Failed in deleting the information from the image database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	

Event	Event Source	Description	Causes	Remedies	Remarks
31016	FFCustomMsgBox	[31016] Failed in connecting to the flag database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31017	FFCustomMsgBox	[31017] Failed in accessing the flag database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31018	FFCustomMsgBox	[31018] Failed in setting information to the flag database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31019	FFCustomMsgBox	[31019] Failed in initialization process for menu setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31020	FFCustomMsgBox	[31020] Failed in obtaining the menu information from the menu setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31021	FFCustomMsgBox	[31021] Failed in obtaining the menu parameter information from the menu setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31022	FFCustomMsgBox	[31022] Failed in terminating the menu setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31023	FFCustomMsgBox	[31023] Failed in obtaining the connection characters to the network setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31024	FFCustomMsgBox	[31024] Failed in connecting to the network setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31025	FFCustomMsgBox	[31025] Failed in obtaining the information from the network setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31026	FFCustomMsgBox	[31026] Failed in issuing the image information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31027	FFCustomMsgBox	[31027] Failed in obtaining the image information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation. Use the DICOM MWM C-FIND Tag Setting of CL Service Utility to see if Distribution Code (ID:141) is checked or not. If checked, uncheck it.	
31028	FFCustomMsgBox	[31028] Failed in setting the image information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31029	FFCustomMsgBox	[31029] Failed in deleting the image information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31030	FFCustomMsgBox	[31030] Failed in reading the image information file.	An image-related file was not successfully accessed. The problem is attributable to a disk.	Restart. If the same symptom frequently occurs, replace the disk.	
31031	FFCustomMsgBox	[31031] Failed in writing the image information file.	An image-related file was not successfully accessed. The problem is attributable to a disk.	Restart. If the same symptom frequently occurs, replace the disk.	
31032	FFCustomMsgBox	[31032] Failed in releasing the image information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31033	FFCustomMsgBox	[31033] Failed in obtaining the caption information (ID#).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31034	FFCustomMsgBox	[31034] Failed in obtaining the caption information (study#).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31035	FFCustomMsgBox	[31035] Failed in obtaining the caption information (patient name).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31036	FFCustomMsgBox	[31036] Failed in obtaining the caption information (Kanji-patient name).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31037	FFCustomMsgBox	[31037] Failed in obtaining the caption information (sex).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31038	FFCustomMsgBox	[31038] Failed in obtaining the caption information (sex: M).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31039	FFCustomMsgBox	[31039] Failed in obtaining the caption information (sex: F).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31040	FFCustomMsgBox	[31040] Failed in obtaining the caption information (sex: O).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31041	FFCustomMsgBox	[31041] Failed in obtaining the caption information (data of birth).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31042	FFCustomMsgBox	[31042] Failed in obtaining the system setting information (ID# input character limitation).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31043	FFCustomMsgBox	[31043] Failed in obtaining the system setting information (Study # input character limitation).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31044	FFCustomMsgBox	[31044] Failed in obtaining the system setting information (ID # pudding format).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31045	FFCustomMsgBox	[31045] Failed in obtaining the system setting information (Study # pudding format).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31047	FFCustomMsgBox	[31047] Failed in obtaining the system setting information (date of birth format).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31051	FFCustomMsgBox	[31051] Invalid character is input in ID #.	A 2-byte character, @, or other unacceptable character was contained.	Make a proper entry.	
31052	FFCustomMsgBox	[31052] Invalid character is input in Study #.	A 2-byte character, @, or other unacceptable character was contained.	Make a proper entry.	
31053	FFCustomMsgBox	[31053] Invalid character is input in patient name.	A 2-byte character, @, or other unacceptable character was contained.	Make a proper entry.	
31054	FFCustomMsgBox	[31054] Invalid character is input in kanji-patient name.	A 1-byte character or other unacceptable character was contained.	Make a proper entry.	
31055	FFCustomMsgBox	[31055] Invalid character is input in sex.	A character other than “M”, “F”, and “O” was contained.	Make a proper entry.	
31056	FFCustomMsgBox	[31056] Invalid format for date of birth is input.	The entry did not agree with a preselected birth date format.	Make a proper entry.	
31057	FFCustomMsgBox	[31057] Failed in accessing the requesting department database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31058	FFCustomMsgBox	[31058] Failed in obtaining the caption information (requesting dep.).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31059	FFCustomMsgBox	[31059] Failed in obtaining the item information for displaying in the requesting dep. Selection list.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31060	FFCustomMsgBox	[31060] Failed in obtaining the requesting department information.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31061	FFCustomMsgBox	[31061] Failed in obtaining the connection characters to the requesting department database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31062	FFCustomMsgBox	[31062] Failed in accessing the technician information database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31063	FFCustomMsgBox	[31063] Failed in caption information (technician).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31064	FFCustomMsgBox	[31064] Failed in obtaining the item information for displaying in the technician selection list.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31065	FFCustomMsgBox	[31065] Failed in obtaining the technician information.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31066	FFCustomMsgBox	[31066] Failed in obtaining the connection characters to the technician database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31067	FFCustomMsgBox	[31067] Failed in obtaining the registry information (window size).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31068	FFCustomMsgBox	[31068] No patient information is input.	Nothing was entered in the patient information input field.	Enter at least the patient's sex.	
31069	FFCustomMsgBox	[31069] Failed in obtaining the system setting information (succeeded from exposure menu reservation list).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31070	FFCustomMsgBox	[31070] Multiple studies cannot be executed.	An attempt was made to start an examination process with more than one examination item selected from an examination waiting list.	Start an examination process with one examination item selected.	
31071	FFCustomMsgBox	[31071] No list is selected.	An attempt was made to start execution with no examination item selected.	Select at least one examination item.	
31072	FFCustomMsgBox	[31072] Invalid character is input for film annotation.	An unacceptable character was contained.	Make a proper entry.	
31074	FFCustomMsgBox	[31074] Failed in obtaining the information from the flag database.	The problem is attributable, for instance, to an inactive SQL service manager or uninitialized image database.	Check whether the SQL service manager is normally operating. If the symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
31076	FFCustomMsgBox	[31076] Failed in obtaining the button image (Clear button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31077	FFCustomMsgBox	[31077] Failed in obtaining the button image (OK button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31078	FFCustomMsgBox	[31078] Failed in obtaining the button image (Cancel button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31079	FFCustomMsgBox	[31079] Failed in obtaining the button image (increment button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31080	FFCustomMsgBox	[31080] Failed in obtaining the button image (decrement button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31081	FFCustomMsgBox	[31081] Failed in obtaining the button image (Next page button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31082	FFCustomMsgBox	[31082] Failed in obtaining the button image (previous page button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31097	FFCustomMsgBox	[31097] Failed in obtaining the information from the character database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31099	FFCustomMsgBox	[31099] An error of unknown cause occurred.	It is highly probable that the program was faulty.		
31100	FFCustomMsgBox	[31100] The image display process resulted in a failure while operating in the image input subsystem.	It is conceivable that the image data or image information file was damaged.	Restart. If the same symptom recurs, perform a reinstallation.	
31101	FFCustomMsgBox	[31101] Failed in obtaining the pass information (log saving folder).	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31103	FFCustomMsgBox	[31103] Failed in calling up the patient information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31105	FFCustomMsgBox	[31105] Failed in terminating the image input subsystem.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31106	FFCustomMsgBox	[31106] Failed in terminating the image input subsystem.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31107	FFCustomMsgBox	[31107] Failed in image inputting process in the image input sub-system.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31108	FFCustomMsgBox	[31108] Failed in image inputting process in the image input sub-system.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31109	FFCustomMsgBox	[31109] Failed in image inputting process in the image input sub-system.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31110	FFCustomMsgBox	[31110] Failed in calling up the exposure menu.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31111	FFCustomMsgBox	[31111] Failed in study terminating process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31112	FFCustomMsgBox	[31112] Failed in image inputting process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31113	FFCustomMsgBox	[31113] Failed in image inputting process.	- Software version A07 or earlier was used. - The system was unstable.	- Upgrade the software to version A08 or later. - Restart. If the same symptom recurs, perform a reinstallation.	
31114	FFCustomMsgBox	[31114] Failed in specifying the urgent processing.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31116	FFCustomMsgBox	[31116] Communication line for monitoring the connection status with the Image Reader(%s) has broken.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31117	FFCustomMsgBox	[31117] No connection monitoring response from the Image Reader(%s).	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31118	FFCustomMsgBox	[31118] Control line with the Image Reader(%s) has broken.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31119	FFCustomMsgBox	[31119] No command response from the Image Reader(%s).	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31120	FFCustomMsgBox	[31120] Failed in Image Reader status control.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31121	FFCustomMsgBox	[31121] Command requested to the Image Reader has not been executed.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31122	FFCustomMsgBox	[31122] Failed in obtaining the information (status) from the Image Reader.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31123	FFCustomMsgBox	[31123] Failed in obtaining the information (machine code) from the Image Reader.	It is highly probable that the RU or line was faulty.	Check the RU and line.	

Event	Event Source	Description	Causes	Remedies	Remarks
31124	FFCustomMsgBox	[31124] Failed in obtaining the information (FRUP version) from the Image Reader.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31125	FFCustomMsgBox	[31125] Failed in re-connecting with the Image Reader.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31126	FFCustomMsgBox	[31126] Failed in breaking connection with the Image Reader.	It is highly probable that the RU or line was faulty.	Check the RU and line.	
31127	FFCustomMsgBox	[31127] Failed in obtaining the caption information (Study with QA completed).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31128	FFCustomMsgBox	[31128] Failed in obtaining the caption (only exposure competed).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31129	FFCustomMsgBox	[31129] Failed in obtaining the caption information (Study interrupt button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31130	FFCustomMsgBox	[31130] Failed in obtaining the caption information (Cancel button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31131	FFCustomMsgBox	[31131] Failed in obtaining the caption information (Study reception tab).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31132	FFCustomMsgBox	[31132] Failed in obtaining the caption information (waiting for study tab).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31133	FFCustomMsgBox	[31133] Failed in obtaining the caption information (waiting for QA tab).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31134	FFCustomMsgBox	[31134] Failed in obtaining the caption information (Waiting for output tab).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31135	FFCustomMsgBox	[31135] Failed in obtaining the caption information (Already output tab).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31136	FFCustomMsgBox	[31136] Failed in obtaining the caption information (All tab).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31137	FFCustomMsgBox	[31137] Failed in obtaining the caption information (Today tab).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31138	FFCustomMsgBox	[31138] Failed in obtaining the button image (System button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31139	FFCustomMsgBox	[31139] Failed in obtaining the caption information (Study reservation button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31140	FFCustomMsgBox	[31140] Failed in obtaining the caption information (Study start button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31141	FFCustomMsgBox	[31141] Patient information is illegal.	An unacceptable character was contained.	Make a proper entry.	
31142	FFCustomMsgBox	[31142] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31143	FFCustomMsgBox	[31143] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31144	FFCustomMsgBox	[31144] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31145	FFCustomMsgBox	[31145] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31146	FFCustomMsgBox	[31146] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31147	FFCustomMsgBox	[31147] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31148	FFCustomMsgBox	[31148] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31149	FFCustomMsgBox	[31149] Failed in obtaining the display group data.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31152	FFCustomMsgBox	[31152] Failed in obtaining the exposure menu information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31153	FFCustomMsgBox	[31153] Failed in obtaining the button image (Urgent button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31154	FFCustomMsgBox	[31154] Failed in obtaining the button image (Study completed button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31155	FFCustomMsgBox	[31155] Failed in obtaining the button image (Update button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31158	FFCustomMsgBox	[31158] Failed in obtaining the button image (New button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31159	FFCustomMsgBox	[31159] Failed in obtaining the button image (Repeat button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31160	FFCustomMsgBox	[31160] Failed in obtaining the button image (Re-shoot button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31161	FFCustomMsgBox	[31161] Failed in obtaining the button image (Add button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31162	FFCustomMsgBox	[31162] Failed in obtaining the button image (Delete button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31163	FFCustomMsgBox	[31163] Failed in obtaining the button image (Before scroll button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31164	FFCustomMsgBox	[31164] Failed in obtaining the button image (After Scroll button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31165	FFCustomMsgBox	[31165] Failed in obtaining the button image (Monitor mode button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31166	FFCustomMsgBox	[31166] Failed in obtaining the button image (QA button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31167	FFCustomMsgBox	[31167] Failed in obtaining the button image (Change button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31168	FFCustomMsgBox	[31168] Failed in obtaining the button image (Rotation/ Inversion button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31169	FFCustomMsgBox	[31169] Failed in obtaining the button image (EDR mode button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31170	FFCustomMsgBox	[31170] Failed in obtaining the button image (Image format button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31171	FFCustomMsgBox	[31171] Failed in obtaining the button image (Change menu parameter button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31172	FFCustomMsgBox	[31172] Failed in obtaining the tool tip (New button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31173	FFCustomMsgBox	[31173] Failed in obtaining the tool tip (Repeat button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31174	FFCustomMsgBox	[31174] Failed in obtaining the tool tip (Re-shoot button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31175	FFCustomMsgBox	[31175] Failed in obtaining the tool tip (Add button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31176	FFCustomMsgBox	[31176] Failed in obtaining the tool tip (Delete button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31177	FFCustomMsgBox	[31177] Failed in obtaining the tool tip (Before scroll button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31178	FFCustomMsgBox	[31178] Failed in obtaining the tool tip (After scroll button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31179	FFCustomMsgBox	[31179] Failed in obtaining the tool tip (Monitor mode button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31180	FFCustomMsgBox	[31180] Failed in obtaining the tool tip (QA button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31181	FFCustomMsgBox	[31181] Failed in obtaining the tool tip (Change button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31182	FFCustomMsgBox	[31182] Failed in obtaining the tool tip (Rotation/ Inversion button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31183	FFCustomMsgBox	[31183] Failed in obtaining the tool tip (EDR mode button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31184	FFCustomMsgBox	[31184] Failed in obtaining the tool tip (Image format button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31185	FFCustomMsgBox	[31185] Failed in obtaining the tool tip (Change menu parameter button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31186	FFCustomMsgBox	[31186] Failed in obtaining the registry information (Set No.).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31187	FFCustomMsgBox	[31187] Failed in setting the tool tip (Before scroll button).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31188	FFCustomMsgBox	[31188] Failed in obtaining the system setting information (System ID).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31189	FFCustomMsgBox	[31189] Failed in obtaining the system setting information (Auto-distribution instruction information).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31191	FFCustomMsgBox	[31191] Failed in obtaining the system setting information (Selector auto-switchover information).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31192	FFCustomMsgBox	[31192] Failed in obtaining the system setting information (Menu auto-sequence information).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31193	FFCustomMsgBox	[31193] Failed in obtaining the system setting information (Set No. minimum value information).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31194	FFCustomMsgBox	[31194] Failed in obtaining the system setting information (Set No. maximum value information).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31196	FFCustomMsgBox	[31196] Failed in obtaining the system setting information (Series information issuing method).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31197	FFCustomMsgBox	[31197] No matching work ID exists.	The contents of the image file did not agree with those of the image database.	Initialize the image database.	
31198	FFCustomMsgBox	[31198] Failed in distribution process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31201	FFIIPInImgCtrl	Data error. [Detailed error information 31201 2 items]	Abnormal data was entered from the RU or the 5000 Series equipment.	Check the RU and the 5000 Series equipment. Perform an image input process again or restart.	
31201	FFIIPInImgCtrl	Image sizecode error.	Illegal image size code when a request was issued for image input.	Check the RU and the 5000 Series equipment. Perform an image input process again or restart.	
31201	FFIIPInImgCtrl	InImgReadProc method parameter error.	Illegal image input request method parameters.	Check the RU and the 5000 Series equipment. Perform an image input process again or restart.	
31201	FFInImgMonitorCtrl	Data error.%n[%1]	Input data was incorrect.	Restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
31202	FFCustomMsgBox	[31202] Failed in obtaining the system setting information (Patient information online serial port No.).	It is conceivable that the database file was damaged or deleted.	Check the RU and the 5000 Series equipment. Perform an image input process again or restart.	
31202	FFIIPInImgCtrl	Initialize error. [Detailed error information 31202 14 items]	An abnormality occurred in the initialization process. The common probable causes are as follows: • Installation was not normally ended. • The parameter file was incorrect.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	Create Instance error.	Failed in creating Control Instance.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	Directory path get error.	Failed in acquiring each directory path name.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	Thread make error.(Read)	Failed in creating image input thread.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	Thread make error.(Disp)	Failed in creating image display thread.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	EDR parameter file load error.	Failed in memory loading of the EDR processing parameter file.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	Image parameter file load error.	Failed in memory loading of the image processing parameter file.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	GetMessage(THREAD_ END) error.	Failed in acquiring the image input/display thread startup completion event.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	DICOM SCP control run error.	Failed in DICOM SCP control startup.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	

Event	Event Source	Description	Causes	Remedies	Remarks
31202	FFIIPInImgCtrl	GetMessage(DICOM_ RUN_COMPLETE) error.	Failed in acquiring the DICOM SCP control startup completion event.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	PostThreadMessage(IMG_ END_REQ) error.	Failed in requesting for terminating image input thread.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	PostThreadMessage(DISP _END_REQ) error.	Failed in requesting for terminating image display thread.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	GetMessage(THREAD_ COMPLETE) error.	Failed in acquiring the image input/display thread termination completion event.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	GetMessage(DICOM_END _COMPLETE) error.	Failed in acquiring the DICOM SCP control termination completion event.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFIIPInImgCtrl	DICOM SCP control (EndPrc method) error.	Failed in requesting for terminating DICOM SCP control.	Restart the system. If the same symptom occurs after a restart, perform a reinstallation and initialize the image database.	
31202	FFInImgMonitorCtrl	Initialize error.%n[%1]	Failed in initialization processing.	Restart the system.	
31203	FFCustomMsgBox	[31203] Failed in obtaining the system setting information (Patient information online device name.).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31203	FFInImgMonitorDispCtrl	Method process error.%n [%1]	An error was detected during method processing.	Restart the system.	
31204	FFInImgMonitorDispCtrl	Windows API access error. %n[%1]	The system was unstable.	Restart the system.	
31205	FFInImgMonitorDispCtrl	Parameter error.%n[%1]	An abnormal parameter was detected.	Restart the system.	
31206	FFInImgMonitorDispCtrl	Memory access error. %n[%1]	System memory was insufficient.	Restart the system.	
31207	FFInImgMonitorDispCtrl	Function error.%n[%1]	An error was detected during internal processing.	Restart the system.	
31207	FFCustomMsgBox	[31207] Failed in setting the Image Reader machine code.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31208	FFCustomMsgBox	[31208] Failed in obtaining the button image (New button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31208	FFInImgMonitorDispCtrl	File access error.%n[%1]	The system was unstable.	Restart the system.	
31210	FFCustomMsgBox	[31210] Failed in obtaining the system setting information (Image rotation/ inversion selectable range).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31211	FFCustomMsgBox	[31211] Failed in obtaining the button image (frontal image button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31212	FFCustomMsgBox	[31212] Failed in obtaining the button image (Left-right invert button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31213	FFCustomMsgBox	[31213] Failed in obtaining the button image (Up-side-down invert button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31214	FFCustomMsgBox	[31214] Failed in obtaining the button image (180 degree rotation button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31215	FFCustomMsgBox	[31215] Failed in obtaining the button image (90 degree rotation button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31218	FFCustomMsgBox	[31218] Failed in obtaining the system setting information (Image format selectable range).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31219	FFCustomMsgBox	[31219] Failed in obtaining the button image (SINGLE button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31220	FFCustomMsgBox	[31220] Failed in obtaining the button image (TWIN button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31225	FFCustomMsgBox	[31225] Failed in obtaining the connection characters to the film annotation database.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31226	FFCustomMsgBox	[31226] Failed in connecting characters to the film annotation database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31227	FFCustomMsgBox	[31227] Failed in obtaining the information from the film annotation database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31232	FFCustomMsgBox	[31232] Failed in obtaining the system setting information (upper limit of No. of output film).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31235	FFCustomMsgBox	[31235] Failed in obtaining the caption information (CS).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31236	FFCustomMsgBox	[31236] Failed in obtaining the caption information (SS).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31241	FFCustomMsgBox	[31241] Failed in creating thumbnail images with the image input subsystem.	- Software version A06 or earlier was used to enter an image from the 5000 plus Series. - The system was unstable.	- Upgrade the software to version A07 or later. - Restart. If the same symptom recurs, perform a reinstallation.	
31242	FFCustomMsgBox	[31242] Failed in processing in image input subsystem.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31243	FFCustomMsgBox	[31243] Image format information is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31244	FFCustomMsgBox	[31244] Annotation information is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31245	FFCustomMsgBox	[31245] No. of output film information is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31246	FFCustomMsgBox	[31246] Distribution code information is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31247	FFCustomMsgBox	[31247] Image reading sensitivity is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31248	FFCustomMsgBox	[31248] Average output density is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31249	FFCustomMsgBox	[31249] EDR mode is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31250	FFCustomMsgBox	[31250] Image filing mode is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31251	FFCustomMsgBox	[31251] Function mode is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31252	FFCustomMsgBox	[31252] IP logical size information is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	

Event	Event Source	Description	Causes	Remedies	Remarks
31253	FFCustomMsgBox	[31253] Contrast shift is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31254	FFCustomMsgBox	[31254] Sensitivity shift information is illegal.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31255	FFCustomMsgBox	[31255] There is a discrepancy between system setting and image information.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31256	FFCustomMsgBox	[31256] There is a discrepancy between system setting and image information.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31257	FFCustomMsgBox	[31257] There is a discrepancy between system setting and image information.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31258	FFCustomMsgBox	[31258] There is a discrepancy between system setting and image information.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31259	FFCustomMsgBox	[31259] Failed in obtaining the image invert/rotate information.	It is conceivable that the image information was damaged.	Delete the associated examination. If the same symptom frequently recurs, perform a reinstallation.	
31260	FFCustomMsgBox	[31260] Failed in setting the image format information.	A value in the image file conflicted with a system setting.	Since a standard setting will be used as a substitute to continue with the process, no particular response is required.	
31261	FFCustomMsgBox	[31261]Failed in obtaining the image format information.	It is conceivable that the image information was damaged.	Delete the associated examination. If the same symptom frequently recurs, perform a reinstallation.	
31262	FFCustomMsgBox	[31262] Film annotation is illegal.	The registered film mark contained an unacceptable character.	Correct the film mark setup with a user utility.	
31265	FFCustomMsgBox	[31265] Failed in obtaining the caption information (FIX).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31266	FFCustomMsgBox	[31266] Failed in obtaining the caption information (S value).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31267	FFCustomMsgBox	[31267] Failed in obtaining the caption information (SEMI-X).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31268	FFCustomMsgBox	[31268] Failed in obtaining the caption information (Density Ave)	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31269	FFCustomMsgBox	[31269] Failed in obtaining the caption information (Density Average).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31270	FFCustomMsgBox	[31270] Input value is illegal.	The entered value contained an unacceptable character or was out of range or otherwise abnormal.	Make a proper entry.	
31272	FFCustomMsgBox	[31272] Failed in obtaining the system setting information (Function selectable range).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31273	FFCustomMsgBox	[31273] Failed in setting the function information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31274	FFCustomMsgBox	[31274] Failed in setting the No. of output film.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31277	FFCustomMsgBox	[31277] Failed in setting the contrast shift.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31278	FFCustomMsgBox	[31278] Failed in setting the sensitivity shift.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31279	FFCustomMsgBox	[31279] Failed in setting the EDR mode information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31280	FFCustomMsgBox	[31280] Failed in setting the FIX mode S value.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31281	FFCustomMsgBox	[31281] Failed in setting the SEMI-X mode average output density.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31282	FFCustomMsgBox	[31282] Failed in QA starting process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31284	FFCustomMsgBox	[31284] Failed in obtaining the system setting information (Filing mode selectable range).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31285	FFCustomMsgBox	[31285] Failed in setting the image filing information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31288	FFCustomMsgBox	[31288] Failed in obtaining the distribution destination information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31290	FFCustomMsgBox	[31290] Failed in obtaining IP logical size information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31291	FFCustomMsgBox	[31291] Failed in obtaining the system setting information (Distribution code change).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31292	FFCustomMsgBox	[31292] Failed in obtaining the system setting information (Film annotation change).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31293	FFCustomMsgBox	[31293] Failed in obtaining the system setting information (Function change).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31294	FFCustomMsgBox	[31294] Failed in terminating process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31295	FFCustomMsgBox	[31295] Failed in terminating process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31296	FFCustomMsgBox	[31296] Failed in updating the list display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31303	FFCustomMsgBox	[31303] No list (Waiting for study) is selected.	It is highly probable that the program was faulty.		
31304	FFCustomMsgBox	[31304] No list (Waiting for QA) is selected.	It is highly probable that the program was faulty.		
31305	FFCustomMsgBox	[31305] No list (Waiting for output) is selected.	It is highly probable that the program was faulty.		
31306	FFCustomMsgBox	[31306] No list (Already output) is selected.	It is highly probable that the program was faulty.		
31307	FFCustomMsgBox	[31307] No list (All) is selected.	It is highly probable that the program was faulty.		
31308	FFCustomMsgBox	[31308] No list (Today) is selected.	It is highly probable that the program was faulty.		
31309	FFCustomMsgBox	[31309] Failed in updating the list (Waiting for study) display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31310	FFCustomMsgBox	[31310] Failed in updating the list (Waiting for QA) display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31311	FFCustomMsgBox	[31311] Failed in updating the list (Waiting for output) display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31312	FFCustomMsgBox	[31312] Failed in updating the list (Already output) display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31313	FFCustomMsgBox	[31313] Failed in updating the list (All) display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31314	FFCustomMsgBox	[31314] Failed in updating the list (Today) display.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31315	FFCustomMsgBox	[31315] No. of selected study is illegal. Study cannot be started.	It is highly probable that the program was faulty.		
31316	FFCustomMsgBox	[31316] Failed in study starting process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31317	FFCustomMsgBox	[31317] No. of selected studies is illegal. QA cannot be started.	It is highly probable that the program was faulty.		
31318	FFCustomMsgBox	[31318] Failed in QA starting process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31319	FFCustomMsgBox	[31319] Failed in QA starting process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31320	FFCustomMsgBox	[31320] Failed in obtaining the system setting information (Operational mode after studying).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31321	FFCustomMsgBox	[31321] Failed in obtaining the button image (Utility button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31322	FFCustomMsgBox	[31322] Failed in obtaining the patient information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31323	FFCustomMsgBox	[31323] Date of birth could not be converted to the displaying format.	Illegal birth date information was set.	Delete the associated examination. If the same symptom recurs after deletion, perform a reinstallation.	
31324	FFCustomMsgBox	[31324] Failed in obtaining the caption information (Stop alarm button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31329	FFCustomMsgBox	[31329] Message from the Image Reader could not be displayed.	The RU software version conflicted with the message file version on the IIP side or the RU message file was damaged or otherwise abnormal.	Confirm software version and setups on the RU side.	
31330	FFCustomMsgBox	[31330] Failed in the obtaining the caption information (System Terminating button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31331	FFCustomMsgBox	[31331] Failed in obtaining the caption information (User Utility button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31332	FFCustomMsgBox	[31332] Failed in obtaining the caption information (Study list setting button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31333	FFCustomMsgBox	[31333] Failed in obtaining the caption information (Version displaying button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31334	FFCustomMsgBox	[31334] Failed in obtaining the caption information (Cancel button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31335	FFCustomMsgBox	[31335] Failed in obtaining the button image (Clear button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31336	FFCustomMsgBox	[31336] Failed in obtaining the tool tip information (Clear button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31337	FFCustomMsgBox	[31337] Failed in displaying the thumbnail images.	The thumbnail image file was damaged, deleted, or otherwise abnormal.	There are no processing problems except for the inability to display thumbnail images. If the same symptom frequently occurs, initialize the image database.	
31339	FFCustomMsgBox	[31339] Failed in executing the dust removing process starting method of the Image Reader.	The RU is not ready for performing the method.	Check the RU.	
31340	FFCustomMsgBox	[31340] Failed in obtaining the caption information (Cancel button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31341	FFCustomMsgBox	[31341] Failed in obtaining the caption information (Cancel button).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31343	FFCustomMsgBox	[31343] Failed in inputting images.	It is conceivable that there was a problem with the RU or line.	Check the RU and line.	
31344	FFCustomMsgBox	[31344] Image size could not be detected.	It is conceivable that there was a problem with the RU.	Check the RU.	
31346	FFCustomMsgBox	[31346] Failed in obtaining the Image Reader error information.	The RU software version conflicted with the message file version on the IIP side or the RU message file was damaged or otherwise abnormal.	Check the software version and setup on the RU side.	
31347	FFCustomMsgBox	[31347] Failed in obtaining the Image Reader status information.	The RU software version conflicted with the message file version on the IIP side or the RU message file was damaged or otherwise abnormal.	Check the software version and setup on the RU side.	
31348	FFCustomMsgBox	[31348] Failed in thumbnail image creation process.	The thumbnail image file was damaged, deleted, or otherwise abnormal.	There are no processing problems except for the inability to display thumbnail images. If the same symptom frequently occurs, initialize the image database.	
31349	FFCustomMsgBox	[31349] Failed in displaying the list (Waiting for study).	It is conceivable that the system was unstable or that the program was faulty.	If the same symptom recurs after a restart, perform a reinstallation.	
31350	FFCustomMsgBox	[31350] Failed in displaying the list (Waiting for QA).	It is conceivable that the system was unstable or that the program was faulty.	If the same symptom recurs after a restart, perform a reinstallation.	
31351	FFCustomMsgBox	[31351] Failed in displaying the list (Waiting for output).	It is conceivable that the system was unstable or that the program was faulty.	If the same symptom recurs after a restart, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31352	FFCustomMsgBox	[31352] Failed in displaying the list (Already output).	It is conceivable that the system was unstable or that the program was faulty.	If the same symptom recurs after a restart, perform a reinstallation.	
31353	FFCustomMsgBox	[31353] Failed in displaying the list (All).	It is conceivable that the system was unstable or that the program was faulty.	If the same symptom recurs after a restart, perform a reinstallation.	
31354	FFCustomMsgBox	[31354] Failed in displaying the list (Today).	It is conceivable that the system was unstable or that the program was faulty.	If the same symptom recurs after a restart, perform a reinstallation.	
31355	FFCustomMsgBox	[31355] Failed in customizing the list display.	It is conceivable that the system was unstable or that the program was faulty.	If the same symptom recurs after a restart, perform a reinstallation.	
31356	FFCustomMsgBox	[31356] Failed in obtaining the system setting information (Default menu code).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31358	FFCustomMsgBox	[31358] Failed in obtaining the tool tip text.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31359	FFCustomMsgBox	[31359] Failed in obtaining the caption information (Title bar).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31360	FFCustomMsgBox	[31360] Failed in obtaining the caption information (Option label).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31361	FFCustomMsgBox	[31361] Failed in obtaining the version information.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31362	FFCustomMsgBox	[31362] Option list could not be obtained.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31363	FFCustomMsgBox	[31363] Failed in obtaining the registry information (Next multiple frame set No.).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31364	FFCustomMsgBox	[31364] Failed in setting the registry information (Next multi-frame set No.).	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31365	FFCustomMsgBox	[31365] Failed in obtaining the system setting information (Series issuing type).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31366	FFCustomMsgBox	[31366] Failed in obtaining the multi-frame UID information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31367	FFCustomMsgBox	[31367] Failed in obtaining the cassette insertion enabled image.	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31368	FFCustomMsgBox	[31368] Failed in obtaining the cassette insertion disabled image.	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31369	FFCustomMsgBox	[31369] Failed in obtaining the image icon (Mis-exposure).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31370	FFCustomMsgBox	[31370] Failed in obtaining the button image (Image style button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31371	FFCustomMsgBox	[31371] Failed in obtaining the button image (EDR button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31372	FFCustomMsgBox	[31372] Failed in obtaining the button image (Function button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31373	FFCustomMsgBox	[31373] Failed in obtaining the button image (No. of output film button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31374	FFCustomMsgBox	[31374] Failed in obtaining the button image (IP size button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31375	FFCustomMsgBox	[31375] Failed in obtaining the button image (Film format button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31376	FFCustomMsgBox	[31376] Failed in obtaining the button image (Filing button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31377	FFCustomMsgBox	[31377] Failed in obtaining the button image (Film annotation button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31378	FFCustomMsgBox	[31378] Failed in obtaining the button image (Distribution code button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31379	FFCustomMsgBox	[31379] Failed in obtaining the button image (CS/SS button).	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31380	FFCustomMsgBox	[31380] Failed in obtaining the system setting information (Serial port No. for connecting to XCON).	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31381	FFCustomMsgBox	[31381] Failed in obtaining the XCON device name.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31382	FFCustomMsgBox	[31382] Image data line to the Image Reader(%s) has broken.	The line was abnormal.	Check the line.	
31386	FFCustomMsgBox	[31386] Failed in obtaining the caption information.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31387	FFCustomMsgBox	[31387] Failed in reading the bit-map file.	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31388	FFCustomMsgBox	[31388] Failed in obtaining the font information.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31390	FFCustomMsgBox	[31390] The information about a requesting department was illegal.	The entered information or its format was in error.		
31391	FFCustomMsgBox	[31391] The information about a paramedic was illegal.	The entered information or its format was in error.		
31392	FFCustomMsgBox	[31392] A patient information search was unsuccessful.	Nothing matched the entered patient information.	Check the patient information.	
31393	FFCustomMsgBox	[31393] Failed in setting up connection status with the RIS.	This error is attributable to an RIS problem or RIS setup problem.	Check RIS-side status or RIS setup.	
31394	FFCustomMsgBox	[31394] The line connected to the RIS was faulty.	This error is attributable to an RIS problem or RIS setup problem.	Check the RIS status and RIS setup.	
31400	FFCustomMsgBox	[31400]The selected menu did not exist.	This error is attributable to an RIS problem or RIS setup problem.	Check the RIS status and RIS setup.	
31401	FFCustomMsgBox	[31401] Path information (image data folder) acquisition was not successful.	It is conceivable that the file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31402	FFCustomMsgBox	[31402] Parameter icon image acquisition was not successful.	It is conceivable that the bitmap file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31403	FFCustomMsgBox	[31403] Caption information acquisition was not successful.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31404	FFCustomMsgBox	[31404] Failed in communicating with other connected device.	This error is attributable to a problem with the connected equipment or connection setup.	Check the connected equipment, connection setup, and others.	
31405	FFCustomMsgBox	[31405] Failed in evacuating the IP.	The connected equipment may be faulty.	Check the connected equipment.	
31406	FFCustomMsgBox	[31406] Failed in setting the IP.	The connected equipment may be faulty.	Check the connected equipment.	
31407	FFCustomMsgBox	[31407] Failed in setting the exposure size.	The connected equipment may be faulty.	Check the connected equipment.	
31408	FFCustomMsgBox	[31408] Failed in setting the reference position for exposure.	The connected equipment may be faulty.	Check the connected equipment.	

Event	Event Source	Description	Causes	Remedies	Remarks
31409	FFCustomMsgBox	[31409] No response comes from other connected device.	The connected equipment may be faulty.	Check the connected equipment.	
31410	FFCustomMsgBox	[31410] There is no answer from the device that ID information is shared.	The connected equipment may be faulty.	Check the connected equipment.	
31411	FFCustomMsgBox	[31411] A Study can’t register because the exposure menu registerd in IDT isn't registered in IIP.	This error is attributable to an improperly registered menu.	Check the menu registration information.	
31412	FFCustomMsgBox	[31412] An image data line with the reader is cut off.	The connected equipment may be faulty.	Check the connected equipment.	
31413	FFCustomMsgBox	[31413] There are some inconsistency in the IIP-RU connection setting of the system configuration.	The connection setup may be improper.	Check the connection setup.	
31414	FFCustomMsgBox	[31414] Failed in obtaining the caption information (RIS tab).	The database file may be damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
31415	FFCustomMsgBox	[31415] A communication error with RIS occurred.	The connected equipment may be faulty.	Check the connected equipment.	
31416	FFCustomMsgBox	[31416] Some exposure menus couldn’t be registered.	This error is attributable to an improperly set menu parameter or other setup failure.	Check the settings.	
31417	FFCustomMsgBox	[31417] An exposure menu couldn’t be registered.	This error is attributable to an improperly set menu parameter or other setup failure.	Check the settings.	
31418	FFCustomMsgBox	[31418] Failed in the reference of the reader device.	The connection setup may be faulty.	Check the connection setup.	
31419	FFCustomMsgBox	[31419] The exposure condition values to be sent to the X-ray apparatus was over the limit.	The XCON settings (limit values) were inconsistent with the exposure condition preset values for the menus.	There is no practical problem because the limit values are transferred to the XCON.	
31420	FFCustomMsgBox	[31420] A failure occurred in the communication with the RIS.	It is conceivable that the connected equipment may be faulty.	Check the connected equipment.	
31422	FFCustomMsgBox	[31422] Failed in registering the study to the patient information database.	The patient information database operation was wrong.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31423	FFCustomMsgBox	[31423] Failed in image stitching processing.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation. Ensure that only period is used as a symbol representing a decimal point for values to be set in “OS Settings - Regional Options”. If any symbol other than a period is used, correct it appropriately. For details of how to perform settings, see the section concerned in “RI: Reinstalling the Software”. ● For Windows 2000 ☞ **“■ Defining the character to be used as a decimal point” in “2.1.3 Setting the OS”** ● For Windows XP ☞ **“■ Defining the character to be used as a decimal point” in “2.2.3 Setting the OS”**	
31424	FFCustomMsgBox	[31424] Failed in saving the exposure result information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
31425	FFCustomMsgBox	[31425] Failed in setting actual exposure result value.	Invalid characters were used for the performed procedure step description, protocol name, or filter type. The radiation source-to-detector distance or radiation time did not consist of numerals only. The film output count or film size ID was out of range.	No remedial action is needed because the process will be continuously performed with the invalid settings replaced with the standard ones.	
31426	FFCustomMsgBox	[31426] Failed in acquiring coloring information.	Settings may have been corrupted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
31427	FFCustomMsgBox	[31427] Failed in image distribution processing.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
31428	FFCustomMsgBox	[31428] Failed in displaying the study information list.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
31429	FFCustomMsgBox	[31429] Failed in setting patient information.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
31430	FFCustomMsgBox	[31430] Failed in acquiring patient information.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
31431	FFCustomMsgBox	[31431] Failed in acquiring image (background).	The bitmap file may have been damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
31441	FFCustomMsgBox	[31441] Failed in acquiring parameters used for displaying mammography images.	It is conceivable that the file was damaged or deleted. It is also conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
31850	FFCustomMsgBox	[31850] Failed in communicating with X-ray equipment.	It is conceivable that the connected equipment may have a problem or the network may be unstable.	Check status of the connected equipment.	
31851	FFCustomMsgBox	[31851] Failed in registering a reserved study.	The system is unstable.	Restart the system. If the same symptom recurs, reinstall the system.	
31852	FFCustomMsgBox	[31852] Failed in starting a reserved study.	The system is unstable.	Restart the system. If the same symptom recurs, reinstall the system.	
31853	FFCustomMsgBox	[31853] An error occurred with connection to the equipment.	The system is unstable.	Restart the system. If the same symptom recurs, reinstall the system.	
31854	FFCustomMsgBox	[31854] Failed in searching a reserved study.	The system is unstable.	Restart the system. If the same symptom recurs, reinstall the system.	
31855	FFCustomMsgBox	[31855] Received illegal information from the outside.	It is conceivable that the connected equipment may have transmitted illegal information.	Check information transmitted from the connected equipment.	
31856	FFCustomMsgBox	[31856] Received illegal information from the outside.	It is conceivable that the connected equipment may have transmitted illegal information.	Check information transmitted from the connected equipment.	
32001	FFCustomMsgBox	[32001] The card type is not acceptable.	The employed card type did not agree with the card type defined by the system setup data.	Check both the system settings and employed card type.	
32001	FFIIPInImgCtrl	Initialize warning. [Detailed error information 32001 35 items]	A warning-level error occurred in an image database initialization process. The common probable causes are as follows: • An abnormality occurred when the image database was accessed. • An abnormality occurred when an information file was accessed. • An abnormality occurred when an image file was created or referenced for image file recovery. • The contents of the image database or information file were illegal. • An unrecoverable image file was encountered.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	DICOM SCP was Not found in NetConfigDB.	DICOM SCP is not defined in the NetConfigDB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	

Event	Event Source	Description	Causes	Remedies	Remarks
32001	FFIIPInImgCtrl	DICOM SCP control status error.	Failed in starting the DICOM SCP control.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	DDO file load error.	Failed in reading the information file (DDO).	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	DDO file save error.	Failed in storing the information file. (DDO).	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Size code was not found in DDO.	There is no size code in the information file (DDO).	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	RecordID was not found in DDO.	There is no record ID in the information file (DDO).	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	HQ file was not found in DDO.	There is no HQ image file in the information file (DDO).	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Std file was not found in DDO.	There is no standard image file name in the information file (DDO).	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Image size was not found in DDO.	There is no image size in the information file (DDO).	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	

Event	Event Source	Description	Causes	Remedies	Remarks
32001	FFIIPInImgCtrl	Image sizecode error.	Illegal image size cede.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Std file make error.	Standard image generation processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Thumb file make error.	Thumbnail image generation processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	FoeEDR file make error.	Reduced image generation processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Moire control error.	Standard image generation processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Thumb control error.	Thumbnail image generation processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	ForEDR control error.	Reduced image generation processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	EDR process error.	EDR processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	

Event	Event Source	Description	Causes	Remedies	Remarks
32001	FFIIPInImgCtrl	Jpeg control error.	JPEG processing error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	InfoFileURL was not found in ImageDB.	The InfoFileURL field cannot be found in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	InfoFile was “EMPTY” in ImageDB.	The InfoFileURL field in the image DB is “EMPTY”.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	StdImageFileURL was not found in ImageDB.	The StdImageFileURL field cannot be found in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	ThmImageFileURL was not found in ImageDB.	The ThmImageFileURL field cannot be found in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	MaskImageFileURL was not found in ImageDB.	The MaskImageFileURL field cannot be found in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	EDRBackupFileURL was not found in ImageDB.	The EDRBackupFileURL field cannot be found in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	StdImageFileURL set error in ImageDB.	Failed in registering the standard image file name in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	

Event	Event Source	Description	Causes	Remedies	Remarks
32001	FFIIPInImgCtrl	ThmImageFileURL set error in ImageDB.	Failed in registering the thumbnail image file name in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	MaskImageFileURL set error in ImageDB.	Failed in registering the reduced image file name in the image DB.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	ImageDB access(get_Fields) error.	Image DB access error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	ImageDB access error.	Image DB access error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	UpdateCloseRec error.	Image DB access error.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	Create file error.	Failed in creating a file.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	File open error.	Failed in opening a file.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	File close error.	Failed in closing a file.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	

Event	Event Source	Description	Causes	Remedies	Remarks
32001	FFIIPInImgCtrl	File read error.	Failed in reading a file.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFIIPInImgCtrl	File write error.	Failed in writing a file.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
32001	FFInImgMonitorCtrl	Initialize warning.%n[%1]	A warning-level error occurred during initialization processing.	Nothing particular. (Processing was continued.)	
32001	FFInImgMonitorDispCtrl	Initialize warning.%n[%1]	A warning-level error occurred during initialization processing.	Nothing particular. (Processing was continued.)	
32002	FFCustomMsgBox	[32002] Failed in reading the card.	A simple read error occurred or the problem might have been caused by damaged contents of a card or a broken magnetic card reader.	Read the card again. If the same symptom recurs, check the contents of the card and the magnetic card reader.	
32002	FFIIPInImgCtrl	Data not found.(warning) [Detailed error information 32002 1 item]	A warning-level error was found in information file data.	Nothing in particular. (The data found abnormal was replaced by the default value to continue with the process.)	
32002	FFIIPInImgCtrl	Data not found.	There is no data in the information file (DDO).	Nothing in particular. (The data found abnormal was replaced by the default value to continue with the process.)	
32002	FFInImgMonitorCtrl	Data not found.(warning) %n[%1]	A warning-level error was detected in the information file data.	Nothing particular. (The error data was replaced by the default value and processing was continued.)	
32002	FFInImgMonitorDispCtrl	Data not found.(warning) %n[%1]	A warning-level error was detected in the information file data.	Nothing particular. (The error data was replaced by the default value and processing was continued.)	
32003	FFInImgMonitorCtrl	Status warning. [Detailed error information 32003 1 item]	A process request was issued while an initialization or termination process was being performed.	Nothing in particular. (The process request was rejected.)	
32003	FFIIPInImgCtrl	Status error.(IDInfoChange method)	Image display request method execution timing error after ID information was changed.	Nothing in particular. (Processing requested was rejected.)	
32003	FFInImgMonitorCtrl	Status warning.%n[%1]	A warning-level error occurred during method processing.	Nothing particular. (The error data was replaced by the default value and processing was continued.)	
32003	FFInImgMonitorDispCtrl	Status warning.%n[%1]	A warning-level error occurred during method processing.	Nothing particular. (The error data was replaced by the default value and processing was continued.)	

Event	Event Source	Description	Causes	Remedies	Remarks
32012	FFCustomMsgBox	[32012] Illegal information has been detected in the patient information.	The problem was caused, for instance, by an invalid character contained in the contents of the card.	Check the contents of the card.	
32015	FFCustomMsgBox	[32015] A barcode was not successfully read.	The problem was caused, for instance, by an incompatible barcode format.	Check the contents of the barcode.	
34001	FFCustomMsgBox	[34001] The same patient information has been input.	The card read was about the patient whose examination was being conducted.	This dialog box merely opens to attract the user's attention. No particular response is required.	
34002	FFCustomMsgBox	[34002] A certain examination finished before the completion of an image read.	The last examination was ended abruptly during an image read process (due, for instance, to a power failure).	Check information sent by the connected device.	
34084	FFCustomMsgBox	[34084] Illegal information was transmitted from the RIS.	A connected device may have sent illegal information.	Check information sent by the connected device.	
34085	FFCustomMsgBox	[34085] Communication with the RIS was disabled.	A connected device may have a problem or the network can be unstable.	Reconnect. If the same symptom recurs, check status of the connected device.	
34092	FFCustomMsgBox	[34092] A failure occurred when starting the ordered study.	The system was unstable.	Restart.	
34095	FFCustomMsgBox	[34095] A failure occurred in communication with the RIS at startup of a study.	The system was unstable.	Restart.	
34096	FFCustomMsgBox	[34096] A failure occurred in communication with the RIS when finishing a study.	The system was unstable.	Restart.	
34097	FFCustomMsgBox	[34097] A failure occurred when changing the RIS user.	The system was unstable.	Match technologist registration information of this equipment with that of the connected device.	
34098	FFCustomMsgBox	[34098] Failed in communicating with other connected device.	RIS screen display failed.	Retry after a while. If the same symptom recurs, restart the system.	
39001	FFIIPInImgCtrl	Memory allocate error. [E1027]	Sufficient memory was not available to the system.	Restart.	
39001	FFIIPInImgCtrl	Socket recv buffer.	Failed in acquiring the socket reception buffer.	Restart.	
39001	FFIIPInImgCtrl	Pantomo work buffer.	Failed in acquiring the pantomography reading buffer.	Restart.	
39001	FFIIPInImgCtrl	ImgReadProcess memory allocate error.	Failed in memory acquisition.	Restart.	
39001	FFIIPInImgCtrl	Memory allocate error.	Failed in memory acquisition.	Restart.	
39001	FFIIPInImgCtrl	Memory Exception error.	An exception generated when acquiring memory.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
39001	FFIIPInImgCtrl	Disp Qeue param.	Failed in acquiring an image display queue.	Restart.	
39001	FFIIPInImgCtrl	Read qeue param.	Failed in acquiring an image reading queue.	Restart.	
39001	FFIIPInImgCtrl	ReadThread main param.	Failed in acquiring image input thread parameters.	Restart.	
39001	FFIIPInImgCtrl	JpegThread main param.	Failed in acquiring JPEG compression thread parameters.	Restart.	
39001	FFIIPInImgCtrl	Image Data area.	Failed in acquiring image reading date area.	Restart.	
39001	FFIIPInImgCtrl	Image Time area.	Failed in acquiring image reading time area.	Restart.	
39001	FFIIPInImgCtrl	DICOMDataObj set data area.	Failed in acquiring information file (DDO) setup memory area.	Restart.	
39001	FFIIPInImgCtrl	EDR data.	Failed in acquiring EDR image separation processing area.	Restart.	
39001	FFIIPInImgCtrl	EDR out data.	Failed in acquiring EDR image separation processing area.	Restart.	
39001	FFIIPInImgCtrl	Disp image data.	Image display area.	Restart.	
39001	FFIIPInImgCtrl	SkGp Image area.	Failed in acquiring image area after normalization processing.	Restart.	
39001	FFIIPInImgCtrl	GammaTable(LUT) area.	Failed in acquiring the γ processing table.	Restart.	
39001	FFIIPInImgCtrl	Beta param area.	Failed in acquiring the β processing parameter area.	Restart.	
39001	FFIIPInImgCtrl	DRC param area.	Failed in acquiring the DRC processing parameter area.	Restart.	
39001	FFIIPInImgCtrl	MFP-DRC param area.	Failed in acquiring the MFP-DRC processing parameter area.	Restart.	
39001	FFIIPInImgCtrl	MFP-USM param area.	Failed in acquiring the MFP-USM processing parameter area.	Restart.	
39001	FFRUInpImgMgr	Initialization failed. %n[%1]	The initialization process was not successfully performed.	Restart.	
39001	FFInImgMonitorCtrl	Memory allocate error. %n[%1]	System memory was insufficient.	Restart.	
39002	FFIIPInImgCtrl	Message post/get error. [Detailed error information 39002 5 items]	The system was unstable.	Restart.	
39002	FFIIPInImgCtrl	PostThreadMessage (%s) error.	Failed in (%s) message transmission while in image input processing.	Restart.	
39002	FFIIPInImgCtrl	PostMessage error.	Failed in message transmission while in image input processing.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
39002	FFIIPInImgCtrl	GetMessage (%s) error.	Failed in (%s) message reception while in image input processing.	Restart.	
39002	FFIIPInImgCtrl	GetMessage error.	Failed in message reception while in image input processing.	Restart.	
39002	FFIIPInImgCtrl	Post/Get Message error.	Failed in message transmission/reception while in image input processing.	Restart.	
39002	FFRUInpImgMgr	Finalize Failed. %n[%1]	The finalization process was not successfully performed.	Restart.	
39002	FFInImgMonitorCtrl	Message post/get error. %n[%1]	The system was unstable.	Restart.	
39003	FFIIPInImgCtrl	IIPInImg control error. [Detailed error information 39003 19 items]	An abnormality was found in the IIP input image process.	Restart.	
39003	FFIIPInImgCtrl	Get DispatchID error. Property = %s	Failed in setting DICOM SCP control properties (%s).	Restart.	
39003	FFIIPInImgCtrl	Invoke error. Property = %s	Failed in setting DICOM SCP control properties (%s).	Restart.	
39003	FFIIPInImgCtrl	Get DispatchID error. Property = %s	Failed in viewing DICOM SCP control properties (%s).	Restart.	
39003	FFIIPInImgCtrl	Invoke error. Property = %s	Failed in viewing DICOM SCP control properties (%s).	Restart.	
39003	FFIIPInImgCtrl	Get DispatchID error. Method = %s	Failed in performing the DICOM SCP control method (%s).	Restart.	
39003	FFIIPInImgCtrl	Invoke error. Method = %s	Failed in performing the DICOM SCP control method (%s).	Restart.	
39003	FFIIPInImgCtrl	DispQeue was full.	Failed in registering an image display queue.	Restart.	
39003	FFIIPInImgCtrl	DispQeue status error.	Failed in registering an image display queue (illegal status).	Restart.	
39003	FFIIPInImgCtrl	Thumbnail image disp error.	Failed in displaying a pre-reading image.	Restart.	
39003	FFIIPInImgCtrl	EDR/ID image disp error.	Failed in displaying a processed image.	Restart.	
39003	FFIIPInImgCtrl	Data not found.	The relevant menu code cannot be found in the image processing parameters.	Restart.	
39003	FFIIPInImgCtrl	Image File Path get error.	Failed in acquiring the directory path name of the image file.	Restart.	
39003	FFIIPInImgCtrl	File name set error.(%s)	Failed in setting the (%s) file name in the information file (DDO).	Restart.	
39003	FFIIPInImgCtrl	JPEG Thread error.	Failed in creating a JPEG compression thread.	Restart.	
39003	FFIIPInImgCtrl	Image process error(%s).	Failed in starting the image processing control.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
39003	FFIIPInImgCtrl	Input image control error.	Internal discrepancy found during input image processing.	Restart.	
39003	FFIIPInImgCtrl	File type error.	Internal discrepancy found during input image processing.	Restart.	
39003	FFIIPInImgCtrl	Img type error.	Internal discrepancy found during input image processing.	Restart.	
39003	FFIIPInImgCtrl	Exception error.	An exception found during input image processing.	Restart.	
39003	FFRUInpImgMgr	Invalid Status. %n[%1]	The status was invalid.	Restart.	
39004	FFIIPInImgCtrl	CR-Image control error. [Detailed error information 39004 13 items]	An abnormal end was found in an image file creation process or image display process. The problem is attributable to a disk.	Restart.	
39004	FFIIPInImgCtrl	Disp control(%s Method) error.	Image display processing error (method name: %s).	Restart.	
39004	FFIIPInImgCtrl	EDR control (%s) error.	Error occurred during EDR processing (processing ID:%s).	Restart.	
39004	FFIIPInImgCtrl	EDR process error.	Error occurred during EDR processing.	Restart.	
39004	FFIIPInImgCtrl	ForEDR control error.	Error occurred during reduced image creation processing.	Restart.	
39004	FFIIPInImgCtrl	HQ file create error.(%s)	Failed in creating an HQ image file (file ID).	Restart.	
39004	FFIIPInImgCtrl	Image Jpeg-compress error.	Error occurred during JPEG compression processing.	Restart.	
39004	FFIIPInImgCtrl	Image process error.(%s)	Failed in starting the image processing control. (Internal processing name: %s)	Restart.	
39004	FFIIPInImgCtrl	Image sizecode error.	Illegal image size code.	Restart.	
39004	FFIIPInImgCtrl	ImageDB/DDO access error.(%s)	Error occurred in access to the image DB or information file (DDO).	Restart.	
39004	FFIIPInImgCtrl	Jpeg control (%s) error.	Error occurred during JPEG processing (processing ID: %s).	Restart.	
39004	FFIIPInImgCtrl	Miore control error.	Error occurred during standard image creating processing.	Restart.	
39004	FFIIPInImgCtrl	SkGp control (%s) error.	Error occurred during normalization processing. (Processing ID:%s)	Restart.	
39004	FFIIPInImgCtrl	Thumbnail control error.	Error occurred during thumbnail image creating processing.	Restart.	
39004	FFRUInpImgMgr	Thread Invoke failed. %n[%1]	Thread creation was not successfully completed.	Restart.	
39004	FFInImgMonitorCtrl	CR-Image control error. %n[%1]	An error was detected during image processing.	Restart.	
39005	FFIIPInImgCtrl	Pipe error. [Detailed error information 39005 1 item]	The system remains unstable.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
39005	FFIIPInImgCtrl	Pipe create error.(%s)	Failed in creating a pipe. (Pipe type: %s)	Restart.	
39005	FFRUInpImgMgr	Socket Access Failed. %n[%1]	A socket communication error occurred.	Check the network status and then restart the system.	
39005	FFInImgMonitorCtrl	Pipe error. %n[%1]	The system was unstable.	Restart.	
39006	FFIIPInImgCtrl	File error. [Detailed error information 39006 7 items]	The system remains unstable.	Restart.	
39006	FFIIPInImgCtrl	File error.	Failed in accessing the file.	Restart.	
39006	FFIIPInImgCtrl	File error(%s).	Failed in accessing the file. (Processing type.)	Restart.	
39006	FFIIPInImgCtrl	Create file error.	Failed in file creation processing.	Restart.	
39006	FFIIPInImgCtrl	CreateFileMapping error.	Failed in file mapping processing.	Restart.	
39006	FFIIPInImgCtrl	MapViewOfFile error.	Failed in file mapping processing.	Restart.	
39006	FFIIPInImgCtrl	EDRImageFile mapping error.	Failed in mapping the reduced image file before EDR processing.	Restart.	
39006	FFIIPInImgCtrl	File mapping error.	Failed in file mapping processing.	Restart.	
39006	FFRUInpImgMgr	System Function Call Failed. %n[%1]	An error was returned by a system call (Win32 API, etc.).	Restart.	
39006	FFInImgMonitorCtrl	File error.%n[%1]	The system was unstable.	Restart.	
39007	FFIIPInImgCtrl	Data not found.(error) [Detailed error information 39007 3 items]	The data in the image database or information file was abnormal.	Make an exposure again. If the error recurs, initialize the image database (the entire image data is then deleted).	
39007	FFIIPInImgCtrl	Data not found. / DDO Data not found.	The relevant VR cannot be found in the information file (DDO).	Make an exposure again. If the error recurs, initialize the image database (the entire image data is then deleted).	
39007	FFIIPInImgCtrl	Data not found.(%s) / DDO Data not found.(%s)	The relevant data cannot be found in the information file (DDO).	Make an exposure again. If the error recurs, initialize the image database (the entire image data is then deleted).	
39007	FFIIPInImgCtrl	%s GetVR error.	Failed in acquiring VR shown by %s.	Make an exposure again. If the error recurs, initialize the image database (the entire image data is then deleted).	
39007	FFRUInpImgMgr	Invalid Receive Data. %n[%1]	Invalid data was received from the RU.	Check the connection to the RU.	
39007	FFInImgMonitorCtrl	Data not found.(error) %n[%1]	There is an error in the image database/ information file data.	Restart.	
39008	FFIIPInImgCtrl	DB access error. [Detailed error information 39008 19 items]	An abnormality occurred when a database was accessed.	Restart. If the same symptom frequently occurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB key get error.	Image DB key name acquisition error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB connect error.	Image DB connection error.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
39008	FFIIPInImgCtrl	ImageDB OpenRecordset error.	Image DB open error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB get_Fields error.	Image DB viewing error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB get_Item error.	Image DB viewing error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB get_Value error.	Image DB viewing error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB put_Value error. Data:%s	Image DB setup error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB SetValue error.(%s)	Image DB setup error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB (%s) set error.	Image DB setup error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	DICOM&ImageDB data set error.	Image DB setup error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB UpdateRecordset error.	Image DB update error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB CloseRecordset error.	Image DB close error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB close error.	Image DB close error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB: ReceiveFlag set error.	ReceiveFlag setup error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB access error.	Image DB access error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB access(%s) error.	Image DB access error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	ImageDB access error.(%s)	Image DB access error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	SysConfig DB access error.	SysConfig DB access error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgCtrl	Net Config DB access error.	NetConfig DB access error.	Restart. If the same symptom recurs, perform a reinstallation.	
39008	FFIIPInImgMgr	Insufficient memory. %n[%1]	The available memory was insufficient.	Restart.	
39008	FFInImgMonitorCtrl	DB access error.%n[%1]	An error occurred with accessing to several databases.	Restart.	
39009	FFIIPInImgCtrl	Socket access error. [Detailed error information 39009 5 items]	The problem is attributable to a disconnected RU or the like.	Check the connection to the RU.	

Event	Event Source	Description	Causes	Remedies	Remarks
39009	FFIIPInImgCtrl	Socket error.	Error occurred during socket generation termination processing.	Check the connection to the RU.	
39009	FFIIPInImgCtrl	Socket connect error.	Error occurred during socket connection processing.	Check the connection to the RU.	
39009	FFIIPInImgCtrl	Socket close error.	Error occurred during socket disconnection processing.	Check the connection to the RU.	
39009	FFIIPInImgCtrl	Socket recv error.	Error occurred while receiving data from the socket.	Check the connection to the RU.	
39009	FFIIPInImgCtrl	Socket recv time out.	Timeout detected while receiving data from the socket.	Check the connection to the RU.	
39009	FFIIPInImgMgr	Create Dicom Data Object Failed. %n[%1]	Data object creation was not successfully completed.	Restart.	
39010	FFIIPInImgCtrl	DICOMDataObj data area.	An exception occurred when accessing to the information file (DDO).	Restart. If the same symptom recurs, perform a reinstallation.	
39010	FFIIPInImgCtrl	Exception error. [Detailed error information 39010 5 items]	Exception handling was done.	Restart. If the same symptom frequently occurs, perform a reinstallation.	
39010	FFIIPInImgCtrl	Exception error. Property = %s	An exception occurred when setting DICOM SCP control properties (%s).	Restart. If the same symptom recurs, perform a reinstallation.	
39010	FFIIPInImgCtrl	Exception error. Method = %s	An exception occurred when performing the DICOM SCP control method (%s).	Restart. If the same symptom recurs, perform a reinstallation.	
39010	FFIIPInImgCtrl	Exception error. / Exception error.(%s)	An exception occurred. (Processing type.)	Restart. If the same symptom recurs, perform a reinstallation.	
39010	FFIIPInImgCtrl	Memory Exception error.	An exception occurred while acquiring memory.	Restart. If the same symptom recurs, perform a reinstallation.	
39010	FFIIPInImgMgr	Input Image Operation is Busy. %n[%1]	The disk was full or the connection limit was exceeded by the input request (busy state).	This is not an operating error. Wait a while and then input again.	
39010	FFInImgMonitorCtrl	Exception error.%n[%1]	An exceptional error occurred.	Restart.	
39010	FFInImgMonitorDispCtrl	Exception error.%n[%1]	An exceptional error occurred.	Restart.	
39035	FFCustomMsgBox	[39035] Unable to obtain study UID from the list (worklist).	Information coming from the RIS may not include study UID.	Include study UID in the information that comes from the RIS.	
39044	FFCustomMsgBox	[39044] No list has been selected.	There may be a problem on the connection device side.	Check the connection device status.	
39901	FFInitializingStudy	[%1] An exception error occurred(%2).	An exception error occurred.	Restart.	
39902	FFInitializingStudy	[%1] %2.	An error occurred.	Restart.	
40001	FFCustomMsgBox	[40001] An error of unknown cause occurred.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
40200	FFQAMsgBox	Process Communication Control Error. [File Name] [Function Name] [Error Code]	The method return value for the inter-process communication control resulted in an error.	Restart.	
40201	FFQAMsgBox	Journal Proc Failure. [File Name] [Function Name] [Error Code]	The method return value for the log save control resulted in an error.	Restart.	
40202	FFQAMsgBox	CustomMessageCtrl Access Failure. [File Name] [Function Name] [Error Code]	The return value for the custom message box control resulted in an error.	Restart.	
40203	FFQAMsgBox	Image DB Access Control Error. [File Name] [Function Name] [Error Code]	The method return value for the image database access control resulted in an error.	Restart.	
40204	FFQAMsgBox	Media DB Access Control Error. [File Name] [Function Name] [Error Code]	The method return value for the media database access control resulted in an error.	Restart.	
40205	FFQAMsgBox	Process Communication API Error. [File Name] [Function Name] [Error Code]	The method return value for the inter-process communication API resulted in an error.	Restart.	
40206	FFQAMsgBox	SysConfig DB Access Error. [File Name] [Function Name] [Error Code]	An error occurred with connection/disconnection/value acquisition/value setup for the system setup database access API.	Restart.	
40207	FFQAMsgBox	LangStr DB Access Error. [File Name] [Function Name] [Error Code]	An error occurred with connection/disconnection of the character string database access API.	Restart.	
40208	FFQAMsgBox	LangMsgBox DB Access Error. [File Name] [Function Name] [Error Code]	An error occurred with connection/disconnection of the message box database access API.	Restart.	
40209	FFQAMsgBox	Flag DB Access Error. [File Name] [Function Name] [Error Code]	An error occurred with connection/value acquisition/value setup/disconnection of the flag database access.	Restart.	
40210	FFQAMsgBox	Return value of a ImgDeliveryCom makes an error. [File Name] [Function Name] [Error Code]	The method return value for the image distribution instruction component resulted in an error.	Restart.	
40211	FFQAMsgBox	NetConfig DB Access Error. [File Name] [Function Name] [Error Code]	An error occurred with connection/disconnection/value acquisition/value setup for the network setup database (irreplaceable).	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
41001	FFCustomMsgBox	[41001] The device is not ready.	No floppy disk was set in position.	Set media that is appropriate for the device.	
41002	FFCustomMsgBox	[41002] Remaining capacity is insufficient.	The file to be copied was too large to fit onto the media at the receiving end.	Switch to larger-capacity media.	
41003	FFCustomMsgBox	[41003] Destination for file copy is illegal.	An invalid pathname was specified as the file copy destination.	Check the system setup.	
41004	FFCustomMsgBox	[41004] E-mail program cannot be started.	Outlook was not properly set up.	Exit IIP and then complete Outlook setup.	
41005	FFCustomMsgBox	[41005] No data cannot be written on the disk.	The disk was write-protected or damaged.	Check the disk.	
41106	FFCustomMsgBox	[41106] Hard Disk Full.	The hard disk was full.	Exit QA, delete unnecessary images from the list, and retry the distribution.	
41107	FFCustomMsgBo	[41107] Hard Disk Full.	The hard disk was full.	Exit QA, delete unnecessary images from the list, and retry the distribution.	
41108	FFCustomMsgBox	[41108] Failed in reading the LUT file for JPEG Image.	No JPEG image gradation correction file is available or the format is illegal.	Check the correction file.	
41109	FFCustomMsgBox	[41109] A menu of a different modality has been selected.	A menu of a different modality was selected.	Select a menu of the same modality.	
41110	FFCustomMsgBox	[41110] Failed in access to the image database.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
41111	FFCustomMsgBox	[41111] Failed in access to the image database.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	
41112	FFCustomMsgBox	[41112] Failed in access to the image database.	It is conceivable that QA processing was performed on other equipment.	Check other equipment or perform another study.	
41113	FFCustomMsgBox	[41113] Failed in access to the image file.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	
41114	FFCustomMsgBox	[41114] Failed in saving the information.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	
41115	FFCustomMsgBox	[41115] Failed in access to the image file.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	
41116	FFCustomMsgBox	[41116] Failed in saving the information.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	
41117	FFCustomMsgBox	[41117] Failed in saving the information.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	
41118	FFCustomMsgBox	[41118] Failed in image output processing.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	
41119	FFCustomMsgBox	[41119] Failed in QA startup processing.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
41120	FFCustomMsgBox	[41120] Failed in access to the image file.	It is conceivable that the shared host has not been started.	Check targets involved in the shared host.	

Event	Event Source	Description	Causes	Remedies	Remarks
41130	FFCustomMsgBox	[41130] Failed in replacing an image.	No extension menus have been registered.	Check menu registration information.	
41131	FFCustomMsgBox	[41131] Study information cannot be modified.	It is conceivable that system settings for the study # and ID # have been changed.	Check the settings.	
41140	FFCustomMsgBox	[41140] The function cannot be implemented.	A function that was called up did not match the optional system settings.	Check the customized settings.	
41141	FFCustomMsgBox	[41141] An error occurred.	The system was unstable.	Reinstall the program if the same symptom recurs after restarting the equipment.	
41150	FFCustomMsgBox	[41150] Failed in file output processing.	A failure occurred in accessing the transmission file. The system may have been unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
41151	FFCustomMsgBox	[41151] There is no free space on the hard disk.	The hard disk was full.	Exit QA processing, delete unnecessary images from the list, and retry output processing.	
41152	FFCustomMsgBox	[41152] Free space is insufficient on the destination for output.	The hard disk was full.	Exit QA processing, delete unnecessary images from the list, and retry output processing.	
41200	FFQAMsgBox	HDD FULL. [File Name] [Function Name] [Error Code]	The hard disk was full.	Increase the free hard disk space and then retry operation.	
41201	FFQAMsgBox	The specified path does not exist. [File Name] [Function Name] [Error Code]	The specified path was not found.	Check path settings.	
41202	FFQAMsgBox	Media are not ready. [File Name] [Function Name] [Error Code]	No media was ready.	Check the media status.	
41203	FFQAMsgBox	The capacity of copy place media is insufficient. [File Name] [Function Name] [Error Code]	The capacity of the media targeted for copy was insufficient.	Replace the media for anyone of larger capacity.	
41210	FFQAMsgBox	Return value of a ImgDeliveryCom makes an error. [File Name] [Function Name] [Error Code]	The method return value for the image distribution instruction component resulted in an error. (Processing other than image distribution can be continued.)	Check the destination for image distribution and then retry.	
42200	FFQAMsgBox	Can’t Get Bitmap (Processing continuation). [File Name] [Function Name] [Error Code]	Failed in acquiring a bitmap (replaceable).	Reinstall the program.	
42201	FFQAMsgBox	CustomMessageCtrl Access Failure(Processing continuation). [File Name] [Function Name] [Error Code]	The return value for the custom message box control resulted in an error.	Reinstall the program.	

Event	Event Source	Description	Causes	Remedies	Remarks
42202	FFQAMsgBox	SysConfig DB Access Failure(Processing continuation). [File Name] [Function Name] [Error Code]	An error occurred when obtaining a system setup database access API value or the obtained value was illegal (replaceable).	Reinstall the program.	
42203	FFQAMsgBox	LangStr DB Access Failure(Processing continuation). [File Name] [Function Name] [Error Code]	An error occurred when obtaining a character string database access API value (replaceable).	Reinstall the program.	
42204	FFQAMsgBox	LangMsgBox DB Access Failure(Processing continuation). [File Name] [Function Name] [Error Code]	The return value for the message box database access API resulted in an error.	Reinstall the program.	
42205	FFQAMsgBox	FF32 Access Failure (Probably acquisition of Registry goes wrong.) [File Name] [Function Name] [Error Code]	The return value for the FF32 library (FF32.dll) resulted in an error. * When acquiring an optional key registry, no error will be registered even if no key is available.	Reinstall the program.	
42206	FFQAMsgBox	Tag Information Access Failure(Processing continuation). [File Name] [Function Name] [Error Code]	No tag information was set up though it must have been set up beforehand (replaceable).	Use default information for processing. There is no operational problem.	
42207	FFQAMsgBox	NetConfig DB Access Failure(Processing continuation). [File Name] [Function Name] [Error Code]	An error occurred when obtaining a network setup database value or obtained value was not correct (replaceable).	Reinstall the program.	
42209	FFQAMsgBox	FF32 Access Failure (Processing continuation). [File Name] [Function Name] [Error Code]	Failed in obtaining/setting an FF32 library value (replaceable).	Reinstall the program.	
42210	FFQAMsgBox	Invalid function ID Number. (Processing continuation). [File Name] [Function Name] [Error Code]	An illegal function ID (disregard).	There is no operational problem.	
42211	FFQAMsgBox	Data is not found in CustomScreenDB. [File Name] [Function Name] [Error Code]	No custom setup database registered (processing can be continued).	Register custom setup database using the customization setting displayed on the User Utility window.	
42212	FFQAMsgBox	LogFile Access Failure. [File Name] [Function Name] [Error Code]	Failed in accessing the log file.	Reinstall the program.	

Event	Event Source	Description	Causes	Remedies	Remarks
42214	FFQAMsgBox	The amount of adjustments is 0. [File Name] [Function Name] [Error Code]	The amount of position adjustment is set to 0 (zero).	Manually adjust the positioning amount from the trimming dialog.	
42299	FFQAMsgBox	Data resource access error. [File Name] [Function Name] [Error Code]	A clustering resource access error (processing can be continued).	Check network connection status.	
43000	FFQAManagerCom	%S	Information for development personnel.	There are operational problems.	A character string is placed in the “%S” position.
43010	FFIIPInImgCtrl	Can’t Get FontSize Information.	The font size was not registered in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
43010	FFQAManagerCom	Can’t Get FontSize Information.	The font size was not registered in the registry.	Reinstall the IIP because the displayed characters can be corrupted.	
43020	FFIIPInImgCtrl	Can’t Get Caption Information.	The character string database did not exist or was damaged.	Reinstall the IIP because the displayed characters can be corrupted.	
43060	FFQAManagerCom	[Control: %1, Function: %2 , Code: %3]	The character string database did not exist or was damaged.	Reinstall the IIP because the displayed characters can be corrupted.	
43061	FFQAManagerCom	[Control: %1, Function: %2 , Code: %3]	The character string database did not exist or was damaged.	Reinstall the IIP because the displayed characters can be corrupted.	
43062	FFQAManagerCom	[Control: %1, Function: %2 , Code: %3]	The character string database did not exist or was damaged.	Reinstall the IIP because the displayed characters can be corrupted.	
43063	FFQAManagerCom	[Control: %1, Function: %2 , Code: %3]	The character string database did not exist or was damaged.	Reinstall the IIP because the displayed characters can be corrupted.	
43064	FFQAManagerCom	[Control: %1, Function: %2 , Code: %3]	The character string database did not exist or was damaged.	Reinstall the IIP because the displayed characters can be corrupted.	
43110	FFIIPInImgCtrl	Can’t Access Local Configuration Data.	The language setup data was not obtained.	Reinstall the IIP because the displayed characters can be corrupted.	
43201	FFIIPQACtrl	Focus Set Failure.	The focus cannot be determined properly.	There is no particular problem with operations. (The focus cannot be determined properly because the annotation character input dialog has been inactivated.) After shutting the magnification function, input of annotation characters becomes possible.	
43301	FFQAManagerCom	[Control: %1, Function: %2 , Code: %3]	The screen size was not obtained.	Reinstall the IIP because the displayed characters can be corrupted.	
43310	FFQAManagerCom	[Control: %1, Function: %2 , Code: %3]	The language setup data was not obtained.	Reinstall the IIP because the displayed characters can be corrupted.	
44200	FFQAMsgBox	Journal Proc Failure. [File Name] [Function Name] [Error Code]	The method return value for the log storage control resulted in an error.	Restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
44201	FFQAMsgBox	An unexpected Method call. [File Name] [Function Name] [Error Code]	An unexpected method call (called up at an impossible timing, being possible though to continue processing).	Restart the system.	
44354	FFCustomMsgBox	[44354] Invalid character has been input in ID #.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44355	FFCustomMsgBox	[44355] Invalid character has been input in Study #.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44356	FFCustomMsgBox	[44356] Invalid character has been input in patient name.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44357	FFCustomMsgBox	[44357] Invalid character has been input in kanji-patient name.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44358	FFCustomMsgBox	[44358] Invalid character has been input in the sex (gender).	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44359	FFCustomMsgBox	[44359] Format of date of birth is not applicable.	The entry did not agree with the date format defined by system setup.	Make a proper entry.	
44360	FFCustomMsgBox	[44360] The same study No. already exists.	An attempt was made to enter an examination number that was already used.	Enter another number.	
44361	FFCustomMsgBox	[44361] Anatomical region has not been input.	An anatomical region name was not entered.	Make a proper entry.	
44362	FFCustomMsgBox	[44362] Invalid character has been input in the anatomical region.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44363	FFCustomMsgBox	[44363] Invalid character has been input in the kanji-anatomical region.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44364	FFCustomMsgBox	[44364] No menu name has been input.	A menu name was not entered.	Make a proper entry.	
44365	FFCustomMsgBox	[44365] Invalid character has been input in the menu name.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44366	FFCustomMsgBox	[44366] Invalid character has been input in the kanji-menu name.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44367	FFCustomMsgBox	[44367] Invalid character has been input in the film annotation characters.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	

Event	Event Source	Description	Causes	Remedies	Remarks
44368	FFCustomMsgBox	[44368] No patient information has been input.	The patient information was not entered.	Make a proper entry.	
44369	FFCustomMsgBox	[44369] The Study ID contained an invalid character.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
44551	FFCustomMsgBox	[44551] Film format will be changed.	This window opens for confirmation only.		
49200	FFQAMsgBox	FF32 Error. [File Name] [Function Name] [Error Code]	The return value for the FF32 library (FF32.dll) resulted in an error (irreplaceable).	Restart the system.	
49201	FFQAMsgBox	Method Argument Error. [File Name] [Function Name] [Error Code]	A method argument type error (for instance, there were no objects).	Restart the system.	
49202	FFQAMsgBox	Can't get Tag Information. [File Name] [Function Name] [Error Code]	No tag information was set up though it must have been set up beforehand (irreplaceable).	Restart the system.	
49203	FFQAMsgBox	Memory or Resource cannot be gained. [File Name] [Function Name] [Error Code]	Failed in acquiring memory/handle resources.	Restart the system.	
49204	FFQAMsgBox	Windows API error occurred. [File Name] [Function Name] [Error Code]	Windows API return value resulted in an error.	Restart the system.	
49298	FFQAMsgBox	Secondary detection code Error. [File Name] [Function Name] [Error Code]	An error occurred with the return value of the secondary detection code.	Restart the system.	
49299	FFQAMsgBox	Exception Error occurred. [File Name] [Function Name] [Error Code]	An exceptional error (an error detected with Try/Catch, OnErrorGoto).	Restart the system.	
50000	FFFinpSend	Memory Error.%n%1	The system was abnormal (memory allocation was not accomplished).	Restart.	
50000	FFOutImgPrc	Initialize Error.%n%1	An abnormality was encountered during initialization.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50001	FFCustomMsgBox	[50001] Failed in initialization process.	- Output option setup was not completed. - The system was unstable.	- Perform output option setup. - Restart. If the same symptom recurs, perform a reinstallation.	
50001	FFFinpSend	Dicom Data Object Load Error.%n%1	The DicomDataObject file for output was not found.	Perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
50001	FFIIPOUTPUT	Initialize Error.%n[%1]	Initialization process error. • Output control was not exercised. • The error check method was not successfully called. • A certain other program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation.	
50001	FFOutImgPrc	DB Connect Error.%n%1	An abnormality occurred in the connection to a database.	Check whether the SQL service manager is normally operating. If the same symptom occurs while the SQL service manager is normally operating, initialize the image database (the entire image data is then deleted).	
50001	Spooler	Initialize Error.%n[%1]	Initialization process error. • No output control was exercised. • An error check method call was unsuccessful. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation.	Output section container.
50002	FFCustomMsgBox	[50002] Failed in output process.	The system was unstable.	Restart. If the same symptom recurs after a restart, perform a reinstallation.	
50002	FFFinpSend	File Open Error.%n%1	There is no output raw data file.	Reinstall.	
50002	FFIIPOUTPUT	State Change Error.%n[%1]	State transition notification process error. • The output destination was not successfully reregistered. • The state transition notification call was not successful. • An unknown program error occurred.	Restart.	
50002	FFOutImgPrc	DB Information Error.%n%1	The database information was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50002	Spooler	State Change Error.%n[%1]	State change notification process error. • An output destination was not successfully registered. • A state change notification call was not successful. • Other program error. • Line establishment message transmission error [not used]. • Line abnormality message transmission error [not used].	Restart.	Output section container.
50003	FFCustomMsgBox	[50003] Failed in output process.	The system was unstable.	Restart. If the same symptom recurs after a restart, perform a reinstallation.	
50003	FFFinpSend	File Read Error.%n%1	The output raw data file is abnormal.	Reinstall.	

Event	Event Source	Description	Causes	Remedies	Remarks
50003	FFIIPOUTPUT	Routine Change Error.%n[%1]	Routine change process error. • The resumption request was not successfully made.	Restart.	
50003	FFOutImgPrc	System Error.%n%1	The system was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50003	Spooler	Routine Change Error.%n[%1]	Routine change process error. • A resumption request was not successfully made.	Restart.	Output section container.
50004	FFCustomMsgBox	[50004] Failed in output process.	- An exposure menu name with an apostrophe was used with software version A07 or earlier. - The system was unstable.	- Upgrade the software to version A08 or later. - Restart. If the same symptom recurs, perform a reinstallation.	
50004	FFFinpSend	FinpSend Error.%n%1	An abnormality occurred in the output sequence.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50004	FFIIPOUTPUT	Spool Error.%n[%1]	Spool process error. • The spool request call was not successfully made. • The reoutput request was not successfully made. • The study termination notification was not successfully made. • The spool request response status was invalid. • An unknown program error occurred.	Restart.	
50004	FFOutImgPrc	I/F Timing Error.%n%1	An interface abnormality was encountered.	Restart.	
50004	Spooler	Spool Error.%n[%1]	Spool process error. • A spool request call was not successfully made. • A reoutput request was not successfully made. • An examination end notification was not successful. • The spool request response state was illegal. • Other program error.	Restart.	Output section container.
50005	FFCustomMsgBox	[50005] Failed in output process.	The system was unstable.	Restart. If the same symptom recurs after a restart, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
50005	FFIIPOUTPUT	ExeOutput Error.%n[%1]	Forced-output process error. • The spool forced output request call was not successfully made. • The queue forced output response message was not successfully transmitted. • An unknown program error occurred.	Restart.	
50005	FFOutImgPrc	CreateFileMapping Error.%n%1	File mapping was unachievable.	Restart.	
50005	Spooler	ExeOutput Error.%n[%1]	Forced output process error. • A spool forced output request was not successfully called. • A queue forced output response message was not successfully transmitted. • Other program error.	Restart.	Output section container.
50006	FFCustomMsgBox	[50006] Failed in output process.	The system was unstable.	Restart. If the same symptom recurs after a restart, perform a reinstallation.	
50006	FFIIPOUTPUT	Image Proc Error.%n[%1]	Image processing error. • The image processing request call was not successfully made. • The image processing setup completion call was not successfully made. • The image processing completion notification call was not successfully made. • The image processing job acquisition request was not successfully made. • An unknown program error occurred.	Restart.	
50006	FFOutImgPrc	File Open Error.%n%1	The file could not be opened.	Check the file.	
50007	FFCustomMsgBox	[50007] Failed in terminating process.	The system was unstable.	Restart. If the same symptom recurs after a restart, perform a reinstallation.	
50007	FFIIPOUTPUT	Output Proc Error.%n[%1]	Output processing error. • The output destination information was not successfully acquired. • The output request call was not successfully made. • The output completion notification was not successfully made. • An unknown program error occurred.	Restart.	
50007	FFOutImgPrc	File Read/Write Error.%n%1	A file write/read was unsuccessful. The problem is attributable to a disk.	If the problem frequently occurs, replace the disk or take some other remedial action.	

Event	Event Source	Description	Causes	Remedies	Remarks
50007	Spooler	Terminate Error.%n[%1]	Termination process error. • Other program error.	Restart.	Output section container.
50008	FFCustomMsgBox	[50008] Failed in image processing for output.	The system was unstable.	Restart. If the same symptom recurs after a restart, perform a reinstallation.	
50008	FFIIPOUTPUT	Commit Proc Error.%n[%1]	Commitment processing error. • The commitment destination information was not successfully acquired. • The commitment request call was not successfully made. • The commitment completion notification was not successfully made. • An unknown program error occurred.	Restart.	
50008	FFOutImgPrc	CreateDispatch Error.%n%1	The control was not successfully initialized.	Check that the control is registered.	
50008	Spooler	Image Proc Error.%n[%1]	Image process error. • An image process request was not successfully called. • An image process setup completion call was not successfully made. • An image process completion notification was not successfully called. • An image process job acquisition request was not successfully issued. • Other program error.	Restart.	Output section container.
50009	FFCustomMsgBox	[50009] Failed in output process.	The system was unstable.	Restart. If the same symptom recurs after a restart, perform a reinstallation.	
50009	FFIIPOUTPUT	Queue Resume Error.%n[%1]	Queue resumption process error. • The queue resumption request call was not successfully made. • The queue resumption response message was not successfully transmitted. • An unknown program error occurred.	Restart.	
50009	FFOutImgPrc	Memory Get Error.%n%1	The system was abnormal (memory allocation was not achieved).	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
50009	Spooler	Output Proc Error.%n[%1]	Output process error. • Output destination information was not successfully acquired. • An output request was not successfully called. • An output completion notification was not successful. • Other program error.	Restart.	Output section container.
50010	FFIIPOUTPUT	Queue Delete Error.%n[%1]	Queue deletion process error. • The queue deletion request was not successfully made. • The queue deletion response message was not successfully transmitted. • An unknown program error occurred.	Restart.	
50010	FFOutImgPrc	Memory(DDO) Get Error.%n%1	The system was abnormal (memory allocation was not achieved).	Restart.	
50010	Spooler	Queue Resume Error.%n[%1]	Queue resumption process error. • A queue resumption request was not successfully called. • A queue resumption response message was not successfully transmitted. • Other program error.	Restart.	Output section container.
50011	FFIIPOUTPUT	Unit Suspend Error.%n[%1]	Equipment output suspension process error. • The equipment output suspension request call was not successfully made. • The equipment output suspension response message was not successfully transmitted. • An unknown program error occurred.	Restart.	
50011	FFOutImgPrc	Memory(VR) Get Error.%n%1	The system was abnormal (memory allocation was not achieved).	Restart.	
50011	Spooler	Queue Delete Error.%n[%1]	Queue deletion process error. • A queue deletion request was not successfully issued. • A queue deletion response message was not successfully transmitted. • Other program error.	Restart.	Output section container.

Event	Event Source	Description	Causes	Remedies	Remarks
50012	FFIIPOUTPUT	Unit Resume Error.%n[%1]	Equipment output resumption error. • The equipment output resumption request call was not successfully made. • The equipment output resumption response message was not successfully transmitted. • An unknown program error occurred.	Restart.	
50012	FFOutImgPrc	Dicom Data Object Error.%n%1	Dicom Data Object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50012	Spooler	Unit Suspend Error.%n[%1]	Unit output suspension process error. • A unit output suspension request was not successfully called. • A unit output suspension response message was not successfully transmitted. • Other program error.	Restart.	Output section container.
50013	FFOutImgPrc	Dicom Data Object No Data.%n%1	Dicom Data Object did not contain any data.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50013	Spooler	Unit Resume Error.%n[%1]	Unit output resumption process error. • A unit output resumption request was not successfully called. • A unit output resumption response message was not successfully transmitted. • Other program error.	Restart.	Output section container.
50015	FFIIPOUTPUT	Terminate Error.%n[%1]	Termination process error. • An unknown program error occurred.	Restart.	
50020	FFOutImgPrc	Data Error.%n%1	A data abnormality was encountered.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50021	FFOutImgPrc	Output Job DB Error.%n%1	The output database was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50022	FFOutImgPrc	Memory Over.%n%1	A memory area abnormality was encountered.	Restart.	
50030	FFOutImgPrc	OutImgPrc Error.%n%1	An abnormality occurred.	Restart.	
50100	FFOutImgPrc	IFormatCom Error.%n%1	The format calculation object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	

Event	Event Source	Description	Causes	Remedies	Remarks
50100	Spooler	Spooler Error.%n%1	Common error message. • Queue information class related message. An output job file was not successfully accessed. Output job information was not successfully accessed. Film information was not successfully acquired. Information was not successfully acquired. The job status was not successfully acquired (program error). Job information was not successfully freed. • Unit information class related message. Unit information was not successfully freed. • Spooler class related message. The film count was not successfully checked. The image count/image information area was not successfully acquired. Unit information was not successfully acquired. • Other program error	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50101	FFOutImgPrc	IRawMakeCom Error.%n%1	The raw data creation object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50101	Spooler	RunProc Error.%n%1	Initialization process error. • The spooler control state was abnormal. • A spool start process was in error. • A database connection was not successfully closed. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50102	FFOutImgPrc	FFNetDB Error.%n%1	An abnormality occurred at the time of network setup data acquisition. (It is conceivable that the network setup database was abnormal.)	Restart. If the same symptom frequently occurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
50102	Spooler	OutputRegisterProc Error.%n%1	Output destination registration process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • An output destination registration request message was not successfully issued. • An output destination was not successfully registered. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50103	FFOutImgPrc	IImgJpegCtrl Error.%n%1	The decompression object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50103	Spooler	StateChangeProc Error.%n%1	Local printer/Dicom printer state change notification process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • A printer state change notification message was not successfully issued. • The unit status was not successfully acquired. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50104	FFOutImgPrc	IFMImgSkGpCtrl Error.%n%1	The normalization process object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50104	Spooler	ErrorCheckProc Error.%n%1	Data integrity check process error. • The spooler control state was abnormal. • A data integrity check request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50105	FFOutImgPrc	IFMImgVRSCtrl Error.%n%1	The zoom object (VRS method) was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50105	Spooler	RestoreJob Error.%n%1	Job restoration error. • The spooler control state was abnormal. • An unprocessed job restoration request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50106	FFOutImgPrc	IRotateCom Error.%n%1	The rotation object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	

Event	Event Source	Description	Causes	Remedies	Remarks
50106	Spooler	SpoolProc Error.%n%1	Spool process error. • The spooler control state was abnormal. • A parameter error occurred. • A spool request message was not successfully issued. • DDO file information was not successfully acquired. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50107	FFOutImgPrc	IFMImgParamCtrl Error.%n%1	The image process management parameter object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50107	Spooler	ReoutputProc Error.%n%1	Reoutput start process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • A reoutput start message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50108	FFOutImgPrc	IFMImgHandCtrl Error.%n%1	The CR image process object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50108	Spooler	StudyReqEndProc Error.%n%1	Study termination request processing error. • Spooler control status error. • Illegal parameters. • Failed in issuing study termination request message. • Other program errors.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50109	FFOutImgPrc	IFMImgFCmpCtrl Error.%n%1	FCR compression (compression/ decompression (Fuji's unique method)) was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50109	Spooler	ExeOutputJob Error.%n%1	Forced output request process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • A forced output request message was not successfully issued. • The requested output image data did not exist. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50110	FFOutImgPrc	IDataToPrintCom Error.%n%1	Data conversion (for DICOM) was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	

Event	Event Source	Description	Causes	Remedies	Remarks
50110	Spooler	GetImageProcJob Error.%n%1	Image processing job acquisition process error. • The spooler control state was abnormal. • An image processing job acquisition request message was not successfully issued. • Data was not databased. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50111	FFOutImgPrc	IDataToStorageCom Error.%n%1	Data conversion (for DICOM Storage) was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50111	Spooler	SetImageProcComplete Error.%n%1	Image processing completion notification process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • An image processing completion notification message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50112	FFOutImgPrc	IFMImgMoireCtrl Error.%n%1	Moire elimination was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50112	FFQCMsgBox	Custom DB Access Error. [File Name] [Function Name] [50112]	Access error to ReaderQC.mdb.	Restart.	
50112	Spooler	GetOutputProcJob Error.%n%1	Output job acquisition response process error. • The spooler control state was abnormal. • An output job acquisition response message was not successfully issued. • Data was not databased. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50113	FFOutImgPrc	IFilmCharMakeCom Error.%n%1	The film annotation character generation object was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50113	Spooler	SetOutputProcComplete Error.%n%1	Output completion notification process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • An output completion notification message was not successfully issued. • Data was not databased. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler

Event	Event Source	Description	Causes	Remedies	Remarks
50114	FFOutImgPrc	MaskProcExec Error.%n%1	The blackening process was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50114	Spooler	GetCommitProcJob Error.%n%1	Commitment job acquisition response process error. • The spooler control status was abnormal. • The commitment jog acquisition response message was not successfully issued. • The data was not found in the database. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50115	FFOutImgPrc	RecognizeProcExec Error.%n%1	The blackening automatic recognition process was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50115	Spooler	QueueResume Error.%n%1	Queue output resumption request process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • A queue output resumption request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50115	Spooler	SetCommitProcComplete Error.%n%1	Commitment completion notification process error. • The spooler control status was abnormal. • An illegal parameter was encountered. • The commitment completion notification message was not successfully issued. • The queue was not found. • The data was not found in the database. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50116	FFOutImgPrc	ExecMarker Error.%n%1	The marker imbedding process was abnormal.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50116	Spooler	QueueDelete Error.%n%1	Queue deletion request process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • A queue deletion request message was not successfully issued. • Output job file information was not successfully accessed. • Queue deletion was not successful. • Database access was not successful. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50117	FFOutImgPrc	ExecMarker Warning.%n%1	Information for software development personnel.	There is no problem with operations.	

Event	Event Source	Description	Causes	Remedies	Remarks
50117	FFOutImgPrc	LUTProcExec Error.%n%	An error occurred in a display gradation correction process.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50117	Spooler	QueueResume Error.%n%1	Queue output resumption request process error. • The spooler control status was abnormal. • An illegal parameter was encountered. • The queue output resumption request message was not successfully issued. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50117	Spooler	UnitSuspend Error.%n%1	Unit suspension request process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • A unit suspension request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50118	FFOutImgPrc	ExecMarker Information.%n%1	Information for software development personnel.	There is no problem with operations.	
50118	FFOutImgPrc	MPMCode Error.%n%1	An error occurred in an output information conversion process.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50118	Spooler	QueueDelete Error.%n%1	Queue deletion request process error. • The spooler control status was abnormal. • An illegal parameter was encountered. • Failed in issuing a queue deletion request message. • Failed in accessing the output job file information. • Failed in deleting the queue. • Failed in accessing the database. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50118	Spooler	UnitResume Error.%n%1	Unit resumption request process error. • The spooler control state was abnormal. • An illegal parameter was encountered. • A unit resumption request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50119	Spooler	SuspendProc Error.%n%1	Suspension request process error. • The spooler control state was abnormal. • A suspension request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler

Event	Event Source	Description	Causes	Remedies	Remarks
50119	Spooler	UnitSuspend Error.%n%1	Equipment suspension request process error. • The spooler control status was abnormal. • An illegal parameter was encountered. • The equipment suspension request message was not successfully issued. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50119	FFOutImgPrc	Trimming Error.%n%1	An error occurred while in trimming processing.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50120	Spooler	ResumeProc Error.%n%1	Resumption request process error. • The spooler control state was abnormal. • A resumption request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50120	Spooler	UnitResume Error.%n%1	Equipment resumption request process error. • The spooler control status was abnormal. • An illegal parameter was encountered. • The equipment resumption request message was not successfully issued. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50120	FFOutImgPrc	AnnotationProc Error.%n%1	An error occurred while in annotation information embedding processing.	Restart. If the same symptom frequently occurs, perform a reinstallation and then intialize the image database.	
50121	Spooler	EndProc Error.%n%1	End request process error. • The spooler control state was abnormal. • An end request message was not successfully issued. • Other program error.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
50121	Spooler	SuspendProc Error.%n%1	Suspension request process error. • The spooler control status was abnormal. • The suspension request message was not successfully issued. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50121	FFOutImgPrc	FNCProc Error.%n%1	An error occurred during FNC processing.	Restart. If the same symptom recurs, perform reinstallation and initialize the image database.	

Event	Event Source	Description	Causes	Remedies	Remarks
50122	Spooler	ResumeProc Error.%n%1	Resumption request process error. • The spooler control status was abnormal. • The resumption request message was not successfully issued. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50123	Spooler	EndProc Error.%n%1	Termination request process error. • The spooler control status was abnormal. • The termination request message was not successfully issued. • An unknown program error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
50400	FFQCAutoCalcCom	File %1, Spot %2, Code %3.	Fatal Error (exceptional error)		
50500	FFQCAutoCalcCom	File %1, Spot %2, Code %3.	Fatal Error (exceptional error)		
50600	FFlipMedia	Logical Program Error. %n	Program error.	Restart.	
50601	FFlipMedia	Catch Exception Error. %n	An unexpected exception error occurred.	Restart.	
50602	FFlipMedia	Out Of Memory Error. %n	Failed in securing necessary memory.	Restart.	
50603	FFlipMedia	Data Base Error. %n	An error occurred in the database.	Restart.	
50604	FFlipMedia	Not Initialize. %n	Initialization not performed.	Restart.	
50605	FFlipMedia	File I/O Error. %n	An error occurred while in file read processing.	Check to see if the image file is correct.	
50606	FFlipMedia	Create Instance Error. %n	Failed in creating COM component instance.	Restart.	
50607	FFlipMedia	Pipe Create Error. %n	Failed in creating a pipe.	Restart.	
50608	FFlipMedia	Pipe Create Error. %n	Failed in closing a pipe.	Restart.	
50609	FFlipMedia	The Demand Is Already Performing. %n	The relevant request cannot be accepted because it is now being implemented or other request is now being implemented.	Wait for a while and then re-implement as there is a process that is being now implemented.	
50610	FFlipMedia	Send Message Error. %n	Failed in transmitting a message (Send message failure).	Restart.	
50611	FFlipMedia	Unjust Event Reception. %n	An illegal event, such as inconsistency in AE name, was received.	Make sure that the network setting is correct.	
50612	FFlipMedia	Not FCR Image. %n	The selected study couldn’t be acquired because it didn’t include FCR images.	Make sure that the image file is correct.	
50613	FFlipMedia	AEMedia no entry. %n	No media that is for the determined AE is registered.	Make sure that the network setting is correct.	
50614	FFlipMedia	Resource Access Error. %n	A resource access error.	Restart.	
50615	FFlipMedia	Media Process End. %n	The media control process ended.	Nothing particular.	

Event	Event Source	Description	Causes	Remedies	Remarks
50616	FFlipMedia	UPSEvent Pipe Create Failure. %n	Failed in creating a named pipe for detection of power rupture.	Restart.	
50617	FFlipMedia	Attribute Error. %n	The attribute caused an error to occur.	Make sure that the network setting is correct.	
50618	FFlipMedia	Picture storage demand start failure. %n	Failed in starting a request for image storage.	Make sure that the image file is correct.	
50619	FFlipMedia	Picture get demand start failure. %n	Failed in starting a request for image acquisition.	Make sure that the image file is correct.	
50620	FFlipMedia	Send Message Error. %n	Message transmission error.	Restart.	
50621	FFlipMedia	Get Host Name Error. %n	An error occurred when acquiring a host name.	Restart.	
50622	FFlipMedia	Resistry Error. %n	Failed in operating a registry.	Restart.	
50623	FFlipMedia	DVDform.exe not exist. %n	The DVDForm.exe file did not exist.	Check the format function system setting.	
50624	FFlipMedia	DVDform.exe Start Error. %n	Failed in starting the DVDForm.exe file.	Check the format function system setting.	
50625	FFlipMedia	DVDform.exe. Operation Error. %n	An error occurred while operating the DVDForm.exe file.	Check the format function system setting.	
50626	FFlipMedia	Format end Error. %n	A format end detection error.	Check the format function system setting.	
50627	FFlipMedia	Media Format Error. %n	A media format failure.	Nothing particular.	
50628	FFlipMedia	Media Drive Type Error. %n	The media drive type was not correct.	Make sure that the network setting is correct.	
50629	FFlipMedia	BatFile not exist. %n	The bat file did not exist.	Restart.	
50630	FFlipMedia	MediaDB Restore Error. %n	An error occurred while in bat restore processing.	Restart.	
50631	FFlipMedia	MediaDB Store Error. %n	An error occurred while in bat store processing.	Restart.	
50632	FFlipMedia	Message Box Error. %n	An error occurred in the custom message box.	Nothing particular.	
50633	FFlipMedia	File Format Error. %n	The file format is not correct.	Nothing particular.	
50634	FFlipMedia	Can’t Terminate by Storrtrv busy. %n	The Terminate process was disabled because the thread was in operation or in process of finishing.	Wait for a while and then re-implement because there is a process in operation.	
50635	FFlipMedia	DDOFile Invalid. %n	An illegal image information file.	Nothing particular.	
50636	FFlipMedia	Reconstruction is Error. %n	An error occurred during data reconstruction processing.	Nothing particular.	
50637	FFlipMedia	Program Error. %n	Program error.	Restart.	
50638	FFlipMedia	File I/O Error. %n	File I/O error.	Restart.	
50639	FFlipMedia	Memory not allocated. %n	Memory securing error.	Restart.	
50640	FFlipMedia	Other Error. %n	Other errors.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
50641	FFlipMedia	ddo error. %n	Failed in image information processing.	Nothing particular.	
50642	FFlipMedia	Drive not Exist. %n	The specified drive did not exist.	Make sure that the network setting is correct.	
50643	FFlipMedia	Disk not Exist. %n	There was no disk in the specified drive.	Make sure that the network setting is correct.	
50644	FFlipMedia	Not Removable. %n	The specified drive was not for removable media.	Make sure that the network setting is correct.	
50645	FFlipMedia	Eject FALSE. %n	Media ejection failed.	Nothing particular.	
50646	FFlipMedia	Lock FALSE. %n	Media lock failed.	Nothing particular.	
50647	FFlipMedia	Unlock FALSE. %n	Media unlock failed.	Nothing particular.	
50648	FFlipMedia	Cannot get Freespace. %n	Failed in securing free space.	Nothing particular.	
50649	FFlipMedia	SaveDCMFile FALSE. %n	Failed in creating a DICOM format file.	Nothing particular.	
50650	FFlipMedia	SaveDDOFile FALSE. %n	Failed in creating an image information file.	Nothing particular.	
50651	FFlipMedia	Set invalid value. %n	No parameter values have been set up.	Restart.	
50652	FFlipMedia	Cannot make DICOMDIR. %n	Failed in creating DICOMDIR.	Replace the media.	
50653	FFlipMedia	Cannot create file. %n	CreateFile method error.	Restart.	
50654	FFlipMedia	Cannot mapping file. %n	CreateFileMapping method error.	Restart.	
50655	FFlipMedia	Cannot mapview of file. %n	MapViewOfFile method error.	Restart.	
50656	FFlipMedia	Cannot flushview of file. %n	MapViewOfFile method error.	Restart.	
50657	FFlipMedia	Not Found consistflag. %n	The file consistency flag was not found in DICOMDIR.	Make sure that the image file is correct.	
50658	FFlipMedia	Drive not Ready. %n	The drive was not ready for use.	Nothing particular.	
50659	FFlipMedia	File not Found. %n	The file did not exist.	Nothing particular.	
50660	FFlipMedia	Load DICOMDIR no use. %n	Failed in reading the media management file.	Make sure that the image file is correct.	
50661	FFlipMedia	Initialize failed. %n	Failed in initialization processing.	Restart.	
50662	FFlipMedia	Data not found. %n	No data available.	Make sure that the image file is correct.	
50663	FFlipMedia	DeleteFile failed. %n	Failed in deleting the file.	Make sure that the image file is correct.	
50664	FFlipMedia	Memory not allocated. %n	Failed in securing memory.	Restart.	
50665	FFlipMedia	File I/O Error. %n	A failure occurred in file reading processing.	Restart.	
50666	FFlipMedia	Buffer Error. %n	Failed in securing buffer.	Restart.	
50667	FFlipMedia	Get filesize failed. %n	Failed in acquiring the file size.	Restart.	
50668	FFlipMedia	Not set path. %n	No paths have been set.	Make sure that the network setting is correct.	

Event	Event Source	Description	Causes	Remedies	Remarks
50669	FFIipMedia	Incorrect image information. %n	Image information was not correct.	Make sure that the image file is correct.	
50670	FFIipMedia	FFGetString failed. %n	A failure occurred with the FFGetString function.	Restart.	
50671	FFIipMedia	DB COM create failed. %	A failure occurred in creation of a database instance.	Restart.	
50672	FFIipMedia	DB COM connect failed. %n	A failure occurred in connection of the database.	Restart.	
50673	FFIipMedia	DB COM close failed. %n	A failure occurred when releasing the database.	Restart.	
50674	FFIipMedia	ADO queryinterface failed. %n	A failure occurred in acquisition of the ADO interface.	Restart.	
50675	FFIipMedia	DB COM openrecordset failed. %n	Failed in acquiring a record set.	Restart.	
50676	FFIipMedia	DB COM updaterecordset failed. %n	Failed in updating the record.	Restart.	
50677	FFIipMedia	DB COM closerecordset failed. %n	Failed in releasing the record set.	Restart.	
50678	FFIipMedia	DB COM deleterecordset failed. %n	Failed in deleting the record.	Restart.	
50679	FFIipMedia	ADO setrecord failed. %n	Failed in setting up the ADO interface record.	Restart.	
50680	FFIipMedia	FFDicom2Internal failed. %n	A failure occurred with the FFDicom2Internal function.	Restart.	
50681	FFIipMedia	FFInternal2Output failed. %n	A failure occurred with the FFInternal2Output function.	Restart.	
50700	FFIIPDicomQR	Unknown Error. %n[Module] %1%n[Function] %2 %n[SpotCode]%3 %n[Ret]%4 %n[Description]%5	An error of unknown cause occurred.	Restart the system.	
50700	FFCustomMsgBox	[50700] An unknown error occurred.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
50701	FFIIPDicomQR	Logical Program Error. Exception has Occurred. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An exceptional error occurred. It is difficult to continue processing because it is a serious error.	Restart the system.	
50701	FFCustomMsgBox	[50701] Failed in initialization processing.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
50702	FFIIPDicomQR	Logical Program Error. Not Supported Case. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	The error that occurred is unsupported though it is within the supposed range. Processing cannot be continued because it is a serious error.	Restart the system.	
50703	FFIIPDicomQR	Initialization Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An initialization processing error.	Restart the system.	
50704	FFIIPDicomQR	UnInitialization Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A shutdown processing error.	Restart the system.	
50705	FFIIPDicomQR	System Configuration Information Acquisition Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A system setup acquisition error.	Shut down the system to make sure that system settings are correct.	
50706	FFIIPDicomQR	Network Configuration Information Acquisition Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A network setting acquisition error.	Shut down the system to make sure that system settings are correct.	
50707	FFIIPDicomQR	Resource (Message/String/ Bitmap etc.) Acquisition Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A resource (message, character string, BMP, etc.) acquisition error.	Restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
50708	FFIIPDicomQR	Registry Information Acquisition Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A registry setting acquisition error.	Restart the system.	
50709	FFIIPDicomQR	InterProcess Message Communication Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An error occurred during an inter-process message communication.	Restart the system.	
50710	FFIIPDicomQR	Database Access Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A database access error.	Restart the system.	
50711	FFIIPDicomQR	DDO Access Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A DDO file access error.	Restart the system.	
50720	FFIIPDicomQR	Query Processing Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A search processing error occurred. Processing cannot be continued because it is a serious error.	Restart the system.	
50721	FFIIPDicomQR	Queried Information Display Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A search result display error occurred. Processing cannot be continued because it is a serious error.	Restart the system.	
50740	FFIIPDicomQR	Retrieve Processing Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An acquisition processing error. Processing cannot be continued because it is a serious error.	Restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
50741	FFIIPDicomQR	Retrieved Image Display Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 n[Ret]%4 %n[Description] %5	An acquired image display error occurred. Processing cannot be continued because it is a serious error.	Restart the system.	
50742	FFIIPDicomQR	Retrieved Image Output Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An image delivery processing error occurred. Processing cannot be continued because it is a serious error.	Restart the system.	
50809	FFCustomMsgBox	[50809] An unknown anomaly was encountered.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
51001	FFIIPOUTPUT	Initialize Warning.%n[%1]	Initialization process warning. • The output equipment execution was not successfully started. • The output equipment name (AE name/ host name) was not successfully acquired (there was an inconsistency between the option and network settings). • The FFNET database was not successfully accessed.	Check the network settings. If any setting is incorrect, perform a reinstallation.	
51001	Spooler	Initialize Warning.%n[%1]	Initialization process warning. • An output device execution was not successfully started. • An output device name (AE name/host name) was not successfully acquired. • FFNETDB access was unsuccessful.	Restart. If the same symptom frequently occurs, perform a reinstallation.	Output section container.
51002	FFIIPOUTPUT	State Change Warning.%n[%1]	State transition notification process warning. • The response to an acquisition request was not successfully made.	Restart.	
51002	Spooler	State Change Warning.%n[%1]	State change notification process warning. • An acquisition request was not successfully answered.	Restart.	Output section container.

Event	Event Source	Description	Causes	Remedies	Remarks
51007	Spooler	Terminate Warning.%n[%1]	Termination process warning. • A process status flag was not successfully set. • A process termination response message was not successfully transmitted. • An abnormality occurrence notification message was not successfully transmitted. • A message box was not successfully displayed. • A spooler termination request was not successfully called. • A spooler control end request was not successfully called. • The spooler control end response state was abnormal. • An image process control end request was not successfully issued. • An output device control end request was not successfully issued. • The output device control end response state was abnormal.	Restart.	Output section container.
51010	FFCustomMsgBox	[51010] Specified device does not exist.	The setup data was incorrect or the equipment not started.	Reset the data or check the equipment.	
51011	FFCustomMsgBox	[51011] Failed in reading of the configuration file (TagLookup.ini).	The setup file format was incorrect or the file could not be read.	Check settings.	
51012	FFCustomMsgBox	[51012] Failed in reading of the gray level correction file.	The setup file format was incorrect or the file could not be read.	Check settings.	
51013	FFCustomMsgBox	[51013] Failed in output process.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
51015	FFIIPOUTPUT	Terminate Warning.%n[%1]	Termination process warning. • The process status flag was not successfully set. • The process termination response message was not successfully transmitted. • The abnormality occurrence notification message was not successfully transmitted. • The message box was not successfully opened. • The spooler termination request call was not successfully made. • The spooler control termination request call was not successfully made. • The spooler control termination response status was abnormal. • The image processing control termination request was not successfully made. • The output equipment control termination request was not successfully made. • The output equipment control termination response status was abnormal.	Restart.	
51300	FFCustomMsgBox	[51300] The measurement process cannot be performed.	The measurement process could not be performed because there was no image.	Make sure that the images are entered.	
51301	FFCustomMsgBox	[51301] The hard disk is full.	The remaining free space is insufficient.	Increase the free space and then perform the output process again.	
51302	FFCustomMsgBox	[51302] Failed in the image output process.	The image output process could not be performed because the host at the output destination was not running.	Start up the host at the output destination and then perform the output process again.	
51303	FFCustomMsgBox	[51303] The measurement process cannot be performed.	The measurement process could not be performed because images derived from different image readers are contained in a single study.	To perform the measurement process, use images that are derived from the same image reader.	
51304	FFCustomMsgBox	[51304] The measurement process cannot be performed.	All the images necessary for measurement process execution were not entered.	Make sure that the images are entered.	
51305	FFCustomMsgBox	[51305] The measurement process cannot be performed.	The measurement process can be performed only when the 1-Shot Phantom image size is 24×30cm or larger.	Check the 1-Shot Phantom image size and make an exposure again.	
51306	FFCustomMsgBox	[51306] The entered value is illegal.	The entered monitor dosage value was out of range.	Enter another value.	
51307	FFCustomMsgBox	[51307] The entered value is illegal.	The artifact setting was out of range.	Enter another value.	

Event	Event Source	Description	Causes	Remedies	Remarks
51308	FFCustomMsgBox	[51308] The entered value is illegal.	The burger phantom setting was out of range.	Enter another value.	
51309	FFCustomMsgBox	[51309] The entered value is illegal.	The wire mesh setting was out of range.	Enter another value.	
51310	FFCustomMsgBox	[51310] The data save process cannot be performed.	The save process could not be performed because there was no image.	Make sure that the images are entered.	
51311	FFCustomMsgBox	[51311] The measurement process cannot be performed.	The phantom position was invalid.	Ensure that the phantom is properly positioned for the IP, and then make an exposure again.	
51312	FFCustomMsgBox	[51312] Failed in the image output process.	The selected image was not found.	Select an image that can be output.	
51313	FFCustomMsgBox	[51313] The entered value is illegal.	The S-value setting was out of range.	Enter another value.	
51314	FFCustomMsgBox	[51314] The entered value is illegal.	The shading setting was out of range.	Enter another value.	
51315	FFCustomMsgBox	[51315] The entered value is illegal.	The image noise setting was out of range.	Enter another value.	
51316	FFCustomMsgBox	[51316] The entered value is illegal.	The sharpness setting was out of range.	Enter another value.	
51317	FFCustomMsgBox	[51317] The entered value is illegal.	The jitter setting was out of range.	Enter another value.	
51318	FFCustomMsgBox	[51318] The entered value is illegal.	The linearity setting was out of range.	Enter another value.	
51319	FFCustomMsgBox	[51319] The entered value is illegal.	The setting for accuracy of measurement was out of range.	Enter another value.	
51320	FFCustomMsgBox	[51320] Failed in accessing the image file.	The image file was not found.	Make sure that the images are entered.	
51321	FFCustomMsgBox	[51321] Failed in accessing the database. [ReaderQC]	The database could not be accessed.	Restart.	
51322	FFCustomMsgBox	[51322] Failed in the data save process.	The output file was not successfully created.	Perform the log output process again.	
51323	FFCustomMsgBox	[51323] An error of unknown cause occurred.		Restart. If the same symptom recurs, perform a reinstallation.	
51324	FFCustomMsgBox	[51324] The measurement process cannot be performed.	The measurement process could not be performed because images differing in reading pixel density coexisted.	Check the menu for a mixture of high- and standard-pixel density images, and then make an exposure again.	
51325	FFCustomMsgBox	[51325] The image is illegal.	The 1-Shot Phantom image was invalid.	Ensure that the phantom is properly positioned for the IP, and then make an exposure again.	
51326	FFCustomMsgBox	[51326] The measurement process cannot be performed.	The image reader name was not set for the image file.	Ensure that the name is properly set.	

Event	Event Source	Description	Causes	Remedies	Remarks
51501	FFCustomMsgBox	[51501] Failed in initialization processing.	An abnormality occurred during the initialization of the FINP input subsystem.	Processes other than FINP input can be performed.	
51502	FFCustomMsgBox	[51502] Descrepancy in settings.	The PRINT attribute output destination was not specified.	Specify the PRINT attribute output destination.	
51702	FFCustomMsgBox	[51702] Failed in displaying the study information list.	The search result includes illegal data.	Stop acquiring studies that include illegal information.	
51710	FFCustomMsgBox	[51710] Input information includes illegal characters.	Input information includes illegal data.	Input correct data.	
51711	FFCustomMsgBox	[51711] Input information exceeds the limit number of characters.	Input information includes illegal data.	Input correct data.	
51712	FFCustomMsgBox	[51712] The hit rate of searching for studies exceeded the limit value. Search processing is suspended.	The number of hit studies is many.	Narrow down the search conditions accordingly.	
51713	FFCustomMsgBox	[51713] Failed in searching study information.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
51714	FFCustomMsgBox	[51714] A network error occurred while in search of study information.	The network settings were inappropriate.	Check settings of network and other connected equipment.	
51715	FFCustomMsgBox	[51715] A timeout error occurred while in search of study information. No responses come from equipment targeted for search.	The network settings were inappropriate.	Check settings of network and other connected equipment.	
51717	FFCustomMsgBox	[51717] Information of equipment targeted for search cannot be found. Network settings may not be correct.	The network settings were inappropriate.	Check settings of network and other connected equipment.	
51718	FFCustomMsgBox	[51718] A communication error occurred while in search of study information.	The network settings were inappropriate.	Check settings of network and other connected equipment.	
51720	FFIIPDicomQR	Query Processing Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A search processing error occurred. Processing can be continued after the error is notified to the user as it is insignificant.	If the same error still recurs, restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
51721	FFIIPDicomQR	Queried Information Display Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A search result display error occurred. Processing can be continued after the error is notified to the user as it is insignificant.	If the same error still recurs, restart the system.	
51721	FFCustomMsgBox	[51721] Failed in processing to acquire studies.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
51722	FFCustomMsgBox	[51722] Failed in processing to acquire studies. Free hard disk space is not sufficient.	Free space on the hard disk is insufficient.	Increase free space on the hard disk appropriately.	
51723	FFCustomMsgBox	[51723] Failed in processing to acquire studies. Studies include images that cannot be displayed.	An acquired study includes illegal data.	Stop acquiring studies that include illegal information.	
51725	FFCustomMsgBox	[51725] Information of equipment targeted for image acquisition cannot be found. Network settings may not be correct.	Network settings were inappropriate.	Check settings of network and other connected equipment.	
51726	FFCustomMsgBox	[51726] A communication error occurred in an attempt to acquire studies.	Network settings were inappropriate.	Check settings of network and other connected equipment.	
51727	FFCustomMsgBox	[51727] A timeout error occurred while in process of study acquisition. No responses come from the equipment targeted for study acquisition.	Network settings were inappropriate.	Check settings of network and other connected equipment.	
51729	FFCustomMsgBox	[51729] Input information is not correct.	Input information includes illegal data.	Input correct information.	
51730	FFCustomMsgBox	[51730] An attempt is made to acquire a study generated by an unknown modality.	Acquired study information includes illegal data.	Stop acquiring studies that include illegal information.	
51731	FFCustomMsgBox	[51731] A study generated by an unknown modality was acquired.	Acquired information includes illegal data.	Stop acquiring studies that include illegal information.	
51732	FFCustomMsgBox	[51732] The hit rate of searching for studies exceeded the listed limit value.	The number of hit studies is many.	Narrow down the search conditions accordingly.	

Event	Event Source	Description	Causes	Remedies	Remarks
51740	FFIIPDicomQR	Retrieve Processing Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A study acquisition error occurred. Processing can be continued after the error is notified to the user as it is insignificant.	If the same error still recurs, restart the system.	
51741	FFIIPDicomQR	Retrieved Image Display Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An error occurred when displaying acquired images. Processing can be continued after the error is notified to the user as it is insignificant.	If the same error still recurs, restart the system.	
51742	FFIIPDicomQR	Retrieved Image Output Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A delivery processing error occurred. Processing can be continued after the error is notified to the user as it is insignificant.	If the same error still recurs, restart the system.	
51805	FFCustomMsgBox	[51805] Failed in image display processing. Some images cannot be displayed.	Acquired studies include illegal data.	Stop acquiring studies that include illegal information.	
51806	FFCustomMsgBox	[51806] Failed in image distribution processing.	Acquired studies include illegal data.	Stop acquiring studies that include illegal information.	
51810	FFCustomMsgBox	[51810] Information on the device targeted for image printout was not found. Network settings may possibly be incorrect.	Network settings were inappropriate.	Check settings of network and other connected equipment.	
52000	FFFinpSend	Warning.%n%1	Information for development personnel.	There is no problem with operations.	
52000	FFOutImgPrc	Warning.%n%1	Information for development personnel.	There is no problem with operations.	
52002	FFEifPrinter	SMCU Driver error. [%1]	An error occurred in the SMCU driver. The problem might have been caused, for instance, by data incompleteness or system instability.	Restart.	
52003	FFEifPrinter	EIFIMG Driver error. [%1]	An error occurred in the EIFIMG driver. It is conceivable that the system was unstable.	Restart.	
52004	FFEifPrinter	Received unexpected command. [%1]	An unknown command was received from the printer.	Check the log of communications with the connected printer or restart the printer/IIP.	
52006	FFEifPrinter	File Error. [%1]	The raw data file for output was not found.	Since the problem is attributable to a program error, try performing a reinstall.	
52100	FFQCMsgBox	Custom DB Access Error. [File Name] [Function Name] [50112]	The bitmap was not successfully acquired.	Check that the bitmap file is installed.	

Event	Event Source	Description	Causes	Remedies	Remarks
52100	Spooler	Spooler Warning.%n%1	Common warning message. • Queue information class related message. Image information (SOPInstanceUID) was not successfully acquired. The job status was not successfully acquired. • Spooler class related message. A database connection was not successfully closed. • Illegal image display format data.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52101	Spooler	RunProc Warning.%n%1	Initialization process warning. • A character string database connection was not successfully opened.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52102	FFQCMsgBox	SysConfig DB Access Failure (Processing continuation). [File Name] [Function Name] [52102]	An error/invalid value was encountered when an attempt was made to acquire a system setup database access API value.	Restart.	
52103	FFQCMsgBox	LangStr DB Access Failure (Processing continuation). [File Name] [Function Name] [52103]	An error occurred when an attempt was made to acquire a character string database access API value.	Restart.	
52103	Spooler	StateChangeProc Warning.%n%1	Local printer/Dicom printer state change notification process warning. • A unit state character string was not successfully acquired.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52105	FFQCMsgBox	FF32 Access Failure (Probably acquisition of Registry goes wrong) [File Name] [Function Name] [52105]	The FF32 library (FF32dll) return value was in error. * For option key registry acquisition, no error occurs even if the key is missing.	It is probable that the installation was not properly completed. Perform a reinstallation.	
52105	Spooler	RestoreJob Warning.%n%1	Job restoration warning. • An output job file was not successfully accessed.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52106	Spooler	SpoolProc Warning.%n%1	Spool process warning. • Unit information acquisition was not successful. • File deletion was not successful. • Queue cancellation was not successful. • Data was not successfully written into a log file.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler

Event	Event Source	Description	Causes	Remedies	Remarks
52108	FFQCMsgBox	Custom DB Access Failure (Processing continuation) [File Name] [Function Name] [52108]	An attempt to set/acquire a value from ReaderQC.mdb failed.	Restart.	
52108	Spooler	StudyReqEndProc Warning.%n%1	Examination end request process warning. • A database was not successfully accessed. • DDO file information was not successfully acquired.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52109	FFQCMsgBox	FF32 DB Access Failure (Processing continuation) [File Name] [Function Name] [52109]	Registry setup/acquisition failed (replaceable).	It is probable that the registry information was not properly installed. Perform a reinstallation.	
52109	Spooler	ExeOutputJob Warning.%n%1	Forced output request process warning. • DDO file information was not successfully acquired.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52110	FFQCMsgBox	FF32 DB Access Failure (Processing continuation) [File Name] [Function Name] [52110]	An image file access error occurred.	Since the image is valid, make an exposure again.	
52110	Spooler	GetImageProcJob Warning.%n%1	Image processing job acquisition process warning. • An output unit type parameter error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52112	Spooler	GetOutputProcJob Warning.%n%1	Output job acquisition response process warning. • An output unit type parameter error was encountered.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52114	Spooler	GetCommitProcJob Warning.%n%1	Commitment job acquisition response process warning. • A commitment equipment type parameter error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
52116	Spooler	QueueDelete Warning.%n%1	Queue deletion request process warning. • An image database flag was not successfully set. • The DDO file was not successfully deleted.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52117	Spooler	UnitSuspend Warning.%n%1	Unit suspension request process warning. • A unit status character string was not successfully acquired.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler

Event	Event Source	Description	Causes	Remedies	Remarks
52118	Spooler	QueueDelete Warning.%n%1	Queue deletion request process warning. • The image database flag was not successfully set. • The DDO file was not successfully deleted.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
52118	Spooler	UnitResume Warning.%n%1	Unit resumption request process warning. • A unit status acquisition error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
52119	Spooler	UnitSuspend Warning.%n%1	Equipment suspension request process warning. • The equipment status character string was not successfully acquired.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
52120	Spooler	UnitResume Warning.%n%1	Equipment resumption request process warning. • An equipment status acquisition error occurred.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	
52400	FFQCAAutocalccom	File %1, Spot %2, Code %3.	Warning information.	Perform reexposure and then measurement processing because the image is illegal.	
52500	FFQCAAutocalccom	File %1, Spot %2, Code %3.	Fatal error (exceptional error).		
52720	FFIIPDicomQR	Query Processing Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A search processing error occurred. Processing can be continued as it is insignificant.	If the same error still recurs, restart the system.	
52721	FFIIPDicomQR	Queried Information Display Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A search result display error occurred. Processing can be continued as it is insignificant.	If the same error still recurs, restart the system.	
52740	FFIIPDicomQR	Retrieve Processing Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A study acquisition error occurred. Processing can be continued as it is insignificant.	If the same error still recurs, restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
52741	FFIIPDicomQR	Retrieved Image Display Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An error occurred when displaying an acquired study. Processing can be continued as it is insignificant.	If the same error still recurs, restart the system.	
52742	FFIIPDicomQR	Retrieved Image Output Error. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	A delivery processing error occurred. Processing can be continued as it is insignificant.	If the same error still recurs, restart the system.	
52750	FFIIPDicomQR	Logical Program Error. %nNetwork Warning (Timeout). %n%1 %n %2	A timeout error occurred.	Shut down the system to ensure that network settings are correct. Make sure that other connected equipment is operating properly.	
52751	FFIIPDicomQR	Network Warning(Over Number Of Result). %n%1 %n %2	The number for hit results exceeded the upper limit.	Suspend search processing. Narrow down the search conditions to retry search processing.	
52760	FFTsSearchCondition	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52761	FFTsSearchCondition	DB Operation Status Warning. %n	A warning given when the database operation result status is illegal.	Restart the system.	
52770	FFMaSearchCOM	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52771	FFMaSearchCOM	Network Error. %n	A network error occurred.	Restart the system.	
52772	FFMaSearchCOM	Network Error. %n	The number for hit results exceeded the upper limit.	Restart the system.	
52800	FFIIPDicomQR	Network Warning(Timeout). %n%1 %n %2	A timeout error occurred.	Shut down the system to ensure that network settings are correct. Make sure that other connected equipment is operating properly.	
52801	FFIIPDicomQR	Network Warning(DiskFull). %n%1 %n %2	The hard disk is full.	Suspend acquisition of studies. Increase free space on the hard disk and then retry acquisition.	
52802	FFIIPDicomQR	Warning(Retrieve Image Nothing). %n%1 %n %2	The acquired study does not include images.	Make sure that other connected equipment retains correct study information.	
52810	FFTsImgRetInd	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52820	FFMaRetrieve	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52821	FFMaRetrieve	Storage SCP not found. %n	No Storage SCP is set up.	Restart the system.	
52822	FFMaRetrieve	Cannot Get NetWork Setting. %n	Necessary network settings cannot be acquired.	Restart the system.	
52823	FFMaRetrieve	Integration Warning in DataBase. %n	There is a problem with consistency of the database.	Restart the system.	
52824	FFMaRetrieve	DICOM Data Waring. %n	A DICOM data-related warning.	Restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
52825	FFMaRetrieve	Local Retrieve Warning. %n	A warning given when images cannot be acquired locally.	Restart the system.	
52826	FFMaRetrieve	Input Image Warning (DensityCode = SH). %n	A warning given when an SH image is input.	Restart the system.	
52850	FFMaCommon	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52851	FFMaCommon	Debug Log OutPut. %n	Event log output number for debugging purposes.	Restart the system.	
52852	FFMaCommon	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52860	FFMaCommonImage	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52870	FFTsCommon	Disk Full Error. %n	The hard disk is full.	Restart the system.	
52871	FFTsCommon	Catch DB exception. %n	An exceptional access to the database.	Restart the system.	
53106	Spooler	SpoolProc Infomation.%n%1	Information in a spool process. • Unit type mismatch notification.	Restart. If the same symptom frequently occurs, perform a reinstallation and then initialize the image database.	Spooler
53820	FFMaRetrieve	Retrieve Process Start. %n	Process startup.	Restart the system.	
53821	FFMaRetrieve	Retrieve Process End. %n	Process shutdown.	Restart the system.	
53823	FFMaRetrieve	Image is Already Exists in ImageDB. %n	Information given when the same image is input.	Restart the system.	
53870	FFTsCommon	Retry is success. %n	Database retry information.	Restart the system.	
54100	FFQCMsgBox	Journal Proc Failure. [File Name] [Function Name] [54100]	Writing error.	Check to see the media has not been prohibited for writing.	
54600	FFlipMedia	HDD Disk Full Error. %n	The HDD disk was full.	Secure sufficient HDD space by, for example, deleting unnecessary images.	
54601	FFlipMedia	Network Error. %n	An error occurred on the network.	Make sure that the network setting is correct.	
54602	FFlipMedia	Not Mount. %n	No destination has been mounted for data storage.	Mount the drive.	
54603	FFlipMedia	Media Ctrl(Format or Mount or Unmount)Run. %n	Media control (either of formatting, mounting and unmounting) was in process.	Retry after a while because either of formatting, mounting and unmounting is in process.	
54604	FFlipMedia	Media Read Only. %n	The media was for read only.	Nothing particular.	
54605	FFlipMedia	Media Unformat. %n	The media was not formatted.	Nothing particular.	
54606	FFlipMedia	Media Storage Is Operating. %n	Media storage was in process.	Retry after a while because there is a process in operation.	
54607	FFlipMedia	Message reception from other cases. %n	A message received from other equipment units.	Nothing particular.	
54608	FFlipMedia	ReceptionMessage is Abnormal. %n	The received message was not normal.	Restart.	

Event	Event Source	Description	Causes	Remedies	Remarks
54609	FFlipMedia	Next Transaction by Timeout. %n	The next processing started as a timeout occurred.	Nothing particular.	
54610	FFlipMedia	Media Is Already Mount. %n	The media has already been mounted.	Nothing particular.	
54611	FFlipMedia	Set Default by acquisition failure. %n	Default was set because a failure occurred during data acquisition from Directory.ini.	Nothing particular.	
54612	FFlipMedia	Media White Protect. %n	The media was write-protected.	Nothing particular.	
54613	FFlipMedia	DICOMDIR Read Only. %n	The DICOMDIR file was for read only.	Nothing particular.	
54614	FFlipMedia	Can't Format by DICOMDIRfile. %n	Formatting was not possible because there was the DICOMDIR file.	Nothing particular.	
54615	FFlipMedia	Not Browseable Media. %n	It was not browseable media.	Nothing particular.	
54616	FFlipMedia	Not Writeable Media. %n	It was not writable media.	Nothing particular.	
54617	FFlipMedia	No DICOMDIR Other Exist. %n	There was no DICOMDIR file but were other files.	Nothing particular.	
54618	FFlipMedia	DICOMDIR is mismatching. %n	The DICOM DIR file was mismatching.	Reconstruct the media.	
54619	FFlipMedia	Media no exist. %n	No media existed.	Nothing particular.	
54620	FFlipMedia	Mount User Cancel. %n	The user canceled mounting processing.	Nothing particular.	
54621	FFlipMedia	Version is Different. %n	The database version was different from that of the version file.	Nothing particular.	
54622	FFlipMedia	Media Diskfull. %n	The media disk was full.	Replace the media.	
54623	FFlipMedia	Image not exist in media. %n	Images for the requested study did not exist in the media.	Nothing particular.	
54624	FFlipMedia	Image can't get Exist by Error. %n	Images that couldn't be acquired due to an error existed in the acquired study.	Nothing particular.	
54625	FFlipMedia	Allcancel by Electric Power Stop. %n	Processing discontinued due to power rupture.	Restart.	
54626	FFlipMedia	DICOMDIR not Exist. %n	The DICOMDIR file did not exist.	Make sure that the image file is correct.	
54627	FFlipMedia	DICOMDIR is protected. %n	The management file was for read only or write-protected.	Nothing particular.	
54628	FFlipMedia	Unsuitable right format. %n	The media was unformatted or improperly formatted.	Nothing particular.	
54629	FFlipMedia	Cancellation demand. %n	Processing canceled as it was requested.	Nothing particular.	
54630	FFlipMedia	Reconstruction is not need. %n	The management file needs not to be reconstructed.	Nothing particular.	
54631	FFlipMedia	Disk Limit. %n	The free disk space available was not sufficient.	Secure sufficient HDD space by, for example, deleting unnecessary images.	
54632	FFlipMedia	Other File Exists (May I format?). %n	Files other than DICOMDIR existed. (Are you sure to format?)	Nothing particular.	

Event	Event Source	Description	Causes	Remedies	Remarks
54633	FFlipMedia	Push the O.K. button after inserting media. %n	Insert the media and press the OK button.	Nothing particular.	
54634	FFlipMedia	Finish Reconstruct. %n	Reconstruction finished.	Nothing particular.	
54635	FFlipMedia	Auto Mount Finished. %n	Auto mounting finished.	Nothing particular.	
54640	FFlipMedia	Other Information. %n,	Other information.	Nothing particular.	
59001	FFEifPrinter	System call has failed. [%1]	An error returned upon a WIN32 API function call. It is conceivable that the system was unstable.	Restart.	
59005	FFEifPrinter	Unable to setup timers. [%1]	An unknown timer event occurred. It is conceivable that the system was unstable.	Restart.	
59100	FFQCMsgBox	FF32 Error. [File Name] [Function Name] [59100]	An FF32 library (FF32.dll) return value error (irreplaceable).	It is possible that the registry information has not been installed correctly. Perform a reinstallation.	
59102	FFQCMshBox	Cant get Tag Information. [File Name] [Function Name] [59102]	No value is set up for the tag information even though it must have been set up accordingly (irreplaceable).	Perform reexposure because the image is illegal.	
59103	FFQCMsgBox	Memory or Resource cannot be gained. [File Name] [Function Name] [59103]	Failed in obtaining memory/handle resource.	Increase available resources and then retry.	
59198	FFQCMsgBox	Secondary detection code Error. [File Name] [Function Name] [59198]	A secondary detection code return value error.		
59701	FFIIPDicomQR	Logical Program Error. Exception has Occurred. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	An exceptional error occurred. Processing can be continued because it is insignificant.	If the same error still recurs, restart the system.	
59702	FFIIPDicomQR	Logical Program Error. Not Supported Case. %n[Module] %1 %n[Function] %2 %n[SpotCode] %3 %n[Ret]%4 %n[Description] %5	The error that occurred is unsupported though it is within the supposed range. Processing cannot be continued because it is insignificant.	If the same error still recurs, restart the system.	
59751	FFIIPDicomQR	Catch Exception Error. %n%1 %n %2	An exceptional error occurred unexpectedly.	Restart the system.	
59761	FFTsSearchCondition	Catch Exception Error. %n	An exceptional error occurred unexpectedly.	Restart the system.	
59762	FFTsSearchCondition	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
59763	FFTsSearchCondition	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
59771	FFMaSearchCOM	Catch Exception Error. %n	An unexceptional error occurred unexpectedly.	Restart the system.	
59772	FFMaSearchCOM	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	
59773	FFMaSearchCOM	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
59774	FFMaSearchCOM	Data Base Error. %n	A database error occurred.	Restart the system.	
59801	FFIIPDicomQR	Catch Exception Error. %n%1 %n %2	An exceptional error occurred unexpectedly.	Restart the system.	
59802	FFIIPDicomQR	Invalid Propaty Error. %n%1 %n %2	Illegal properties (AddIndicationMethod only).	Restart the system.	
59811	FFTsImgRetInd	Catch Exception Error. %n	An exceptional error occurred unexpectedly.	Restart the system.	
59812	FFTsImgRetInd	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	
59813	FFTsImgRetInd	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
59821	FFMaRetrieve	Catch Exception Error. %n	An exceptional error occurred unexpectedly.	Restart the system.	
59822	FFMaRetrieve	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	
59823	FFMaRetrieve	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
59824	FFMaRetrieve	Process Communication Error. %n	An error occurred in the communication control.	Restart the system.	
59825	FFMaRetrieve	Retrieve Process Exists. %n	A process was started double.	Restart the system.	
59826	FFMaRetrieve	Image is Already Exists in ImageDB. %n	Image input is disabled because the same image already exists in the image database.	Restart the system.	
59827	FFMaRetrieve	File Error. %n	A file error occurred.	Restart the system.	
59828	FFMaRetrieve	NetWork Error. %n	The association was disconnected due to a network error.	Restart the system.	
59829	FFMaRetrieve	Cannot Get NetWork Setting. %n	Necessary network settings cannot be acquired.	Restart the system.	
59830	FFMaRetrieve	DICOM Retrieve Timeout. %n	A timeout error occurred in an attempt to acquire a study.	Restart the system.	
59831	FFMaRetrieve	DICOM Retrieve is Not Able to Use Now. %n	DICOM acquisition processing is not available at present.	Restart the system.	

Event	Event Source	Description	Causes	Remedies	Remarks
59832	FFMaRetrieve	Processing Image is Deleted. %n	Processing is disabled because the image was deleted.	Restart the system.	
59851	FFMaCommon	Catch Exception Error. %n	An exceptional error occurred unexpectedly.	Restart the system.	
59852	FFMaCommon	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	
59853	FFMaCommon	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
59855	FFMaCommon	Catch Exception Error. %n	An exceptional error occurred unexpectedly.	Restart the system.	
59856	FFMaCommon	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	
59857	FFMaCommon	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
59861	FFMaCommonImage	Catch Exception Error. %n	An exceptional error occurred unexpectedly.	Restart the system.	
59862	FFMaCommonImage	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	
59863	FFMaCommonImage	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
59871	FFTsCommon	Catch Exception Error. %n	An exceptional error occurred unexpectedly.	Restart the system.	
59872	FFTsCommon	Out Of Memory Error. %n	An error occurred, which disabled the memory to be secured appropriately.	Restart the system.	
59873	FFTsCommon	Free Memory Error. %n	An error occurred, which disabled the memory to be released appropriately.	Restart the system.	
60000	FFCustomMsgBox	[60000] Failed in accessing the database.	- An apostrophe was used for exposure menu name setup with the user utility when the employed software version was A07 or earlier. - It is conceivable that the database file is damaged or deleted.	- Upgrade the software to version A08 or later. - Restart. If the same symptom recurs, perform a reinstallation.	
60002	FFCustomMsgBox	[60002] User Utility will be terminated.	There is no alternative but to exit the program due to the occurrence of an abnormality.	Restart. If the same symptom recurs, perform a reinstallation.	
60050	FFCustomMsgBox	[60050] Failed in accessing the character string database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60051	FFCustomMsgBox	[60051] Failed in accessing the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60052	FFCustomMsgBox	[60052] Failed in obtaining the registry information.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
60053	FFCustomMsgBox	[60053] Value of registry information is abnormal.	It is conceivable that the registry information was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60054	FFCustomMsgBox	[60054] Failed in obtaining the information from the character string database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60055	FFCustomMsgBox	[60055] Failed in obtaining the information from the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60056	FFCustomMsgBox	[60056] Failed in obtaining the information from the system setting file.	The setup file format was incorrect or the file could not be read.	Check settings.	
60057	FFCustomMsgBox	[60057] Failed in setting information to the system setting file.	The setup file format was incorrect or the file could not be read.	Check settings.	
60080	FFCustomMsgBox	[60080] Failed in obtaining the display group information.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60081	FFCustomMsgBox	[60081] Failed in obtaining the menu information.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60100	FFCustomMsgBox	[60100] Failed in obtaining the MPM code.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60114	FFCustomMsgBox	[60114] Failed in obtaining the XCON parameter.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60183	FFCustomMsgBox	[60183] Failed in accessing the technician information database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60184	FFCustomMsgBox	[60184] Failed in accessing the technician information database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60185	FFCustomMsgBox	[60185] Failed in obtaining the information from the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60203	FFCustomMsgBox	[60203] Failed in accessing the requesting department information database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60204	FFCustomMsgBox	[60204] Failed in accessing the requesting department information database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60205	FFCustomMsgBox	[60205] Failed in obtaining the information from the system setting database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60215	FFCustomMsgBox	[60215] Failed in accessing the film annotation database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
60216	FFCustomMsgBox	[60216] Failed in accessing the film annotation database.	It is conceivable that the database file was damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60251	FFCustomMsgBox	[60251] Image processing parameter data is abnormal.	The image processing parameter data is abnormal.	Check the image processing parameters.	
60260	FFCustomMsgBox	[60260] System has not been rebooted.	It is conceivable that the IIP executable file was damaged or deleted.	Reinstall.	
60300	FFCustomMsgBox	[60300] The option and the database do not agree with each other.	The menu data and the option do not agree with each other.	Install a menu that is suited to the option.	
60301	FFCustomMsgBox	[60301] Data storage resulted in a failure.	The database file may have been damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
60302	FFCustomMsgBox	[60302] Failed in deleting image data.	The database file may have been damaged or deleted.	Reinstall. If the same symptom recurs, perform a reinstallation.	
61060	FFCustomMsgBox	[61060] Wrong password has been input.	An incorrect password was entered.	The password is fixed at “1111”.	
61082	FFCustomMsgBox	[61082] No menu has been selected.	An attempt was made to start an editing or like operation without selecting any menu.	Complete a menu selection before initiating an editing or like operation.	
61083	FFCustomMsgBox	[61083] Already registered for displaying and cannot be deleted.	The menu could not be deleted because it was registered for display.	Clear the registration for display and then delete the menu.	
61084	FFCustomMsgBox	[61084] Already registered to the study menu and cannot be deleted.	The menu could not be deleted because it was registered for the examination menu.	Remove the target menu from the examination menu in advance.	
61085	FFCustomMsgBox	[61085] No menu was registered for a certain display group.	A certain display group was empty because no menu was registered for it.	No empty display group is allowed to exist. Register one or more menus for the display group or delete the display group.	
61090	FFCustomMsgBox	[61090] Invalid character has been input in the display group name.	The entered data was abnormal due, for instance, to the inclusion of an unacceptable character.	Make a proper entry.	
61093	FFCustomMsgBox	[61093] Display group will be deleted.	This window opens for confirmation only.		
61094	FFCustomMsgBox	[61094] Display group name is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61103	FFCustomMsgBox	[61103] Same extension menu code already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61106	FFCustomMsgBox	[61106] Same ANK exposure menu name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61109	FFCustomMsgBox	[61109] Same kanji-exposure menu name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	

Event	Event Source	Description	Causes	Remedies	Remarks
61110	FFCustomMsgBox	[61110] Extension menu code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61111	FFCustomMsgBox	[61111] ANK exposure menu name is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61112	FFCustomMsgBox	[61112] Kanji-exposure menu name is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61122	FFCustomMsgBox	[61122] MPM code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61125	FFCustomMsgBox	[61125] Same film annotation already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61130	FFCustomMsgBox	[61130] Device code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61131	FFCustomMsgBox	[61131] Film-related code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61132	FFCustomMsgBox	[61132] Auto-exposure mechanism is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61142	FFCustomMsgBox	[61142] Same study menu code already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61145	FFCustomMsgBox	[61145] Same ANK study menu name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61148	FFCustomMsgBox	[61148] Same kanji-study menu name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61149	FFCustomMsgBox	[61149] No exposure menu has been selected.	An attempt was made to start an editing or like operation without selecting any menu.	Complete a menu selection before initiating an editing or like operation.	
61151	FFCustomMsgBox	[61151] Exposure menu cannot be registered.	The maximum permissible number of menu registrations was exceeded.	Delete any unnecessary menu.	
61152	FFCustomMsgBox	[61152] Same exposure menu has already been registered.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61153	FFCustomMsgBox	[61153] Study menu code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61154	FFCustomMsgBox	[61154] ANK study menu code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	

Event	Event Source	Description	Causes	Remedies	Remarks
61155	FFCustomMsgBox	[61155] Kanji-study menu code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61171	FFCustomMsgBox	[61171] No technician code has been input.	An attempt was made to register data with an input field left blank.	Enter a value.	
61172	FFCustomMsgBox	[61172] Technician code is illegal.	The entered data was abnormal due, for instance, to its excessive length or the inclusion of an unacceptable character.	Make a proper entry.	
61173	FFCustomMsgBox	[61173] Invalid character has been input in the technician code.	An unacceptable character was contained.	Make a proper entry.	
61174	FFCustomMsgBox	[61174] Same technician code already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61175	FFCustomMsgBox	[61175] No ANK technician name has been input.	An attempt was made to register data with an input field left blank.	Enter a value.	
61176	FFCustomMsgBox	[61176] ANK technician name is too long.	The entered data was too long.	Make a proper entry.	
61177	FFCustomMsgBox	[61177] Invalid character has been input in the ANK technician name.	An unacceptable character was contained.	Make a proper entry.	
61178	FFCustomMsgBox	[61178] Same ANK technician name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61179	FFCustomMsgBox	[61179] No kanji-technician name has been input.	An attempt was made to register data with an input field left blank.	Enter a value.	
61180	FFCustomMsgBox	[61180] Kanji-technician name is too long.	The entered data was too long.	Make a proper entry.	
61181	FFCustomMsgBox	[61181] Invalid character has been input in the kanji-technician name.	An unacceptable character was contained.	Make a proper entry.	
61182	FFCustomMsgBox	[61182] Same kanji-technician name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61191	FFCustomMsgBox	[61191] No requesting department code has been input.	An attempt was made to register data with an input field left blank.	Enter a value.	
61192	FFCustomMsgBox	[61192] Requesting department code is too long.	The entered data was too long.	Make a proper entry.	
61193	FFCustomMsgBox	[61193] Invalid character has been input in the requesting department code.	An unacceptable character was contained.	Make a proper entry.	

Event	Event Source	Description	Causes	Remedies	Remarks
61194	FFCustomMsgBox	[61194] Same requesting department code already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61195	FFCustomMsgBox	[61195] No ANK requesting department name has been input.	An attempt was made to register data with an input field left blank.	Enter a value.	
61196	FFCustomMsgBox	[61196] ANK requesting department name is too long.	The entered data was too long.	Make a proper entry.	
61197	FFCustomMsgBox	[61197] Invalid character has been input in the ANK requesting department name.	An unacceptable character was contained.	Make a proper entry.	
61198	FFCustomMsgBox	[61198] Same ANK requesting department name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61199	FFCustomMsgBox	[61199] No kanji-requesting department name has been input.	An attempt was made to register data with an input field left blank.	Enter a value.	
61200	FFCustomMsgBox	[61200] Kanji-requesting department name is too long.	The entered data was too long.	Make a proper entry.	
61201	FFCustomMsgBox	[61201] Invalid character has been input in the Kanji-requesting department name.	The entered data value was already registered or otherwise unacceptable.	Make a proper entry.	
61202	FFCustomMsgBox	[61202] Same kanji-requesting department name already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61211	FFCustomMsgBox	[61211] No film annotation characters have been input.	An attempt was made to register data with an input field left blank.	Enter a value.	
61212	FFCustomMsgBox	[61212] Film annotation characters are too long.	The entered data was too long.	Make a proper entry.	
61213	FFCustomMsgBox	[61213] Invalid character has been input in the film annotation characters.	An unacceptable character was contained.	Make a proper entry.	
61214	FFCustomMsgBox	[61214] Same film annotation already exists.	The entered data value was already registered or otherwise unacceptable.	Enter another value.	
61224	FFCustomMsgBox	[61224] Drive is not ready.	No FD was inserted into the FDD.	Insert an FD.	
61234	FFCustomMsgBox	[61234] Drive is not ready.	No FD was inserted into the FDD.	Insert an FD.	
61235	FFCustomMsgBox	[61235] Wrong disk	A wrong FD was inserted into the FDD.	Insert a correct FD.	
61236	FFCustomMsgBox	[61236] Wrong disk	A wrong FD was inserted into the FDD.	Insert a correct FD.	

Event	Event Source	Description	Causes	Remedies	Remarks
61300	FFCustomMsgBox	[61300] Backup processing resulted in a failure.	The database file may have been damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
61301	FFCustomMsgBox	[61301] Restore processing resulted in a failure.	The database file may have been damaged or deleted.	Restart. If the same symptom recurs, perform a reinstallation.	
61302	FFCustomMsgBox	[61302] An error of unknown cause occurred.	The system was unstable.	Restart. If the same symptom recurs, perform a reinstallation.	
61303	FFCustomMsgBox	[61303] Failed in importing the consumables database.	The problem is attributable, for instance, to a damaged file.	Prepare a consumables database again.	
61340	FFCustomMsgBox	[61340] A file backed up with another application cannot be restored.	An attempt was made to restore a backup made by the Viewer for use with the IIP or to restore a backup made by the IIP for use with the Viewer.	To restore to the IIP, use a backup file generated by the IIP. To restore to the Viewer, use a backup file generated by the Viewer.	
61341	FFCustomMsgBox	[61341] This is not a contrast medium database file.	A file other than Supply.mdb was selected for an import.	Select a Supply.mdb file.	
61342	FFCustomMsgBox	[61342] No backup files exist.	Specified drive or folder can be incorrect.	Specify a correct destination for data backup.	
64220	FFCustomMsgBox	[64220] Backup is interrupted.	This window opens for confirmation only.		
64221	FFCustomMsgBox	[64221] Backup is completed.	This window opens for confirmation only.		
64222	FFCustomMsgBox	[64222] Backup is being prepared.	This window opens for confirmation only.		
64223	FFCustomMsgBox	[64223] Insert FD.	This window opens for confirmation only.		
64230	FFCustomMsgBox	[64230] Restoring is interrupted.	This window opens for confirmation only.		
64231	FFCustomMsgBox	[64231] Restoring is completed.	This window opens for confirmation only.		
64232	FFCustomMsgBox	[64232] Being restored.	This window opens for confirmation only.		
64233	FFCustomMsgBox	[64233] Insert FD.	This window opens for confirmation only.		
64237	FFCustomMsgBox	[64237] Insert FD.	This window opens for confirmation only.		
64250	FFCustomMsgBox	[64250] Parameter Batch Updating	This window opens for confirmation only.		
64313	FFCustomMsgBox	[64313] Unable to obtain system configuration of the target destination for image data transfer.	The setup file format is not correct or cannot be read.	Check settings.	
64314	FFCustomMsgBox	[64314] Unable to obtain system configuration.	The setup file format is not correct or cannot be read.	Check settings.	

Event	Event Source	Description	Causes	Remedies	Remarks
64460	FFCustomMsgBox	[64460] File extension is not possible because the MPM code has reached its limit for extension.	The MPM code has reached its limit.	Allot existing MPM code or use extended MPM code.	
70000	FFCustomMsgBox	[70000] Failed in conversion of mis-exposure image log information.	It is possible that the RetakeAnalyisData.mdb file is write-protected.	Open the RetakeAnalysisData.mdb file properties to check to see if it is write-protected.	
70001	FFCustomMsgBox	[70001] Failed in deletion of log files.	It is possible that the RetakeAnalyisData.mdb file is write-protected.	Open the RetakeAnalysisData.mdb file properties to check to see if it is write-protected.	
70002	FFCustomMsgBox	[70002] Failed in accessing the definition file.	It is possible that the file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70005	FFCustomMsgBox	[70005] Connection to the system setting database resulted unsuccessful.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70006	FFCustomMsgBox	[70006] Failed in acquiring information from the system setting database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70007	FFCustomMsgBox	[70007] Connection to the character string database resulted unsuccessful.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70008	FFCustomMsgBox	[70008] Failed in acquiring information from the character string database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70009	FFCustomMsgBox	[70009] Failed in acquiring registry information.	It is possible that the registry information is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70010	FFCustomMsgBox	[70010] Failed in writing registry information.	It is possible that the registry information is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70011	FFCustomMsgBox	[70011] Failed in acquiring technologist information.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70012	FFCustomMsgBox	[70012] Failed in acquiring classifications of mis-exposure images.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70013	FFCustomMsgBox	[70013] Failed in acquiring comments on mis-exposure images.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70014	FFCustomMsgBox	[70014] Connection to the log information database resulted unsuccessful.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70015	FFCustomMsgBox	[70015] Failed in acquiring information for setup of mis-exposure image analysis.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	

Event	Event Source	Description	Causes	Remedies	Remarks
70016	FFCustomMsgBox	[70016] Failed in reading image files.	It is possible that the image file is damaged or deleted.	Although the image file in question is not displayed, there are no problems with other operations.	
70017	FFCustomMsgBox	[70017] Failed in displaying images.	An error occurred while in image processing.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70019	FFCustomMsgBox	[70019] Failed in conversion of date format.	The date display format may have been input incorrectly.	Input in a correct format.	
70020	FFCustomMsgBox	[70020] Failed in storage of the mis-exposure image log list.	This error is displayed when a failure occurred in data storage.	Retry data store. If the same symptom recurs, change the destination for storage accordingly.	
70021	FFCustomMsgBox	[70021] Failed in storage of the calculation result.	This error is displayed when a failure occurred in data storage.	Retry data storage. If the same symptom recurs, change the destination for storage accordingly.	
70022	FFCustomMsgBox	[70022] An error occurred while an image is being displayed.	It is possible that the image display control or image file has a problem.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70023	FFCustomMsgBox	[70023] An unknown error occurred.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70024	FFCustomMsgBox	[70024] Connection to the database of regions to be exposed resulted unsuccessful.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70025	FFCustomMsgBox	[70025] Connection to the database of causes of mis-exposure images resulted unsuccessful.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70026	FFCustomMsgBox	[70026] Failed in calculation of the mis-exposure image log.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70027	FFCustomMsgBox	[70027] Failed in displaying calculation result of the mis-exposure image log.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70028	FFCustomMsgBox	[70028] Connection to the network setting database resulted unsuccessful.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70029	FFCustomMsgBox	[70029] Failed in acquiring necessary data from the network setting database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70030	FFCustomMsgBox	[70030] Failed in displaying the list.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70031	FFCustomMsgBox	[70031] Free hard disk space for writing data is insufficient.	The size of the file copied is too large to be accommodated in the media.	Replace for media of large capacity, if available.	

Event	Event Source	Description	Causes	Remedies	Remarks
70032	FFCustomMsgBox	[70032] Failed in deleting the mis-exposure image log.	It is possible that the file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70033	FFCustomMsgBox	[70033] Failed in deleting the exposure result log.	It is possible that the file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70034	FFCustomMsgBox	[70034] Failed in deleting an image file.	It is possible that the file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70035	FFCustomMsgBox	[70035] Failed in writing image data in the system setting database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70036	FFCustomMsgBox	[70036] Failed in writing image data in the display setting database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70037	FFCustomMsgBox	[70037] Failed in relocating the tree structure.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70038	FFCustomMsgBox	[70038] Failed in reducing the tree structure.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70039	FFCustomMsgBox	[70039] Transition to the main window resulted unsuccessful.	The system was unstable.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70040	FFCustomMsgBox	[70040] Failed in accessing the menu database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70041	FFCustomMsgBox	[70041] Failed in accessing the log information database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70042	FFCustomMsgBox	[70042] Failed in accessing the system setup database.	It is possible that the database file is damaged or deleted.	Restart the system. If the same symptom recurs, perform a reinstallation.	
70043	FFCustomMsgBox	[70043] Failed in storage of image data.	It is possible that the file is damaged or deleted. It is also possible that the target media for file storage has problems.	Retry file storage. If the same symptom recurs, perform a reinstallation.	
94001	FFCustomMsgBox	[94001] The scanner cleaning process was completed.	This window opens for confirmation only.		
94002	FFCustomMsgBox	[94002] The scanner cleaning process could not be performed.	Dust removal was unaccomplished due to a problem on the RU side.	Check the RU status.	

BLANK PAGE